



F&F Filipowski sp. j  
ul. Konstytucyjowa 79/81  
95-200 Pabianice, POLAND  
tel/fax 48 42 2270974  
e-mail: fif@fif.com.pl

## ZT-4

### STABILISED POWER SUPPLY transformer based



5 9 0 8 3 1 2 1 5 9 1 7 5 7

[www.fif.com.pl](http://www.fif.com.pl)

F&F products are covered by an 24 months warranty from date of purchase

#### PURPOSE

ZI is used to supply electrical and electronic equipment with an average power consumption, which require stable, filtered voltage independent of circuit voltage changes.

#### FUNCTIONING

-Due to the high frequency converter, some very sensitive radio or microprocessor can operate wrong. It is recommended that you install an additional filter OP-230 or LC between power supply and receiver. With increasing load above  $I_{max}$  supplier will stabilize the current, and output voltage. will decrease.

- The power supply is resistant to short-circuit.

- The power supply has a thermal fuse protection against overoverload value  $I_{max}$ . When congestion long-term power supply is automatically disconnected.


#### ASSEMBLY

1. Take OFF the power.
2. Power cable connect to input joints..
3. Receiver connet to output joints with marked polarity.

#### TECHNICAL DATA

supply $U_{in}$	180+264VAC
output voltage $U_{out}$	24V DC
output current	1A
power consumption	25W
keying frequency	52kHz
current limitation	$I_{max} = 110\%$ of output current
minimal load	0%
working temperature	-10+40°C
weight	742g
connection	screw terminals 2,5mm <sup>2</sup>
dimensions	6 modules (105mm)
fixing	on rail TH-35

#### WIRING DIAGRAM



A090813

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [DIN Rail Power Supplies](#) category:*

*Click to view products by [F&F](#) manufacturer:*

Other Similar products are found below :

[PS-3015](#) [PSP-480S48](#) [PSR-SD25](#) [PS-S6024](#) [DR-45-24](#) [DRP048V120W1BA](#) [DVP01PU-S](#) [DVP06AD-S](#) [DVP06XA-S](#) [DVDPNET-SL](#)  
[DVPDT01-S](#) [DVPPS01](#) [DVPPS02](#) [KHNA30F-5](#) [KHNA60F-24](#) [S8JX-G01524](#) [S8JX-G01548C](#) [S8JX-G03512D](#) [S8VS-09024B-F](#) [PS-6012](#)  
[PS9Z-5R1G](#) [PS-C24024](#) [PSC-9648](#) [5607189](#) [KHNA30F-24](#) [KHNA480F-24](#) [KHNA90F-12](#) [KHNA90F-24](#) [DVP08ST11N](#) [DVPACAB530](#)  
[DVPCOPM-SL](#) [DVPEN01-SL](#) [DVPPF01-S](#) [S8JX-G10012](#) [S8JX-G15024](#) [CBI1210A](#) [SS14011524](#) [S8JX-G01505C](#) [S8TS-06024-E1](#) [PS-](#)  
[S2012](#) [PSW-12024](#) [PS-UPS40](#) [PSC-6024](#) [S8VS-48024A-F](#) [PSD-A60W12](#) [96PS-A120WDIN](#) [PSD-A60W48](#) [S8JX-G03515CD](#) [PSD-](#)  
[A40W12](#) [PSD-A40W24](#)