

Main frame HM8001-2



The mainframe is supplied without the modules shown in the illustration

Basic unit for modules of the Modular System Series 8000

Modular system



HM8001-2 mainframes can be stacked up to 5 units high



Option H0801 – 4 BNC connectors on rear panel



Power supply for 2 modules

DC voltages electronically regulated,
floating and short-circuit proof

Power transformer with thermal fuse

Up to 5 mainframes can be stacked

Module HM800 for customized instrument construction available

4 BNC connectors on the rear panel of the HM8001-2
(Option H0801) provide for signal transmission to or from
HM8021 and HM8030-6 modules

Mainframe HM8001-2

Valid at 23 °C after a 30 minute warm-up period

General information

Mainframe with power supply accommodates 2 modules

Power supply module

2 x 8V~ max. 0.5A each

2 x 5V = max. 1A each

4 x 20V = max. 0.5A each

Voltages between 5V and 20V are programmable from each module
(Polarity selectable)

Available output power: Max. 36 Watt available for two modules.
All DC voltages are electronically stabilized,
floating and short-circuit proof.

Miscellaneous

Power switch (ON/OFF) located between the two modules on the front panel.

Safety class: Safety Class I (EN61010-1)

Power supply: 115/230V~ (50/60 Hz)

Max. permissible line fluctuation: ± 10 %

Power consumption: max. 110W
(with overload protection)

Operating temperature: 0° C to + 40° C

Dimensions (W x H x D): 285 x 75 x 365 mm

Weight: approx. 4 kg

Color: techno-brown

www.hameg.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [rohde & schwarz](#) manufacturer:

Other Similar products are found below :

[HMF2525](#) [HMP2020](#) [HMP2030](#) [RT-ZP03](#) [HZ24](#) [HV512](#) [HMC8041](#) [RTC1K-102](#) [RTC1K-202](#) [HA-Z211](#) [RTB2002 \(RTB2K-72\)](#) [RTB2004](#)
[+ RTB-B241 \(RTB2K-104\)](#) [RTM-B222](#) [RTM-B223](#) [RTM-B225](#) [RTM-B2210](#) [RTM-B243](#) [RTM-B2410](#) [R&S FPL1003-P4](#) [R&S® FPH-B8](#)
[NGE103B](#) [NGL-K103](#) [FPC-COM1](#) [RTB2K-202](#) [RTB2K-74](#) [RTC1K-COM2](#) [HMC8042](#) [HZ22](#) [RTB2K-104](#) [HM8118.02](#) [HA-Z302](#)
[RTB2002 + RTB-B221 \(RTB2K-102\)](#) [RTB-PK1](#) [RTM-K1](#) [RTM-B242](#) [R&S HMP4030](#) [R&S NRX](#) [R&S RTM-K36](#) [HMC8012](#) [HZ42](#) [RTM-](#)
[K3](#) [RTM-K15](#) [RTM-K18](#) [R&S HM7042-5](#) [RTB2004 \(RTB2K-74\)](#) [RTM3K-COM4](#) [RTM-K2](#) [RTM-K5](#) [RTM-K6](#) [RTM-K7](#)