

# R5F1007AANA

[Provide feedback](#) [Print this page](#) **TEXT SIZE**  
S M L

Products

- MPU & MCU
- RL78 Family
- RL78/G1x
- RL78/G13

**R5F1007AANA**

Overview Documentation Design Support

Product Spec  Order Information  Package & Packing

## Product Spec

Price	-	PWM Output.	-
CPU	RL78	8-bit A/D Converter (ch)	0
Max. Freq (MHz)	32	10-bit A/D Converter (ch)	6
Subclock (32.768kHz)	NO	12-bit A/D Converter (ch)	0
Bit Size	16	16Bit A/D Converter	0
Family	<a href="#">RL78</a>	8-bit D/A Converter (ch)	0
Series	<a href="#">RL78/G1x</a>	10-bit D/A Converter (ch)	0
Group	<a href="#">RL78/G13</a>	12-bit D/A Converter (ch)	0
Memory Management Unit.	NO	14-bit or more D/A Converter (ch)	0
FPU	NO	Operating Temperature Max (°C)	85
RAM	2	Operating Temperature Min (°C)	-40
Program memory	16	CAN (ch)	0
Pin Count	24	Ethernet	NO
Data Flash (KB)	4	USB Host	NO
Program Memory Type	Flash memory	USB Peripheral	NO
Cache type	-	USB OTG	-
Int. main oscillator freq	32	I2C-bus	3
PLL	NO	Ext. address bus	-
RTC	YES	Ext. data bus (Bit)	-
Operating Voltage Max	5.5	External Interrupt Pins	5
Operating Voltage Min	1.6	LCD_Com	-
Note1	-	Low Voltage Detection	YES
Note2	-	Power-On Reset	YES
I/O Ports CMOS I/O	18	DMAC	2
On-Chip Debug	YES	EXDMAC	-
8-bit Timer (ch)	0	CSI	2
16-bit Timer (ch)	8	UART	2
32-bit Timer (ch)	0	Lin	0
Watchdog Timer (ch)	1	IEBus	-
Other timer	Interval Timer x 1 ch	Remarks	-
PWM Output (up to 8Bit)	-	Application	-
PWM Output (9-16Bit)	3	Production Status	Mass Production

[Back To Top](#)

## Order Information

Orderable Part No.	Production Status.	Packing	Environmental	remark
R5F1007AANA#U0	Mass Production	Tray	Pb Free	-

[Back To Top](#)

## Package & Packing

[p24k8-50-cab](#) [fig0012e](#)

Package	
Renesas code	PWQFN0024KE-A
Previous code	P24K8-50-CAB-1
JEITA code	P-HWQFN24-4x4-0.50
Name	HWQFN
Terminal count	24
Terminal pitch (mm)	0.5
Dimensions (mm)	4x4
Mass (g) [Reference value]	0.04
Mounting height (mm) [MAX]	0.8
Terminal material - Base	Cu alloy
Terminal material - Surface	Ni/Pd/Au
Drawing Link	<a href="#">p24k8-50-cab</a>
Mount pad	<a href="#">fig0012e</a>
Remarks	Exposeddiepadtype

[Back To Top](#)

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [16-bit Microcontrollers - MCU category](#):*

*Click to view products by [Renesas manufacturer](#):*

Other Similar products are found below :

[MB90F036APMC-GSE1](#) [MB90F342CASPMC-GSE1](#) [MB90F345CESPMC-GE1](#) [MB90F349CAPFR-GSE1](#) [MB90F428GCPFR-GSE1](#)  
[MB90F462APFM-GE1](#) [MB90F462APMC-G-SNE1](#) [MB90F497GPF-GE1](#) [MB90F546GSPFR-GE1](#) [MB90F947APFR-GS-SPE1](#)  
[MB96F346RSBPMC-GS-N2E2](#) [MB96F683RBPMC-GSAE1](#) [R5F11BGEAFB#30](#) [DF3026XBL25V](#) [S912ZVFP64F1VLL](#)  
[R4F24268NVRFQV](#) [R5F107DEGSP#X0](#) [R5F11B7EANA#U0](#) [R5F21172DSP#U0](#) [M30622F8PGP#U3C](#) [MB90092PF-G-BNDE1](#)  
[MB90F335APMC1-G-SPE1](#) [MB90F342CASPF-R-GS-N2E1](#) [MB90F345CAPFR-GSE1](#) [MB90F543GPF-GE1](#) [MB90F546GSPF-GE1](#)  
[MB90F568PMCR-GE1](#) [MB90F594APFR-GE1](#) [MB90F882ASPMC-GE1](#) [MB96F346RSAPQCR-GS-N2E2](#) [MB96F387RSBPMC-GSE2](#)  
[MB96F387RSBPMC-GS-N2E2](#) [MB96F395RSAPMC-GSE2](#) [MB96F623RBPMC1-GSE1](#) [MB96F646RBPMC-GSE1](#)  
[XE167F96F66LACFXUMA1](#) [MB96F696RBPMC-GSAE1](#) [MB96F018RBPMC-GSE1](#) [MB90F962SPMCR-GE1](#) [MB90F867ASPFR-GE1](#)  
[MB90F543GPF-G-FLE1](#) [MB90F345CESPF-GE1](#) [M30290FCHP#U3A](#) [DF2239FA20IV](#) [HD64F3672FPV](#) [R5F104AEASP#V0](#)  
[R5F100BCANA#U0](#) [R5F100BFANA#U0](#) [S9S12H256J2VFVER](#) [R5F100ACASP#V0](#)