

Small Signal Transistors

TO-18 Case (Continued)



TYPE NO.	DESCRIPTION	BV _{CBO}	BV _{CEO}	BV _{EBO}	I _{CBO} @	V _{CB}	h _{FE}		@ I _C	@ V _{CE}	V _{CE(SAT)}	@ I _C	C _{OB}	f _T	NF	t _{on}	t _{off}
		(V)	(V)	(V)	(μA)		(V)	MIN	MAX	(mA)	(V)	(V)		(mA)	(pF)	(MHz)	(dB)
		MIN	MIN	MIN	MAX					MAX	MAX	MAX	MAX	MIN	MAX	MAX	MAX
2N5183	NPN AMPL/SWITCH	18	18	7.0	0.5	12	75	400	10	10	0.5	300	20	125	--	--	--
2N6430	NPN HIGH VOLTAGE	200	200	6.0	0.1	160	50	200	30	10	0.5	20	4.0	50	--	--	--
2N6431	NPN HIGH VOLTAGE	300	300	6.0	0.1	200	50	200	30	10	0.5	20	4.0	50	--	--	--
2N6432	PNP HIGH VOLTAGE	200	200	5.0	0.25	160	30	150	30	10	0.5	20	6.0	50	--	--	--
2N6433	PNP HIGH VOLTAGE	300	300	5.0	0.25	200	30	150	30	10	0.5	20	6.0	50	--	--	--
BC110	NPN AMPL/SWITCH	80	80	8.0	0.1	80	30	--	2.0	5.0	0.6	50	5.0	50	--	--	--
BC187	PNP AMPL/SWITCH	30	25	5.0	0.1	30	140	--	2.0	5.0	--	--	--	--	--	--	--
BC393	PNP AMPL/SWITCH	180	180	6.0	0.05	100	50	100	10	10	0.3	10	7.0	5.0	--	100	400
BC394	NPN AMPL/SWITCH	180	180	6.0	0.05	100	50	100	10	10	0.3	10	7.0	5.0	--	100	400
BC477	PNP AMPL/SWITCH	90	80	6.0	0.01*	70	70	250	2.0	5.0	0.25	10	6.0	150	10	--	--
BCX22	NPN AMPL/SWITCH	125	125	5.0	0.1*	100	40	--	200	1.0	0.9	300	12	50	--	--	--
BCX23	PNP AMPL/SWITCH	125	125	5.0	0.1*	100	40	--	200	1.0	0.9	300	12	50	--	--	--
BCX24	NPN AMPL/SWITCH	100	100	7.0	0.03*	0.03*	20	--	10	1.0	0.9	300	12	30	--	--	--
BCX39	PNP AMPL/SWITCH	100	100	5.0	0.1*	100	40	--	200	1.0	0.9	300	12	50	--	--	--
BCX94	NPN AMPL/SWITCH	100	100	5.0	100*	100	63	--	100	1.0	0.9	300	8.0	50	--	--	--
BCY70	PNP AMPL/SWITCH	50	40	5.0	0.5	50	15	--	50	1.0	0.25	10	6.0	250	6.0	65	420
BCY71	PNP AMPL/SWITCH	45	45	5.0	0.5	45	100	600	10	1.0	0.25	10	6.0	250	2.0	--	--
BCY79	PNP AMPL/SWITCH	45	45	5.0	0.1*	45	80	1.0K	10	1.0	0.25	10	7.0	180	6.0	150	800
BFR16	NPN LOW NOISE	60	60	8.0	0.01*	50	150	490	1.0	5.0	5.0	10	6.0	70	4.0	--	--
BFW68	NPN AMPL/SWITCH	50	40	5.0	0.01	30	45	--	1.0	10	0.15	10	4.0	250	6.0	30	240
BFX65	PNP AMPL/SWITCH	45	45	6.0	0.01*	40	100	--	1.0	5.0	0.25	10	6.5	100	3.0	--	--
BFY18	NPN AMPL/SWITCH	40	25	3.0	0.01	20	25	--	10	9.0	1.5	10	5.5	200	--	--	--
BFY74	NPN AMPL/SWITCH	60	45	5.0	0.01	45	40	180	10	5.0	1.0	10	4.0	250	--	--	--
BFY76	NPN LOW NOISE	60	60	8.0	0.02*	50	150	300	1.0	5.0	0.35	1.0	6.0	70	4.0	--	--
BSV68	PNP AMPL/SWITCH	110	100	6.0	10	110	30	--	10	5.0	0.25	25	5.0	50	--	--	--
BSX19	NPN AMPL/SWITCH	40	15	--	0.4	20	20	60	10	1.0	0.25	10	4.0	400	--	12	15
BSX20	NPN AMPL/SWITCH	40	15	4.5	0.4	20	40	120	10	1.0	0.25	10	4.0	500	--	12	18
BSX21	NPN AMPL/SWITCH	120	80	5.0	0.2	90	20	--	4.0	1.0	0.70	4.0	4.5	60	--	--	--
BSX36	PNP AMPL/SWITCH	40	40	5.0	0.015	25	40	--	10	10	1.8	500	8.0	100	--	40	100
BSX49	NPN AMPL/SWITCH	60	40	5.0	0.07	50	25	--	100	1.0	1.0	500	6.0	250	--	50	95
BSX79	NPN AMPL/SWITCH	50	45	5.0	0.01	25	100	750	10	1.0	0.2	10	5.0	200	--	150	800
BSY18	NPN AMPL/SWITCH	20	12	5.0	1.0	20	40	120	10	0.35	0.28	10	5.0	280	--	16	24
BSY62	NPN AMPL/SWITCH	25	15	5.0	0.5	15	20	300	10	1.0	0.6	10	5.0	280	--	40	75
BSY79	NPN AMPL/SWITCH	120	--	5.0	0.05	90	30	--	1.0	1.0	0.5	2.0	4.0	50	--	--	--
BSY95A	NPN AMPL/SWITCH	20	15	5.0	0.05	16	50	200	10	0.35	0.35	10	6.0	200	--	--	--
MM4257	PNP FAST SWITCH	6.0	6.0	4.5	0.01*	6.0	30	120	10	0.3	0.15	10	3.0	500	--	25	25
MM4258	PNP FAST SWITCH	12	12	4.5	0.01*	6.0	30	120	10	0.3	0.15	10	3.0	700	--	25	30



OUTSTANDING SUPPORT AND SUPERIOR SERVICES

PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix " TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix " PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centrasemi.com

Worldwide Field Representatives:
www.centrasemi.com/wwreps

Worldwide Distributors:
www.centrasemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centrasemi.com/terms

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [Central Semiconductor manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [MJ15024/WS](#) [MJ15025/WS](#) [BC546/116](#) [BC556/FSC](#) [BC557/116](#) [BSW67A](#) [HN7G01FU-A\(T5L,F,T](#)
[NJVMJD148T4G](#) [NSVMMBT6520LT1G](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE2353](#) [NTE316](#) [IMX9T110](#) [NTE63](#) [NTE65](#)
[C4460](#) [SBC846BLT3G](#) [2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA1727TLP](#) [2SA2126-E](#) [2SB1202T-TL-E](#) [2SB1204S-TL-E](#) [2SC5488A-](#)
[TL-H](#) [2SD2150T100R](#) [SP000011176](#) [FMC5AT148](#) [2N2369ADCSM](#) [2SB1202S-TL-E](#) [2SC2412KT146S](#) [2SC4618TLN](#) [2SC5490A-TL-H](#)
[2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#) [BC557B](#) [TTC012\(Q\)](#) [BULD128DT4](#) [JANTX2N3810](#)
[Jantx2N5416](#) [US6T6TR](#) [KSF350](#) [068071B](#)