

Sync'n Go® -- Portable Precision Frequency Reference



SYNC-10.00MHz.



**RoHS
Compliant**

FEATURES:

- Stand Alone 10.00MHz Portable Precision Frequency Reference
- [World Wide Capability](#)
- Built-in Stratum-III stability, 10.00MHz Signal tuned into 50Ω's • Synchronization circuitry providing dynamic sync capability, enabling Calibration to a known source such as; a GPS Tracked 10.00MHz reference/10.00MHz Rubidium Source/10.00MHz OCXO based reference
- Integrated re-chargeable batteries to provide true stand-alone capability in the field
- Once sync'd; guaranteed ±300 ppb stability over 0°C to 60°C
- Pocket Size - 3.50" * 1.50" * 1.00"; machined aluminum durable enclosure
- Accompanied with a Universal AC-DC Charger
- Continuously operable at full charge for 10-hours

APPLICATIONS:

- Ideally suited as an in-field Calibrated Precision 10.00MHz reference for trouble shooting or tuning hardware and Base Station related equipment
- Reference source for lab use
- Reference source to drive frequency counters and other timing related hardware or instruments
- Precision Portable reference for inspection of in-field wireless transmitters

STANDARD SPECIFICATIONS:

Parameter	Description	Value / Units
Input Reference Frequency for Sync	10.00	MHz
Output Reference Frequency	10.00	MHz
Operable Operating Range	0°C to +60°C	
Synchronization accuracy	±5.00	ppb
Frequency Drift post sync (25°C ± 10°C)	±25.00	ppb Typical
Frequency Drift post sync (25°C ± 20°C)	±50.00	ppb Typical
Frequency Accuracy Over the operating Temperature Range	< ±100 ±300	ppb Typical; Post Sync ppb Maximum; Post Sync
Load Impedance	50	Ω
Charging Time	4.00	Hours maximum
Stand Alone operational time with full charge	10.00	Hours minimum
Phase Noise @ 10.00MHz Carrier		
100 Hz offset	-120	dBc/Hz typical
1,000 Hz offset	-140	dBc/Hz typical
10,000 Hz offset	-150	dBc/Hz typical
100,000 Hz offset	-155	dBc/Hz typical
1,000,000 Hz offset	-155	dBc/Hz typical
Output amplitude	6.0	dBm minimum
ALL Harmonics	-30	dBc maximum
rms jitter	< 0.50 ps	12kHz to 20MHz BW from the carrier

PACKAGE OUTLINE



ABRACON IS
ISO9001:2008
CERTIFIED



**ABRACON
CORPORATION**

Visit www.abracon.com for Terms & Conditions of Sale **Revised: 10.02.11**
30332 Esperanza, Rancho Santa Margarita, California 92688
tel 949-546-8000 | fax 949-546-8001 | www.abracon.com

Sync'n Go® -- Portable Precision Frequency Reference

SYNC-10.00MHz.



**RoHS
Compliant**



OPERATIONAL MANUAL

Charge:

- 1) Plug 5V charger (or PC or any other USB power source) into a mini-USB port
- 2) "Bat" LED may turn yellow for a moment to signal that an internal battery is evaluated
- 3) "Bat" LED will flash green to signal that the battery is being charged
- 4) "Bat" LED will display solid green when the battery is fully charged

Synchronization:

- 1) Connect a 10MHz standard to the "Ref In" input
- 2) Press "Synchronize"
- 3) "Lock" LED will turn-on yellow to signal that "Sync N Go" is evaluating the standard
- 4) If the reference is stable, the "Lock" LED will turn green to signal that the signal is locked and that the reference information is stored
- 5) If the reference is not found or it is outside a frequency range or it is not stable, the "Lock" LED will flash red
- 6) If that occurs, the "Lock" LED turns-off and the "Sync N Go" goes into a sleep mode

Output ON (if battery charged):

- 1) Press "Power"
- 2) "ON" LED will turn green
- 3) "Sync N Go" will output a continuous RF signal on the "Out" connector

Output ON (if battery low):

- 1) Press "Power"
- 2) "ON" LED will turn green.
- 3) "Sync N Go" will output a continuous RF signal on the "Out" connector. At the same time, "Bat" LED will slowly flash red.

Output ON (if battery is discharged):

- 1) Press "Power"
- 2) "Bat" LED will rapidly flash red for few seconds and "Sync N Go" will immediately go back to sleep

Output OFF:

- 1) Press "Power"
- 2) "ON" LED turns off and the "Sync N Go" goes into a sleep mode

ATTENTION: Abracon Corporation's products are COTS – Commercial-Off-The-Shelf products; suitable for Commercial, Industrial and, where designated, Automotive Applications. Abracon's products are not specifically designed for Military, Aviation, Aerospace, Life-dependant Medical applications or any application requiring high reliability where component failure could result in loss of life and/or property. For applications requiring high reliability and/or presenting an extreme operating environment, written consent and authorization from Abracon Corporation is required. Please contact Abracon Corporation for more information.

ABRACON IS
ISO9001:2008
CERTIFIED



Designed & Manufactured in United States

For technical assistance, please contact: techsupport@abracon.com

Visit www.abracon.com for Terms & Conditions of Sale **Revised: 10.02.11**
30332 Esperanza, Rancho Santa Margarita, California 92688
tel 949-546-8000 | fax 949-546-8001 | www.abracon.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Abracon](#) manufacturer:

Other Similar products are found below :

[AISC-0805-R0022J-T](#) [AWSCR-4.00CP-T](#) [ASEMB-26.000MHZ-L-T](#) [ABLNO-V-96.000MHZ](#) [ARRSN5-868.000MHz](#) [ASDMB-50.000MHZ-XY-T](#) [ASEMPLP- ADAPTER-KIT](#) [ASFLMPLV- ADAPTER-KIT](#) [ASG-D-X-A-500.000MHz](#) [ASTMLPD-24.000MHz-LJ-E-T](#) [ABLJO-V-150.000MHz](#) [ABM8G-12.000MHZ-B4Y-T3](#) [AIRD-06-101K](#) [AOCJY3-40.000MHZ](#) [AOCJY6-10.000MHz-1](#) [ASDM1-8.000MHZ-LC-T](#) [ASEMB-20.000MHZ-LC-T](#) [ASEMB-27.000MHZ-XY-T](#) [ASHEK2-32.768KHZ-LT](#) [ASVTX-13-A-26.000MHZ-D15-T](#) [AXS-5032-04-12](#) [ABBTM-2.4GHZ-EVAL](#) [ASFL1-50.000MHZ-EK-T](#) [ASDMB-50.000MHZ-LY-T](#) [AST3TQ-T-10.000MHZ-28](#) [ASV-12.288MHZ-EJS](#) [ABLS2-4.096MHZ-D4Y-T](#) [ALFT-04-5](#) [AOCTQ5-V-10.000MHz-I3-SW](#) [AOCTQ5-X-10.000MHz-M10-SW](#) [ABL-10.000MHZ-D-T](#) [ABL-16.384MHZ-B2](#) [ABLNO-150.000MHZ](#) [AIRD-01-680K](#) [AOCJY2-100.000MHz-F](#) [AOCJY2-10.000MHz](#) [AOCJY2A-10.000MHz](#) [AOCJY3-40.000MHZ-E](#) [AOCJY-38.880MHZ-F](#) [AOCJY3B-10.000MHz-E-SW](#) [ASEM1-100.000MHZ-L-C-T](#) [ASG2-D-X-A-1000.000MHz](#) [ASG-D-X-A-200.000MHz](#) [ASGTX-P-1.500GHz-1](#) [AST3TQ-40.00MHz-5](#) [ASVMPHC-ADAPTER-KIT](#) [AXS-3225-04-04](#) [AXS-3225-04-10](#) [AXS-5032-04-02](#) [AXS-7550-06-05](#)