

Voltage and Continuity Tester **TENMA™**



General Characteristics

Power	: 1.5V Batteries (R03) × 2
Product Colour	: Orange and Grey
Product Net Weight	: 280g
Product Size	: 272mm × 85mm × 31mm
Standard Accessories	: Batteries

Specifications:

Basic Functions	Range	Best Accuracy
LED AC/DC Voltage Indication (V)	12V	± (1.5%+2)
	24V	± (1.5%+2)
	50V	± (1.5%+3)
	120V	± (1.5%+4)
	230V	± (1.5%+5)
	400V	± (1.5%+5)
	690V	± (1.5%+5)
Phase Rotation Test	Operating Voltage: 100V to 690V Frequency: 50Hz to 60Hz	√
Single Lead(L2)Voltage Detection	Operating Voltage: 100V to 690V Frequency: 50Hz to 400Hz	√
Continuity Test	Resistance: 0 to 100kΩ Beeper and LED light Indicator	√
RCD Test	Operating Voltage: 230V (50Hz to 400Hz)	√
Polarity Detection	Positive & Negative	√
Self-inspection	All LED or LCD indicator	√
No Power Test	Operating Voltage: 100V to 690V DC/AC	
Features		
IP65		√
Auto Range	All Range	√
Exceed Voltage	Voltage Range: 713V to 788V	√
Auto standby	Standby current <10μA	√
Silent mode	All Range	√
Work Light	All Range	√
Low Battery Indication	Around 2.5V	√
LCD Backlight	All Range	√
LCD Display (Voltage)	6V to 690V	±(1.5%+5)
LCD Display (frequency)	40Hz to 400Hz	±(3%+5)

Voltage and Continuity Tester

Part Number Table

Description	Part Number
Voltage and Continuity Tester	72-3570

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

X-ON Electronics

Authorized Distributor

Click to view similar products for [Tenma manufacturer](#).

Other Similar products are found below :

[2110130UKEU](#) [2110140](#) [2110142](#) [2110144](#) [2110146](#) [2110148](#) [2110150](#) [2110152](#)
[2110154](#) [2110156](#) [2110158](#) [2110160](#) [2110162](#) [2110164](#) [2110168](#) [2110170](#) [211040](#)
[211041](#) [211042](#) [211045](#) [211046](#) [211047](#) [211050](#) [2110562](#) [2110563](#)