



Features:

- Used in the rework and repair of printed circuit boards, computers, cell phones, or other electronics
- Easily removes solder from components or pads on a circuit board
- Concentrated fine copper braiding utilizes less length of wick for each desoldering application
- Made of clean, oxide-free copper wire
- Tight weave enables quick “on and off” desoldering
- Flux residue on board does not need to be cleaned
- To be used in conjunction with processes using RMA type no-clean fluxes
- 5’ and 10’ lengths available on static-dissipative bobbins in compliance with ESD Association Standard

Wire Specifications:

Wire Type	Width	Configuration
A Wire	0.025" (±0.003") 6.35mm (±0.8mm)	2 strands of 42awg X 16 (total 32 strands), 31 PPI
B Wire	0.050" (±0.004") 12.70mm (±1.0mm)	4 strands of 42awg X 16 (total 64 strands), 12.5 PPI
C Wire	0.075" (±0.005") 19.5mm (±1.3mm)	6 strands of 42awg X 16 (total 96 strands), 16 PPI
D Wire	0.095" (±0.007") 24.1mm (±1.8mm)	5 strands of 42awg X 24 (120 total strands), 19 PPI
E Wire	0.117" (±0.008") 29.7mm (±2.0mm)	5 strands of 40awg X 24 (120 total strands), 16 PPI

Bobbin Identification:

Width	Color Code	Letter Signifier
.025"	Silver	A
.050"	Gold	B
.075"	Green	C
.100"	Blue	D
.125"	Brown	E

EasyBraid expressly warrants that for a period of two (2) years from the date of manufacture, One-Step No Clean Braid will be free of defects in material (parts) and workmanship (labor) when stored appropriately and contained within its original container. Each bobbin is individually stamped with a lot code. A certificate of compliance is available on our [website](#).

Specifications and procedures subject to change without notice.



ONE STEP NO CLEAN DESOLDERING BRAID

11543 K-TEL DRIVE, MINNETONKA, MN 55343
 PHONE: (952) 929-3040
 WEBSITE: EASYBRAIDCO.COM

DRAWING NUMBER
 One Step Braid

DATE:
 February 2018

EasyBraid

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [easy braid manufacturer](#):

Other Similar products are found below :

[EB41D2120](#) [ETZ-KIT-1](#) [SHP-PM](#) [Q-A-100](#) [OS-E-100](#) [OS-E-25](#) [S-B-5AS](#) [S-E-100](#) [S2626-O-T](#) [OS-E-10AS](#) [Q-B-100](#) [S-A-100](#) [Q-D-100](#)
[S3030R-O-T](#) [Q-E-10AS](#) [Q-E-25](#) [Q-A-25](#) [Q-B-25](#) [LF-A-5AS](#) [Q-A-10AS](#) [Q-E-100](#) [LF-E-5AS](#) [Q-A-5AS](#) [S-B-100](#) [S2235-O-T](#) [OS-D-100](#)
[LF-B-5AS](#) [S-A-10AS](#) [S-D-10AS](#) [LF-D-5AS](#) [LF-C-10AS](#) [S-B-10AS](#) [LF-D-10AS](#) [Q-B-10AS](#) [OS-D-5AS](#) [Q-E-5AS](#) [Q-D-10AS](#) [S-C-5AS](#)
[OS-C-100](#) [S-D-5AS](#) [OS-B-25](#) [Q-D-25](#) [Q-C-100](#) [OS-B-100](#) [OS-D-10AS](#) [Q-C-25](#) [S-E-10AS](#) [S-E-5AS](#) [OS-E-5AS](#) [S2432-O-T](#)