


管状保险丝

测试电流 Testing current		熔断时间 Blow Time	
		Min 最小	Max 最大
150%		1h	/
210%		100ms	1800s
275%		10ms	3s
400%		3ms	300ms
1000%		/	20ms



Breaking Capacity 分断能力
VDE: 35A or 10In whichever is greater (250mA-6.3A)
UL: 50 amperes at 125V/250V AC (250mA-10A)

Material 材料
Fuse body --glass tube
End cap--nickel plated brass
Pigtail--tin plated copper on nickel plated brass cap

Approvals 认证 (○ Pending ● Approvals)

额定电流 Current Rating	额定电压 Voltage Rating	VDE	CQC	UL	JET	CCC
250mA	125V/250V	●	●	●		●
300mA	125V/250V			●		
315mA	125V/250V	●	●	●		●
350mA	125V/250V			●		
400mA	125V/250V			●		
500mA	125V/250V	●	●	●		●
600mA	125V/250V			●		
630mA	125V/250V	●	●	●		●
750mA	125V/250V			●		
800mA	125V/250V	●	●	●		●
1A	125V/250V	●	●	●	●	●
1.25A	125V/250V	●	●	●	●	●
1.5A	125V/250V			●	●	
1.6A	125V/250V	●	●	●	●	●
2A	125V/250V	●	●	●	●	●
2.5A	125V/250V	●	●	●	●	●
3A	125V/250V			●	●	
3.15A	125V/250V	●	●	●	●	●
3.5A	125V/250V			●	●	
4A	125V/250V	●	●	●	●	●
5A	125V/250V	●	●	●	●	●
6A	125V/250V			●		
6.3A	125V/250V	●	●	●		●
7A	125V/250V			●		
8A	125V/250V			●		
10A	125V/250V			●		

管状保险丝

附录资料：

管状保险丝（熔断器），一般由三个部分组成，一是熔体部分，它是保险丝的核心，保险丝最重要的参数直接取决于这部分，也是影响保险丝性能的最大部分；二是电极部分，通常有两个，它是熔体与电路联接的重要部件，它必须有良好的导电性，不应产生明显的安装接触电阻，一般为铜帽和引脚；三是支架部分，保险丝的熔体（熔丝）一般都纤细柔软的，支架的作用就是将熔体固定并使三个部分成为刚性的整体便于安装、使用，它必须有良好的机械强度、绝缘性、耐热性和阻燃性，在使用中不应产生断裂、变形、燃烧及短路等现象，一般为玻璃管或者陶瓷管，在这部分，有些保险丝还有灭弧装置，就是在玻璃管或者陶瓷管中填沙，通常为石英沙。

一般要求

- 外形尺寸
尺寸--6.3x32, 5.2x20, 4.5x15, 3.6x10……
外观--管体清洁无缺损、端头镀层光亮均匀
- 熔丝--居中或对角线
避免碰内壁影响散热条件改变熔断特性
- 间隙--管子外壁与铜帽内壁的间隙适当
避免铜帽松动脱落或锡外溢
- 用锡量—锡量适当保证连接良好和结合强度

标志

- 方式：压印或滚印，不致铜帽变形
- 内容：端头 1：商标、安全认证
端头 2：熔断特性、 I_n 、分断能力、 U_n
- 要求：位置可以在端帽外部的圆周和顶部
熔断特性代码：FF、F、M、T、TT
 I_n ：小于 1A-XXX mA、等大于 1A-XX A
分断能力：H、L
 U_n ：XXX V
- 特例：有用色环或文字印刷在管体上的标志

机械要求

- 准直度：用准直规能通过为合格
- 结合强度：端帽和管体的结合力
用拉力与扭力来考核
胶粘剂用量适当，或紧配合
- 引线弯曲力和延展度：能保证工艺过程实施和质量

连接器要求

- 通用要求：接触电阻、插拔力/次数、绝缘电阻、耐压和阻燃性、可焊性。。。
- 熔断器夹：金属材料回弹力、接点压力

管状保险丝

- 熔断器座：金属材料回弹力、接点压力
- 熔断器盒：弹簧回弹力
- 熔断器套：弹簧回弹力

电气要求

- 熔断特性
 - 保持电流：1.05/1.1 I_n 或 1.15/1.2 I_n 不动作
 - 熔断电流：2/2.1 I_n , 2.75 I_n , 4 I_n , 10 I_n 在规定时间内动作
- 分断能力
 - 低分断：35A 或 10 I_n 选大者
 - 中分断：150A 高分断—1500A
 - 不发生持续飞弧/引燃/熔断体碎裂等现象，分断后的绝缘电阻必须大于 0.1 M
- 耐久性
 - 1.05 I_n 通 1h 断 15min，连续 100 周期，最后 1 周期 1.2 I_n 或 1.5 I_n ，试验后电压降增大不超过 10%，标志仍清晰

主要应用市场

- 家用电器
- 仪器仪表
- 配电箱及插头开关
- 机械及其他设备
- 电源及变换器

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Cartridge Fuses](#) category:

Click to view products by [Xucheng](#) manufacturer:

Other Similar products are found below :

[MBO-20](#) [MDA-V-1/100](#) [12C10X38GI](#) [AGA-V-2-1/2](#) [AGC-V-3-12-R](#) [AGY-50](#) [MSL-3](#) [MSL-4](#) [MSL-5](#) [BK1/C436-2A](#) [BK1-GMA-1-6-R](#)
[BK1-GMA-200-R](#) [BK1GMA-6-R](#) [BK1/GMC-100-R](#) [BK1/GMC-1.5-R](#) [BK1-GMC-2-5-R](#) [BK1GMD-4-R](#) [BK1S500-250-R](#) [BK1S500-32-R](#)
[BK1-S500-4-R](#) [BK1S500-5-R](#) [BK1-S505-1-R](#) [BK1-S506-2-R](#) [BK1-S506-3-15-R](#) [BK1/S506-63-R](#) [BK/ABC-5RX](#) [BK/AGW-B-4](#) [BK/AVX-](#)
[1/4](#) [BK/C515S-250-R](#) [BK/MBO-20](#) [BK/MBO-8](#) [BK/MDM-3/4](#) [BK-MDQ-4](#) [BK/S505-V-2.5A](#) [BK/TDC120-15](#) [BK/TDC120-20](#)
[BK/TDC122-45](#) [BP/MDL-7](#) [1C10X38AM](#) [S505-V-500MA](#) [SEF-1697-1-002](#) [AGA-V-7-1/2](#) [AGC-15WX](#) [AGC-2-1-2-R](#) [20.0M6.3X32F](#)
[20C8X32GI](#) [GMC-50-R](#) [361.250](#) [MBO-8](#) [TDC121-30](#)