



F&F Filipowski sp. j  
ul. Konstytucyjna 79/81  
95-200 Pabianice, POLAND  
tel/fax 48 42 2270971  
e-mail: fif@fif.com.pl

## PCU-510

### TIMING RELAYS multi purpose



www.fif.com.pl

F&F products are covered by an 24 months warranty from date of purchase


#### PURPOSE

Timing relays are devised to time the control of industrial and domestic automatic control engineering systems (e.g. entilation, heating, lighting, signalling, etc.).

#### FUNCTIONING

##### Working mode: LAGGED DEACTIVATION(A)

Until the relay is activated, the contact remains in the 8-7, 11-10 position. After the power voltage is supplied (green LED U is shining), contact is shifted to position 8-9, 11-12 and the countdown of the preset value t is commenced. After the preset time t has been counted down, contact returns to position 8-7, 11-10. The working sequence of the relay may be repeated after turning the power supply off and on.



#### WORK TIME SETTINGS

By time range switch T↔ set to one of choosen range and by setting time knob T× set value from 1 to 12. Product of this vaules is equal work time (e.g. 1m×7=7 min).

#### WORK MODE SETTINGS

By knob FUNC set one of functions (e.g. function A - Lagged Deactivation).

#### ATTENTION!

- With the power supply on, the system does not respond to time range setting modifications.
- The newly set time range is active after the power supply has been turned off and on.
- With the power supply on, it is possible to regulate the preset time freely within the selected time range.

#### ASSEMBLY

1. Take OFF the power.
2. Put on the relay on the rail in the switchgearbox.
3. Cables of power connect with wiring diagram with voltage marks: voltage 230V to joints 1-3; voltage 24V to joints 1-4

**ATTENTION:** Connect only one of choosen voltages.

4. System of switching ON receiver connect in line to joints 8-9 and 11-12.

#### LAGGED ACTIVATION (B)


After the power voltage is supplied, the contact remains in position 8-7, 11-10 and the timing of the preset value t is commenced. After the preset time t has been counted down, the contact is shifted to position 8-9, 11-12. The working sequence of the relay may be repeated after turning the power supply off and on.

#### LAGGED ACTIVATION - CYCLIC (D)

The Lagged Activation mode is triggered in equal work cycles according to the preset time values.

#### LAGGED DEACTIVATION - CYCLIC (C)

The Lagged Deactivatin mode is triggered in equal work cycles according to the preset time values.




Setting the time range knob regulator in the:

- ON - position with power supply activated connection of joint in position 8-9 and 11-12.
- OFF - position with power supply activated connection of joint in position 8-7 and 11-10.

#### TECHNICAL DATA

supply	230V AC / 24V AC / DC
current load	2×(<8A)
joint	2P
operation time	0,1sec+24h
switching ON delay	<50msec
power supply indicator	green LED
operation mode indicator	red LED
power consumption	0,8W
working temperature	-25+50°C
connection	screw terminals 2,5mm <sup>2</sup>
dimensions	1 module (18mm)

#### WIRING DIAGRAM



A090603

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Timers](#) category:*

*Click to view products by [F&F](#) manufacturer:*

Other Similar products are found below :

[79237785](#) [H3DS-GL AC24-230/DC24-48](#) [H5AN-4DM DC12-24](#) [H5CN-XDNM AC100-240](#) [H5CN-YAN AC100-240](#) [H5CX-L8S-N AC100-240](#) [H3AMNSCAC100240](#) [H3AM-NSR-B AC100-240](#) [H3CA-8 DC12](#) [H3CR-A8-302 DC24](#) [H3CR-F AC24-48/DC12-48](#) [H3CR-G8EL AC200-240](#) [H5AN-4D DC12-24](#) [81506944](#) [88225029](#) [H5S-YB4-X](#) [H3CR-A-301 AC100-240/DC100-125](#) [H3CR-AS AC24-48/DC12-48](#) [H3DK-GE AC240-440](#) [H3RN-2 AC24](#) [H3RN-21 AC24](#) [H3CR-H8RL AC/DC24 M](#) [H3CR-H8RL AC100-120 S](#) [H3CR-G8EL-31 AC100-120](#) [H3CR-H8RL AC100-120 M](#) [H3CR-HRL AC100-120 M](#) [H3CR-A8-301 AC24-48/DC12-48](#) [H3CR-H8RL AC/DC24 S](#) [H7AN-2D DC12-24](#) [H5CN-XANS DC12-48](#) [H3CA-8 DC110](#) [H7AN-W4DM DC12-24](#) [H7AN-4DM DC12-24](#) [H7AN-4D DC12-24](#) [H7AN-RT6M AC100-240](#) [H3CA-8H AC200/220/240](#) [MTR17-BA-U240-116](#) [PM4HSDM-S-AC240VS](#) [PM4HSDM-S-AC240VSW](#) [PO-405](#) [600DT-CU](#) [H3Y-2-B DC24 30S](#) [PM4HF8-M-DC24V](#) [PM4HS-H-DC12VSW](#) [H3Y-2-B AC100-120 10S](#) [H3Y-2-B AC100-120 30S](#) [H3C-R](#) [H3CR-A8-301 24-48AC/12-48DC](#) [H3CR-A8E 24-48AC/DC](#) [H3CR-F8 100-240AC/100-125DC](#)