



**Catalog Number W (1/2 - 12A)
125Vac or Less
Edison Base
Fast-Acting**

Amp Ratings				
W (Amp)				
1/2	2	4	6-1/2	10
1	2-1/2	5	7	12
1-8/10	3	6	8	—

W Specifications

Fast-Acting

Voltage Rating: 125Vac

Amp Rating: 1/2 - 12 Amps

Interrupting Rating: 10,000 RMS Symmetrical Amps

Agency Approvals:

UL Listed, Guide JEFV, File E 12112

Benefits:

- General purpose for non-inductive lighting and heating loads.
- Economical.
- Edison base threads into non-rejection fuse receptacles.

Obsoleted W-15 through W-30 plug fuses are replaced with T and TL plug fuses.



**Catalog Number SA (1 - 30A)
Rejection Base Fuse Adapter**

Adapter Sizes				
SA (Amp)				
1	2	4	8	20
1-1/4	2-1/2	4-1/2	10	30
1-6/10	3-2/10	6-1/4	15	—

Rejection base fuses (Type S and SL) require adapters to be used in standard Edison base sockets. Once installed, rejection base adapters accept only rejection base fuses which prevents the wrong fuse size from being used.

Dual-Element Type S Fuses and Adapters for Small Motor Protection. (Both Motor Running and Short-Circuit Protection)

Fuse Cat. No.	Adapter Cat. No.	Other Accepted Amp Rating
S3/10, S1/2, S8/10 S4/10, S6/10, S1	SA-1	1 amp and smaller
S1-1/8, S1-1-1/4	SA-1-1/4	All smaller
S1-4/10, S1-6/10	SA-1-6/10	All smaller
S1-8/10, S2	SA-2	—
S2-1/4, S2-1/2	SA-2-1/2	1-8/10, 2
S2-8/10, S3-2/10	SA-3-2/10	1-8/10 thru 2-1/2
S3-1/2, S4	SA-4	—
S4-1/2, S5	SA-4-1/2	3-1/2, 4
S5-6/10, S6-1/4	SA-6-1/4	3-1/2 thru 5
S7, S8	SA-8	—
S9, S10	SA-10	7, 8
S12, S14	SA-15	7, 8, 9, 10
Branch Circuit Protection		
S15	SA-15	—
S20	SA-20	—
S25	SA-30	—
S30	SA-30	20, 25, 30