



SPECIFICATIONS											
WIRING	INPUT		OUTPUT				SHAFT ROTATION TO INCREASE VOLTAGE	TERMINAL CONNECTIONS			
	VOLTS	HERTZ	VOLTS	CONSTANT CURRENT LOAD		CONSTANT IMPEDANCE LOAD		FOR INCREASING VOLTAGE AS VIEWED FROM BASE END			
				MAX. AMPS	MAX. KVA	MAX. AMPS		MAX. KVA	INPUT	JUMPER	OUTPUT
SINGLE PHASE	240	60	0-240	5.0	1.20	7.0	1.68	CW	1-4	---	4-3
								CCW	1-4	---	1-3
<small>UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ± DECIMALS HOLES ANGLES DRAFT .XX .0000 .03 .002 1° 1-1/2° .XXX .005</small>											
MATERIAL:			ALL DIMENSIONS APPLY AFTER PLATING		TITLE: SPEC. CONTROL DRAWING VARIABLE TRANSFORMER MODEL: 1220B						
<small>The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.</small>											
DRAWN BY	DATE	FIRST USED ON	DO NOT SCALE DWG.	CAGE CODE		DWG. NO.					
S.A. SMITH	9/25/97			83008		031-3260					
CHECKER	DATE	WEIGHT APPROX.	SCALE	SHEET 1 OF 1		DWG. NO.					
		9 LBS	1=1			031-3260					

