



USB2.0 to mSATA Converter Board

Quick users guide

1. Features

- Supports SATA III, SATA II and SATA I mSATA SSD
- Compliant with Serial ATA Specification Revision 2.6
- Supports Serial ATA transfer rate of 6.0 Gbps
- Supports ATA/ATAPI Packet Command Set
- Supports ATA/ATAPI LBA 48 Addressing mode
- Compliant with Universal Serial Bus Specification Revision 2.0 (Data Rate 1.5/12/480 Mbps)
- Compliant with Open Host Controller Interface Specification for USB Rev 1.0a
- Compliant with Enhanced Host Controller Interface Specification for USB Rev 0.95
- Both USB micro-B connector and USB 5Pin Pinheader on board for UP board connection
- USB2.0 5Pin Pin Header Assignment: 5V, D-, D+, NC, GND
- Jumper selection either power wafer of external 5V sufficient power or 5V USB bus power to PCBA & mSATA SSD
- On board activity LED for mSATA accessing
- Includes 2 mSATA screws for the retention of mSATA module
- Includes HAT mounting accessory of standoff & nut & screw
- Fully RoHS compliant

2. Installation

1. Make sure your UP board is not powered on or connected to the power adapter.
2. Use a USB Micro-B cable (**USB_m**) or 5Pin cable (**USB_P**) to connect this board to your UP board
3. Install mSATA drive to mSATA Port

USB 5Pin Connector Signal

	Label	Signal Name
○	GND	Signal ground
○	NC	Keyed
○	D+	USB D+ signal
○	D-	USB D- signal
○	+5V	USB +5V

For more information about your UP board, software, accessories and peripherals, please visit

www.up-community.org

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Interface Modules](#) category:

Click to view products by [Aaeon](#) manufacturer:

Other Similar products are found below :

[IFD8520](#) [cPCI-3544](#) [422CON](#) [ATX6022/14GP7](#) [ATX6022/8](#) [AX93221-24/48](#) [FC6A-EXM2](#) [OPT8AP-AE](#) [96RMKVM-19V1C-A](#) [60016-011](#) [60016-014](#) [60006-008](#) [60011-075](#) [HPCI-14S12U](#) [cBP-3208](#) [cBP-3062A](#) [FAB205-6P5](#) [ATX6022/6](#) [60016-012](#) [96RMKVM-17V1C-A](#) [MOS-1120Y-0201E](#) [96RMLCD-17V1-A](#) [96RMKVM-17V8C-A](#) [60004-005](#) [60016-017](#) [60006-009](#) [60016-035](#) [60016-034](#) [60016-031](#) [60016-030](#) [60016-026](#) [60016-024](#) [60016-018](#) [60016-007](#) [60016-005](#) [60007-002](#) [60006-010](#) [AXX10GBTWLHW3](#) [382-BBEH](#) [555-BDCL](#) [K6CMISZBI52](#) [426451401-3](#) [60011-093](#) [MIC-3620/3-BE](#) [MPCIE-UART-KIT02-R20](#) [RSM232](#) [PCIE-1680-AE](#) [BB-FOSTCDRI](#) [73-544-002](#) [UC-313](#)