



EL6692 | EtherCAT bridge terminal

The EtherCAT bridge terminal EL6692 enables real-time data exchange between EtherCAT strands with different masters. It also enables synchronisation of the distributed clocks of the individual strands. The power supply on the primary side (E-bus) comes from the E-bus, on the secondary side (RJ45) via an external connection. If several EL6692 are used, data traffic to the terminals on the other side can continue in the event of a power supply failure on one side. The bridge terminal can also be used for integrating a subordinate PC system as an EtherCAT slave.

Technical data	EL6692
Technology	primary side: E-bus (terminal strand), secondary side: 2 x 100 Mbit/s Ethernet, RJ45, In/Out
Ports	primary: E-bus, secondary: 2 x RJ45 EtherCAT input/output
Function	EtherCAT distributed clock synchronisation, data exchange
Cable length	100 m 100BASE-TX, secondary port
Hardware diagnosis	status LEDs
Power supply	primary: via the E-bus, secondary: via connector
Distributed clocks	yes
Electrical isolation	500 V (E-bus/secondary side)
Current consumption	E-bus: 120 mA; external: 60 mA/24 V (see documentation)
Bit width in the process image	16 bit SYNC input + IO input/output, max. 480 bytes in each direction
Current consumption power contacts	–
Current consumption E-bus	120 mA (E-bus), typ. 60 mA/24 V (external)
Special features	usable in TwinCAT as a reference clock, supports ADS over EtherCAT (AoE)
Weight	approx. 75 g
Operating/storage temperature	-25...+60 °C/-40...+85 °C
Relative humidity	95 %, no condensation
Vibration/shock resistance	conforms to EN 60068-2-6/EN 60068-2-27
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4
Protect. class/installation pos.	IP 20/variable
Approvals	CE, UL, Ex

Related products	
EL6695	EtherCAT bridge terminal

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Controllers](#) category:

Click to view products by [Beckhoff](#) manufacturer:

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)