

## SPECIFICATIONS

### 1502

**Description:** 1.5V/3V/4.5V/6V/9V/12V    0.5A    Power Supply  
**Input Voltage:**        115VAC        60Hz  
**Environment Temperature:**        25C°

	<b>MIN.</b>	<b>TYP.</b>	<b>MAX.</b>	<b>UNIT</b>
Output Voltage 1.5V	1.3		1.8	V
Output Voltage 3V	2.6		3.4	V
Output Voltage 4.5V	4.2		3.4	V
Output Voltage 6V	5.5		6.4	V
Output Voltage 9V	8.5		9.4	V
Output Voltage 12V	11.5		12.5	V
Output Current		0.5		A
Voltage Regulation:				
Load (0-100% Load)			120	mV
Line (110-130VAC Variation)			300	mV
Ripple & Noise			200	mVp-p
No Load Input Current			80	mA
Full Load Input Current (All Rated Load)			180	mA
Fuse 1		2		A
Fuse 2		0.5		A

**Dimensions (W X D X H):** 4.33 x 5.51 x 3.27"

**Weight:** 2.43 lbs.

**Operation:**

Plug model 1502 into AC outlet. Turn power switch on, power light will come on.  
Adjust control knob to desired voltage.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Benchtop Power Supplies](#) category:*

*Click to view products by [B&K Precision](#) manufacturer:*

Other Similar products are found below :

[NL200](#) [PR20](#) [ZUPNC403](#) [ZUP/W](#) [ZUPNC402](#) [TL89F2](#) [TL89K1](#) [TL89T1](#) [1332A-NIST](#) [CPX200DP](#) [AX-3003P](#) [AX-6003P](#) [AX-8450A](#)  
[TPM-3003](#) [HMP2020](#) [HMP2030](#) [HMP4040](#) [1350](#) [UT804](#) [1410](#) [XLNRC](#) [1513](#) [1514](#) [1550](#) [1651A](#) [1665](#) [1666](#) [1667](#) [1693](#) [1694](#) [1698](#)  
[MX100TP](#) [1739](#) [1788](#) [TPM-3005](#) [1902B](#) [9174B](#) [GDM-8245](#) [GDM-8255A](#) [GDM-8341](#) [PSP-603](#) [PSW 160-7.2](#) [QL355P SII](#) [HCS-3400-](#)  
[USB](#) [MX180T](#) [MX180TP](#) [382276](#) [1403](#) [RK153](#) [ENP-120-48](#)