

Data Sheet

4 MHz Sweep Function Generators Models 4001A & 4003A



4001A



4003A

Models 4001A and 4003A are 4 MHz sweep function generators. The sweep function offers linear or log sweep with variable sweep rates and widths. The model 4003A has the addition of a 20 MHz 5-digit external frequency counter.

Features

- Generates Sine, Triangle, & Square waveforms from 0.5 Hz to 4 MHz
- 20 Vpp output into open circuit (10 Vpp into 50 Ω)
- TTL output <25 ns
- ±10 V DC offset
- Variable amplitude output plus 20 dB attenuator
- Kensington security slot

4003A Additional Features

- CMOS variable level output
- 5-digit LED display
- Voltage Controlled Frequency (VCF) input



Kensington security slot helps secure your function generator and prevents theft.



Model	4001A	4003A
Main Output		
Frequency Range	0.5 Hz to 4 MHz in 6 Ranges	
Waveforms	6 Waveforms (Sine, Square, Triangle, Ramp, +Pulse, -Pulse)	
Amplitude	0.2 Vpp - 20 Vpp (no load), 0.1 Vpp - 10 Vpp (50 Ω load)	
Attenuator	-20 db (±2%)	
Output Impedance	50 Ω (±2%)	
DC Offset	±10 V (pull ADJ.)	
Distortion	<2%, 1 Hz to 100 kHz	
Rise/Fall Time	<90 ns	
VCF Input	0 to 10 V control	
SYNC Output		
Rise Time	<60 ns (TTL), <90 ns (CMOS)	
Level	approx. 3 Vpp (TTL), variable 4 Vpp - 15 Vpp [±1 Vpp] (CMOS)	
Waveforms	Square, Pulse	
Sweep		
Mode	Linear/Log Sweep	
Rate	5s to 10 ms Continuously Variable	
Sweep Output	10 Vpp (open)	
Output Impedance	1 kΩ ±2%	
Frequency Counter		
Display	-	5-digit LED display with Autorange
Resolution	-	0.01 Hz
MODE	-	INT Function Generator/EXT Counter
Accuracy	-	< 0.02% ± 1 digit, for ≥ 1 kHz
Frequency Range	-	0.2 Hz~20 MHz
Sensitivity	-	<100 mVrms (1 MHz), <200 mVrms (>1 MHz)
Max Input	-	<150 Vrms
Input Impedance	-	1 MΩ ±2%
AC Input	AC 115V/230 V +10%, 50/60 Hz	
Dimension	11" x 3.6" x 11.9" (279.4 x 91.4 x 302.3 mm)	
Net Weight	5.5 lbs. (2.5 kg)	
One-Year Warranty		
Supplied Accessories	Power cord and user manual	

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Function Generators & Synthesisers](#) category:

Click to view products by [B&K Precision](#) manufacturer:

Other Similar products are found below :

[3001](#) [CT3734](#) [4010A](#) [SFG-210](#) [SFG-205](#) [33502A/903](#) [4013B](#) [AD9166BBPZ](#) [CT3736](#) [FIT0778](#) [28II](#) [28IIEX/ETL](#) [3446GPBU](#)
[EDU33211A](#) [EDU33212A](#) [U2010A](#) [MOKU:GO M1 \(STORM\)](#) [MOKU:GO M0 \(STORM\)](#) [MOKU:GO M2 \(STORM\)](#) [MOKU:GO M0](#)
[\(WHITE\)](#) [MOKU:GO M1 \(WHITE\)](#) [MOKU:GO M2 \(WHITE\)](#) [IZD0024](#) [114991659](#) [T3AFG10](#) [T3AFG120](#) [T3AFG500](#) [T3AFG40](#) [T3AFG5](#)
[T3AFG30](#) [T3AFG60](#) [T3AFG80](#) [W09-4A-12V](#) [33509B](#) [33519B](#) [33512B](#) [33520B](#) [33522B](#) [AFG31051](#) [AFG31101](#) [AFG31152](#) [AFG31251](#)
[AFG31252](#) [CT3733](#) [33510B/903](#) [4011A](#) [33509B/903](#) [33511B/903](#) [33612A](#) [4010](#)