


PmodACL™ Reference Manual

Revised April 15, 2016

This manual applies to the PmodACL rev. E

Overview

The Digilent PmodACL is a 3-axis digital accelerometer module powered by the [Analog Devices® ADXL345](#).



The PmodACL.

Features include:

- 3-axis, $\pm 2/4/8/16g$ accelerometer
- User-selectable resolution
- Activity/inactivity monitoring
- Single/double-tap and free-fall detection
- Small PCB size for flexible designs 1.0 in \times 0.8 in (2.5 cm \times 2.0 cm)
- 12-pin Pmod port with SPI interface and 2 \times 4-pin I²C interface
- Follows Digilent Pmod Interface Specification Type 2A
- Library and example code available in [resource center](#)

1 Functional Description

The PmodACL utilizes Analog Devices ADXL345 to provide high resolution acceleration changes including inclination changes of less than 1.0°. With free fall and single/double-tap detection capabilities, the PmodACL can be configured to take measurements on the user's whim.

2 Interfacing with the Pmod

The PmodACL communicates with the host board via the SPI protocol or the I²C protocol. SPI communication is enabled when the Chip Select line is driven low; conversely, the I²C protocol is enabled when the Chip Select line is driven to a logic level high voltage. An interrupt can be triggered whenever a measured axis acceleration data is over a user-defined threshold limit. A data stream setting the threshold activity to a value of 250 mg and Interrupt 1 to be triggered whenever the X and Y axis exceeds the threshold level through SPI is provided below in Table 1.

Read/~Write	Multi-byte	6-bit Threshold Activity Address					
0	0	1	0	0	1	0	0
8 bits of Threshold Activity data (62.5 mg/LSB scale)							
0	0	0	0	0	1	0	0
Read/~Write	Multi-byte	6-bit Activity/Inactivity Control Address					
0	0	1	0	0	1	1	1
Activity/Inactivity Control Settings							
ACT ac/dc	ACT X	ACT Y	ACT Z	INACT ac/dc	INACT X	INACT Y	INACT Z
0	1	1	0	0	0	0	0
Read/~Write	Multi-byte	6-bit Interrupt Enable Address					
0	0	1	0	1	1	1	0
8 bits of Which Interrupt Sources Are Enabled							
Data Ready	Single Tap	Double Tap	Activity	Inactivity	Free Fall	Watermark	Overrun
0	0	0	1	0	0	0	0

Table 1. Data stream setting the threshold activity through SPI

Once an interrupt has been generated, users may read the data registers (0x32 - 0x37) for the 10 bits of two's complement data in the X, Y, and Z axes, respectively. The data in the two registers for each axis is right-justified with sign extensions as the leading 6 bits. Reading the Interrupt source register (0x30) clears the activity interrupt bit D4.

Users may also follow the given [example code](#) functions and demonstration to start collecting accelerometer data.

2.1 Pinout Description Table

Pin	Signal	Description
1	~CS	Chip Select
2	MOSI	Master-out-slave-in
3	MISO	Master-in-slave-out
4	SCK	Serial Clock
5	GND	Power Supply Ground
6	VCC	Power Supply (3.3V)
7	INT2	Interrupt 2
8	INT1	Interrupt 1
9	NC	Not Connected
10	NC	Not Connected
11	GND	Power Supply Ground
12	VCC	Power Supply (3.3V)

Table 2. Pmod header J1.

Pin	Signal	Description
1, 5	SCL	Serial Clock
2, 6	SDA	Serial Data
3, 7	GND	Power Supply Ground
4, 8	VCC	Positive Power Supply

Table 3. Pmod header J2.

Any external power applied to the PmodACL must be within 2.0V and 3.6V; however, it is strongly recommended that the Pmod is operated at 3.3V.

3 Physical Dimensions

The pins on the pin header are spaced 100 mil apart. The PCB is 1 inch long on the sides parallel to the pins on the pin header and 0.8 inches long on the sides perpendicular to the pin header.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Acceleration Sensor Development Tools](#) category:

Click to view products by [Digilent](#) manufacturer:

Other Similar products are found below :

[2019](#) [EVAL-ADXL343Z-S](#) [BRKOUT-FXLN8362Q](#) [MXC6655XA-B](#) [1018](#) [EVAL-ADXL362-ARDZ](#) [EVAL-KXTJ2-1009](#) [1231](#) [1413](#) [DEV-13629](#) [2020](#) [EVAL-ADXL343Z-DB](#) [EVAL-ADXL344Z-M](#) [EVAL-ADXL375Z-S](#) [EV-BUNCH-WSN-1Z](#) [EV-CLUSTER-WSN-2Z](#) [STEVAL-MKI033V1](#) [EVAL-ADXL344Z-DB](#) [EVAL-ADXL346Z-DB](#) [EVAL-ADXL363Z-MLP](#) [EV-CLUSTER-WSN-1Z](#) [2472](#) [EVAL-ADXL312Z](#) [EVAL-ADXL343Z](#) [EVAL-ADXL344Z-S](#) [EVAL-ADXL363Z-S](#) [EVAL-ADXL375Z](#) [STEVALMKI032V1](#) [DFR0143](#) [SEN0032](#) [SEN0079](#) [SEN0168](#) [SEN0224](#) [MXD6240AU-B](#) [FIT0031](#) [SEN-13963](#) [MXP7205VW-B](#) [ASD2511-R-A](#) [3463](#) [SEN0140](#) [SEN0183](#) [SEN-11446](#) [EVAL-KX022-1020](#) [EVAL-KX023-1025](#) [163](#) [2809](#) [4097](#) [4344](#) [4627](#) [4626](#)