

## Plug Fuses

### MB Edison Base Circuit Breakers



#### Specifications

**Description:** Edison base manual reset circuit breakers.

**Dimensions:** Edison base

**Construction:** Brass threads with plastic body

#### Ratings:

Volts — 125Vac only

Amps — 15-20A

IR — 10kA RMS Sym.

**Agency Information:** UL Listed, File E14942

#### Features and Benefits

- Fit standard Edison base fuse receptacles.
- Resettable upon overload event.

#### Typical Applications\*

- Replacing Edison base plug fuses in residential fuse panels.

#### Catalog Numbers\* (Amps)

MB-15

MB-20

\* Not for use in box cover units or for inductive loads.

### Fustat Fuse Adapters



#### Specifications

**Description:** Adapters for using Type S and SL rejection fuses in Edison base fuse sockets.

#### Features and Benefits

- Fustat adapters screw into the “Edison” thread fuse sockets of standard fuse boxes making it easy to retrofit existing fuse installations
- Available in various amp ratings to cover a wide range of rating requirements

#### Typical Applications

- Plug fuse installations where it is desirable to restrict fuse amp ratings

#### Catalog Numbers (Amps)

SA-1*	SA-3- $\frac{3}{4}$ °*	SA-10*
SA-1- $\frac{1}{4}$ °*	SA-4*	SA-15**
SA-1- $\frac{5}{16}$ °*	SA-5*	SA-20**
SA-2*	SA-6- $\frac{1}{4}$ °*	SA-30**
SA-2- $\frac{1}{2}$ °*	SA-8*	

\* Single motor circuits.

\*\* Branch circuits.

#### Fustat® Adapters for Small Motor Protection\*

Adapter	Accepts Fuses
SA-1	S-1 or smaller
SA-1- $\frac{1}{4}$ °	S-1- $\frac{1}{4}$ or smaller
SA-1- $\frac{5}{16}$ °	S-1- $\frac{5}{16}$ or smaller
SA-2	S-2 or S-1- $\frac{5}{16}$
SA-2- $\frac{1}{2}$ °	S-2- $\frac{1}{2}$ to S-1- $\frac{5}{16}$
SA-3- $\frac{3}{4}$ °	S-3- $\frac{3}{4}$ to S-1- $\frac{5}{16}$
SA-4	S-4 to S-3- $\frac{1}{2}$
SA-5	S-5 to S-3- $\frac{1}{2}$
SA-6- $\frac{1}{4}$ °	S-6- $\frac{1}{4}$ to S-3- $\frac{1}{2}$
SA-8	S-8 to S-7
SA-10	S-10 to S-7
SA-15	S-15 to S-7
SA-20	S-20
SA-30	S-30 to S-20

\* Both motor running and short-circuit protection.

#### Fustat® Adapters for Branch Circuit Protection

Adapter	Accepts Fuses
SA-15	S-15 to S-7
SA-20	S-20
SA-30	S-25
SA 30	S-30 to S-20

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Fuse Holder Accessories](#) category:*

*Click to view products by [Eaton](#) manufacturer:*

Other Similar products are found below :

[BK/1A1337](#) [BK/2A1460](#) [BP/FP-2](#) [903-048](#) [9732](#) [CO2-10](#) [CO3-03](#) [B001-7018/J](#) [B072-7007](#) [BK/1A1853](#) [BK/1A4421](#) [BK/1A6049](#)  
[BK/9732](#) [X30110](#) [09030012H](#) [0904216001](#) [09050023H](#) [FHM20200ZPA](#) [FHM20200Z](#) [BK/9834](#) [901-108](#) [00970021HXNVDL](#) [00BS0232P](#)  
[CO2-04](#) [BK1A1853](#) [BK9835](#) [BK-HHT](#) [BK9834](#) [0880.0001](#) [00970053XP](#) [3566C](#) [04450718ZX900](#) [BP/FP-3](#) [B001-7007/J](#) [359.5900.087](#)  
[868-951](#) [868-952](#) [868-953](#) [868-955](#) [868-956](#) [58600000005](#) [33-012C](#) [09230025LXREDM8](#) [01520903TXN](#) [882-267-002](#) [882-267-003](#)  
[LFLX0006Z-01](#) [880140](#) [00970023S](#) [880150](#)