

Online UPS, 2000 VA

EG-UPSO-2000

ULTIMATE DEFENCE

- Protects important data from power cuts
- Protects valuable equipment
- Protects users



Features

- Online type UPS: double voltage conversion without switching the power
- USB control interface
- LCD display
- Short circuit protection
- Compatible with power generators of any brand
- Surge, spike and lightning protection
- Audible and visual alarms
- Overcharge and overdischarge protection

Packaging

Q'ty in crtn, pcs	1
Crtn volume, CUM	0.061404
Crtn weight, kgs	23.18
Individual package size LxWxH:	510x280x430 mm
Carton size LxWxH:	510x280x430 mm
Country of origin	CN
Barcode	8716309124829
Customs code	8504408590

Package contents

- UPS
- Power cord
- USB cable
- Software CD
- Spare fuse

Specifications

UPS type: online, pure sine wave
 Input: 220V AC \pm 25%, 50Hz / 60Hz \pm 10%
 Output: 220V AC \pm 1%, 50Hz / 60Hz \pm 0.5% (on battery)
 Output power factor: 0.9
 Inverter output efficiency (resistive load): 85%, any load type is allowed
 Switching time: zero
 Backup time: 8...20 mins (depends on the load)
 Battery: 151 x 65 x 95 mm, sealed lead-acid 12 V / 7 Ah x 6 pcs (72 VDC)
 Charge time: 90% capacity restored in 3 hours
 External battery connectors: yes

System requirements

In order to work correctly, the connected load should be at least 5% of the maximum capacity of the UPS. For example, a 700 W UPS needs at least a connected load of 35 W to work.

Certificates



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [UPS - Uninterruptible Power Supplies](#) category:

Click to view products by [Gembird](#) manufacturer:

Other Similar products are found below :

[SMART-1400-RM](#) [UPS1500ITSIT](#) [QUINT4-UPS/24DC/24DC/20/EI](#) [QUINT4-UPS/24DC/24DC/40/EI](#) [QUINT4-UPS/24DC/24DC/10/US](#)
[QUINT4-UPS/24DC/24DC/20/US](#) [QUINT4-UPS/24DC/24DC/40/US](#) [2789910000](#) [2786240000](#) [5AVRZP2000](#) [51942](#) [50717](#) [50719](#) [EG-](#)
[UPS-035](#) [51945](#) [50725](#) [50721](#) [50177](#) [EG-UPS-PS3000-02](#) [51940](#) [50720](#) [UPS-RACK-1200](#) [5AVRZP5000](#) [50722](#) [5AVRZP1000](#) [50351](#)
[51944](#) [50726](#) [EG-UPS-PS2000-02](#) [51941](#) [5AVR3000SE](#) [EG-UPS-036](#) [50724](#) [EG-UPSO-1000](#) [EG-UPS-PS1000-01](#) [SDUCFRELAYCARD](#)
[SDUCFRELAYCARD](#) [SDUMBUSCARD](#) [50348](#) [ISRELAY](#) [6EP1931-2EC21](#) [6EP1933-2EC51](#) [SDU-24-BAT](#) [6EP1931-2DC21](#) [AK-B1-](#)
[500E](#) [AK-B1-700BE](#) [AK-I1-200](#) [AK-I2-150](#) [AK-S1-300](#) [AK-T1-250](#)