

1000VA pure sine wave UPS, LCD display, USB, black

EG-UPS-PS1000-01

ULTIMATE DEFENCE

- Pure sine wave output
- Provide backup power Prevents data loss
- Protects your sensitive and valuable equipment
- Perfect support for solar panel installations and other sensitive equipment that requires pure sinewave input
- Compact and reliable ideal for home and small office use



Features

- Uninterruptable power supply with pure sine wave output
- USB interface
- Automatic AC voltage regulation (AVR)
- Intelligent overload and short-circuit protection
- Audible and visual alarms
- LCD display and LED status indication
- Internal battery with overcharge and over-discharge protection

Packaging

Q'ty in crtn, pcs	1
Crtn volume, CUM	0.039375
Crtn weight, kgs	14.15
Individual package size LxWxH:	492x316x236 mm
Carton size LxWxH:	450x250x350 mm
Country of origin	CN
Barcode	8716309124782
Customs code	8504408590

Package contents

UPS
Power cord
Spare fuse

Specifications

Type: line interactive with pure sine wave
Waveform: sine, 5% distortion at linear load, PF > 0.8 (on battery)

Input: AC 220V±25%, 50Hz/60Hz ±10%
Output: AC 220V±10%, 50Hz/60Hz ±1% (AC 220V±10% at inverter mode)
Switching time: up to 10 ms
Backup time: 10...30 mins (depends on the load)
Battery: 151 x 65 x 94 mm, sealed lead-acid 12V/7Ah, F2 terminals x 2 pcs
Charge time: up to 90% after 6-8 hours
Sockets: C14 input, outputs: Schuko EU type x 1 pc, IEC C13 x 3 pcs

System requirements

In order to work correctly, the connected load should be at least 5% of the maximum capacity of the UPS. For example, a 700 W UPS needs at least a connected load of 35 W to work.

Certificates



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [UPS - Uninterruptible Power Supplies](#) category:

Click to view products by [Gembird](#) manufacturer:

Other Similar products are found below :

[SMART-1400-RM](#) [UPS1500ITSIT](#) [QUINT4-UPS/24DC/24DC/20/EI](#) [QUINT4-UPS/24DC/24DC/40/EI](#) [QUINT4-UPS/24DC/24DC/10/US](#)
[QUINT4-UPS/24DC/24DC/20/US](#) [QUINT4-UPS/24DC/24DC/40/US](#) [2789910000](#) [2786240000](#) [5AVRZP2000](#) [51942](#) [50717](#) [50719](#) [EG-](#)
[UPS-035](#) [51945](#) [50725](#) [50721](#) [50177](#) [EG-UPS-PS3000-02](#) [51940](#) [50720](#) [UPS-RACK-1200](#) [5AVRZP5000](#) [50722](#) [5AVRZP1000](#) [50351](#)
[51944](#) [50726](#) [EG-UPS-PS2000-02](#) [51941](#) [5AVR3000SE](#) [EG-UPS-036](#) [50724](#) [EG-UPSO-1000](#) [EG-UPS-PS1000-01](#) [SDUCFRELAYCARD](#)
[SDUCFRELAYCARD](#) [SDUMBUSCARD](#) [50348](#) [ISRELAY](#) [6EP1931-2EC21](#) [6EP1933-2EC51](#) [SDU-24-BAT](#) [6EP1931-2DC21](#) [AK-B1-](#)
[500E](#) [AK-B1-700BE](#) [AK-I1-200](#) [AK-I2-150](#) [AK-S1-300](#) [AK-T1-250](#)