

Rack 2000VA UPS

UPS-RACK-2000

ULTIMATE DEFENCE

- Protects important data from power cuts
- Protects valuable equipment
- Protects users



Features

- Automatic output voltage regulation (AVR)
- Rack 3.4U metal case
- USB control interface
- LCD display
- Short circuit protection
- Compatible with power generators of any brand
- Surge, spike and lightning protection
- Audible and visual alarms
- Overcharge and overdischarge protection

Packaging

Q'ty in crtn, pcs	1
Crtn volume, CUM	0.04922
Crtn weight, kgs	16.41
Individual package size LxWxH:	535x400x230 mm
Carton size LxWxH:	535x400x230 mm
Country of origin	CN
Barcode	8716309124768
Customs code	8504408590

Package contents

- UPS
- Power cord
- USB cable
- Software CD
- Spare fuse

Specifications

UPS type: line interactive
 Input: 220V AC \pm 25%, 50Hz / 60Hz \pm 10%
 Output: 220V AC \pm 10%, 50Hz / 60Hz \pm 0.5% (on battery)
 Switching time: no more than 10 ms (typically 6 ms)
 Backup time: 8...20 mins (depends on the load)
 Battery: 151 x 65 x 95 mm, sealed lead-acid 12 V / 9 Ah / 2.5 kg x 2 pcs
 Charge time: up to 12 hours
 Sockets: IEC13 output x 2 pcs, german Shuko x 2 pcs; input IEC14, USB-BF control interface, telephone input/output
 Operating conditions: 0°C~40°C, at humidity 10~90%RH non condensing
 Noise: < 45 dB (at 1 meter distance)

System requirements

In order to work correctly, the connected load should be at least 5% of the maximum capacity of the UPS. For example, a 700 W UPS needs at least a connected load of 35 W to work.

Certificates



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [UPS - Uninterruptible Power Supplies](#) category:

Click to view products by [Gembird](#) manufacturer:

Other Similar products are found below :

[UPS1500ITSIT](#) [TRIO-UPS-2G/3AC/24DC/20](#) [QUINT4-UPS/24DC/24DC/20/EI](#) [QUINT4-UPS/24DC/24DC/40/EI](#) [QUINT4-UPS/24DC/24DC/10/US](#) [QUINT4-UPS/24DC/24DC/20/US](#) [QUINT4-UPS/24DC/24DC/40/US](#) [2789910000](#) [2786240000](#) [2789890000](#) [5AVRZP2000](#) [51942](#) [50717](#) [50719](#) [50725](#) [50177](#) [5AVR2000SE](#) [51940](#) [UPS-RACK-1200](#) [5AVRZP5000](#) [50722](#) [5AVRZP1000](#) [50351](#) [50726](#) [51941](#) [5AVR3000SE](#) [50724](#) [5AVRZP3000](#) [UPS-RACK-2000](#) [50728](#) [AVR-3000 PRO](#) [AVR-1000 PRO](#) [5AVRZ10000](#) [50718](#) [50723](#) [WAKSPOWER11-G4-06K0-RT-BC192](#) [5AVR0500SE](#) [5AVR1000SE](#) [50727](#) [AK-C1-600](#) [50342](#) [AK-C1-800](#) [AVR-2000 PRO](#) [WAKSPOWER11-G4-10K0-RT-BC192](#) [AK-C1-500](#) [EG-UPS0-10000](#) [TSPC 240-124UPS](#) [SDUCFRELAYCARD](#) [SDUCFRELAYCARD](#) [SDUMBUSCARD](#)