

GPE-X323 Series



FEATURES


- 1/2/3/4 Independent Isolated Output
- 4.3 Inch LCD Display
- Setting & Read Back Resolution 100mV/10mA (*1)
- Output On/off
- Analog Control (Remote I/O) For Output ON/OFF
- Set View Function For Checking an Original V/I Setting During Output On
- Key Lock Function
- Tracking Series And Parallel Operation
- Smart Cooling Fan Achieving Low Noise
- Optional European Jack Type Terminal



The GPE-X323 series is cutting edge, economical linear DC Power supplies. The GPE-X323 series features output power from 192 to 217 watts, three independent isolated output channels (for GPE-3323), high resolution, low noise, high reliability, and compact size. The GPE-X323 series has a built-in digital panel control design to replace conventional control method. This unique design allows the GPE-X323 series linear DC power supply to provide users with more efficient functionalities, including set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage and current parameters. Additionally, output key light facilitates users in clearly reading the operational status of power supply.

Tracking Series and Parallel Operation

In addition to independent output channels, the GPE-X323 series provides tracking series and parallel operation (For GPE-2323/GPE-3323/GPE-4323). The series and parallel connections allow power supplies to output 32V/6A (Parallel Connection) and 64V/3A (Series Connection).



Internal connection for tracking Series and Parallel operation via control panel

Convenient Function


The GPE-X323 series has a built-in set view and key lock so as to expedite the operation process. The key lock function protects DUTs by preventing others from changing voltage/current parameters.



The key lock function prevent DUTs from unnecessary damages caused by mis-operation.

Remote I/O for output On/Off function

The GPE-X323 Series also provides the analog control (Remote I/O) function for external output On/Off control.



For controlling the output On/Off function through the specific pin assignment of remote control connector which is in rear panel.



Front



Rear Panel

APPLICATIONS

- Laboratories and Educational Facilities
- Product Testing and Quality Assurance
- Service Operation and Post-Sales Support
- Product Development and Debugging

SPECIFICATIONS

| | | GPE-4323 | | | | GPE-3323 | | | GPE-2323 | | GPE-1326 | | |
|------------------------------|---|--|--|--|---|---|-------|-----|----------|-------|----------|-------|--|
| OUTPUT MODE | Number of Channel Voltage Current Tracking Series Voltage Tracking Parallel Current | CH1 | CH2 | CH3 | CH4 | CH1 | CH2 | CH3 | CH1 | CH2 | CH1 | | |
| | | 0~32V | 0~32V | 0~5V | 0~15V | 0~32V | 0~32V | 5V | 0~32V | 0~32V | 0~32V | 0~32V | |
| | | 0~3A | 0~3A | 0~1A | 0~1A | 0~3A | 0~3A | 5A | 0~3A | 0~3A | 0~6A | | |
| | | 0~64V | 0~6A | - | | 0~64V | - | | 0~64V | 0~6A | - | | |
| CONSTANT VOLTAGE OPERATION | Line Regulation Load Regulation Ripple & Noise Recovery Time | $\leq 0.01\%+3mV$ $\leq 0.01\%+3mV$ (rating current $\leq 3A$); $\leq 0.02\%+5mV$ (rating current $> 3A$) $\leq 1mVrms$ (5Hz~1MHz) $\leq 100\mu s$ (50% Load Change, minimum load 0.5A) | | | | | | | | | | | |
| | | CONSTANT CURRENT OPERATION | Line Regulation Load Regulation Ripple & Noise | $\leq 0.2\%+3mA$ $\leq 0.2\%+3mA$ $\leq 3mArms$ | | | | | | | | | |
| TRACKING OPERATION (CH1,CH2) | Tracking Error Parallel Regulation Series Regulation Ripple & Noise | | | $\leq 0.1\%+10mV$ of Master(0~32V) No Load , with Load add load regulation $\leq 100mV$ Line : $\leq 0.01\%+3mV$ Load : $\leq 0.01\%+3mV$ (rating current $\leq 3A$); $\leq 0.02\%+5mV$ (rating current $> 3A$) Line : $\leq 0.01\%+5mV$ Load : $\leq 100mV$ $\leq 2mVrms$, 5Hz ~ 1MHz | | | | | | | | | |
| | | CH3 OPERATION FOR (GPE-3323) | Output Voltage Output Current Line Regulation Load Regulation Ripple & Noise | 5.0V, $\pm 5\%$ 5A $\leq 3mV$ $\leq 5mV$ 1mVrms(5Hz~1MHz) | | | | | | | | | |
| | | | | METER | Voltage Resolution Current Resolution Setting Accuracy Readback Accuracy | 100mV (*1) 10mA (*1) Voltage \pm (0.1% of reading +30mV); Current \pm (0.3% of reading +6mA) Voltage \pm (0.1% of reading +30mV); Current \pm (0.3% of reading +6mA) | | | | | | | |
| INSULATION | Chassis and Terminal Chassis and AC Cord | 20M Ω or above (DC 500V) 30M Ω or above (DC 500V) | | | | | | | | | | | |
| | | ENVIRONMENT CONDITION | Operation Temp Storage Temp Operating Humidity Storage Humidity | 0~40 $^{\circ}C$ -10~70 $^{\circ}C$ $\leq 80\%$ RH $\leq 70\%$ RH | | | | | | | | | |
| OTHER | Power Source Dimensions & Weight | | | AC100V/120V/220V $\pm 10\%$; 230V(+10%~-6%); 50/60Hz 210(W)x 155(H) x 306(D) mm ; Approx. 7kg | | | | | | | | | |

Note : (*1) For a higher resolution (10mV/1mA), please follow the setting procedure of the user manual on p35.
When using a higher resolution, the current or voltage adjustment may be limited by the knob sensibility.

Specifications subject to change without notice. PE-x303CD1DH

ORDERING INFORMATION

GPE-1326 Single Channel, 192W Linear DC Power Supply
GPE-2323 2 Channels, 192W Linear DC Power Supply
GPE-3323 3 Channels, 217W Linear DC Power Supply
GPE-4323 4 Channels, 212W Linear DC Power Supply

ACCESSORIES

User Manual (CD) x 1 ; Power Cord x 1
GPE-1326 Test Lead GTL-104A x 1; GTL-105 x 1 ; or European GTL-204A x 1, GTL-203A x1
GPE-2323 Test Lead GTL-104A x 2; or European GTL-204A x 2
GPE-3323 Test Lead GTL-104A x 3; or European GTL-204A x 3
GPE-4323 Test Lead GTL-104A x 2; GTL-105A x 2 or European GTL-204A x 2, GTL-203A x 2

Global Headquarters

GOOD WILL INSTRUMENT CO., LTD.

No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan
 T +886-2-2268-0389 F +886-2-2268-0639
 E-mail: marketing@goodwill.com.tw

China Subsidiary

GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.

No. 521, Zhujiang Road, Snd, Suzhou Jiangsu 215011 China
 T +86-512-6661-7177 F +86-512-6661-7277
 E-mail: marketing@instek.com.cn

Malaysia Subsidiary

GOOD WILL INSTRUMENT (SEA) SDN. BHD.

No. 1-3-18, Elit Avenue, Jalan Mayang Pasir 3,
 11950 Bayan Baru, Penang, Malaysia
 T +604-6111122 F +604-6115225
 E-mail: sales@goodwill.com.my

Europe Subsidiary

GOOD WILL INSTRUMENT EURO B.V.

De Run 5427A, 5504DG Veldhoven, THE NETHERLANDS
 T +31(0)40-2557790 F +31(0)40-2541194

U.S.A. Subsidiary

INSTEK AMERICA CORP.

5198 Brooks Street Montclair, CA 91763, U.S.A.
 T +1-909-399-3535 F +1-909-399-0819
 E-mail: sales@instekamerica.com

Japan Subsidiary

TEXIO TECHNOLOGY CORPORATION.

7F Towa Fudosan Shin Yokohama Bldg., 2-18-13 Shin
 Yokohama, Kohoku-ku, Yokohama, Kanagawa,
 222-0033 Japan
 T +81-45-620-2305 F +81-45-534-7181
 E-mail: info@texio.co.jp

Korea Subsidiary

GOOD WILL INSTRUMENT KOREA CO., LTD.

Room No.503, Gyeonginro 775 (Mullae-Dong 3Ga,
 Ace Hightech-City B/D 1Dong), Yeongduengpo-Gu,
 Seoul 150093, Korea.
 T +82-2-3439-2205 F +82-2-3439-2207
 E-mail : gwinstek@gwinstek.co.kr

GW INSTEK
 Simply Reliable



www.gwinstek.com

www.facebook.com/GWInstek

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Power Management Specialised - PMIC category](#):

Click to view products by [GW Connect manufacturer](#):

Other Similar products are found below :

[P9145-I0NQGI](#) [SLG7NT4192VTR](#) [AS3729B-BWLM](#) [TLE92623QXV33XUMA1](#) [LNBH25SPQR](#) [ADP5080ACBZ-1-RL](#)

[MC32PF3000A6EP](#) [MB39C831QN-G-EFE2](#) [MAX9959DCCQ+D](#) [MAX1932ETC+T](#) [MAX1856EUB+T](#) [STNRG011TR](#)

[IRPS5401MXI03TRP](#) [S6AE102A0DGN1B200](#) [MMPF0100FDAEP](#) [MCZ33903DS5EK](#) [S6AE101A0DGNAB200](#) [MCZ33903DS3EK](#)

[NCP6924CFCHT1G](#) [MAX17117ETJ+](#) [MCZ33903DS3EKR2](#) [L9916](#) [L9915-CB](#) [MCZ33904D5EK](#) [MCZ33905DS3EK](#) [MMPF0100FCANES](#)

[MCZ33905DD3EK](#) [MMPF0100FBANES](#) [WM8325GEFL/V](#) [MCZ33903DP5EK](#) [MCZ33905DS5EK](#) [MCZ33903D3EK](#) [MCZ33903DD5EK](#)

[ADN8835ACPZ-R7](#) [MCZ33903DP5EKR2](#) [MCZ33903D5EK](#) [MCZ33903DD3EK](#) [MMPF0100FAAZES](#) [SLG7NT4198V](#) [MIC5164YMM](#)

[P9180-00NHGI](#) [NCP6914AFCAT1G](#) [TLE9261QX](#) [TEA1998TS/1H](#) [MAX881REUB+T](#) [TLE9262QX](#) [TLE8880TN](#) [MAX8520ETP+T](#)

[SLG7NT4083V](#) [ADP1031ACPZ-1-R7](#)