



Quality Products. Service Excellence.

Tube Guitar Amplifier - Chokes 194 Series

REPLACEMENT & UPGRADES

Features



- Designed for drop in replacement of original units.
- Physically, parts were designed to look similar to original factory units (where possible).
- Inductances measured at rated D.C. current.
- Material used & design specs. were kept as close as possible to the original part to preserve the stock "tone".
- Units are vacuum impregnated with polyurethane varnish for quiet and long life operation
- "Click" on thumbnail photos below for a full size photo of each part.



Fender (Power Supply Chokes)

| Hammond Part No. | Inductance +/- 15% | D.C. Current | Amplifier Manufacturer | Amplifier Model Names | Equivalent To Manufacturer Part No |
|------------------|--------------------|--------------|------------------------|--|------------------------------------|
| 194A | 4 H | 50 ma. | Fender | Deluxe, Deluxe Reverb, Vibrolux, Vibrolux Reverb | 125C3A & 022707 |
| 194B | 4 H | 90 ma. | Fender | Bandmaster, Dual Showman, Pro Reverb, Twin Super | 125C1A & 022699 |

Marshall (Power Supply Chokes)

| Hammond Part No. | Inductance +/- 15% | D.C. Current | Amplifier Manufacturer | Amplifier Model Names | Equivalent To Manufacturer Part No |
|------------------|--------------------|--------------|------------------------|--|------------------------------------|
| 194G | 3H | 250 ma. | Marshall | Plexi | - |
| 194F | 5 H | 120 ma. | Marshall | Later Mark II and 800 (50 & 100 Watt) not Plexis | - |
| 194C | 40 H | 50 ma. | Marshall | Pre-amp Plexi/JCM800 | - |

VOX (Power Supply Chokes)

| Hammond Part No. | Inductance +/- 15% | D.C. Current | Amplifier Manufacturer | Amplifier Model Names | Similar To Manufacturer Part No |
|------------------|--------------------|--------------|------------------------|-----------------------|---------------------------------|
| 194D | 5 H | 150 ma. | VOX | AC30 reissue | - |
| 194E | 30 H | 100 ma. | VOX | AC30 reissue | - |

YORKVILLE SOUND / TRAYNOR (Power Supply Chokes)

| Hammond Part No. | Inductance +/- 15% | D.C. Current | Amplifier Manufacturer | Amplifier Model Names | Similar To Manufacturer Part No |
|------------------|--------------------|--------------|------------------------|-----------------------|---------------------------------|
| 159Q | 7H | 150 ma. | Yorkville | Bassmaster YBA-1 | A-1311 |

* DISCLAIMER: Hammond Mfg. is not affiliated with Fender Musical Instruments Corp., Marshall Amplification, Yorkville/Traynor, AMPEG or VOX Amplification companies. Amplifier model names are trademarks of the Amplifier companies and are just listed here for reference purpose only.

Data subject to change without notice

© 2022. Hammond Manufacturing Ltd. All rights reserved.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Fixed Inductors](#) category:

Click to view products by [Hammond](#) manufacturer:

Other Similar products are found below :

[CR32NP-100KC](#) [CR43NP-680KC](#) [CR54NP-820KC](#) [CR54NP-8R5MC](#) [CTX32CT-100](#) [70F224AI](#) [MGDQ4-00004-P](#) [MHL1ECTTP18NJ](#)
[MHL1JCTTD12NJ](#) [PE-51506NL](#) [PE-53601NL](#) [PE-53602NL](#) [PE-53630NL](#) [PE-53824SNLT](#) [PE-62892NL](#) [PE-92100NL](#) [PG0434.801NLT](#)
[PG0936.113NLT](#) [9310-16](#) [PM06-2N7](#) [PM06-39NJ](#) [A01TK](#) [1206CS-471XJ](#) [HC2-2R2TR](#) [HC2LP-R47-R](#) [HC3-2R2-R](#) [1206CS-151XG](#)
[RCH664NP-140L](#) [RCH664NP-4R7M](#) [RCH8011NP-221L](#) [RCP1317NP-332L](#) [RCP1317NP-391L](#) [RCR1010NP-470M](#) [RCR110DNP-331L](#)
[DH2280-4R7M](#) [DS1608C-106](#) [ASPI-4020HI-R10M-T](#) [B10TJ](#) [B82477P4333M](#) [B82498B3101J000](#) [B82498B3680J000](#) [ELJ-RE27NJF2](#)
[1812CS-153XJ](#) [1812CS-183XJ](#) [1812CS-223XJ](#) [1812LS-104XJ](#) [1812LS-105XJ](#) [1812LS-124XJ](#) [1812LS-154XJ](#) [1812LS-223XJ](#)