



# Power Schottky Rectifier with common cathode

**I<sub>FAV</sub>** = 2x35 A  
**V<sub>RRM</sub>** = 15 V  
**V<sub>F</sub>** = 0.33 V

## Preliminary Data

V <sub>RSM</sub>	V <sub>RRM</sub>	Type
V	V	
15	15	DSSK 70-0015B



A = Anode, C = Cathode , TAB = Cathode

Symbol	Conditions	Maximum Ratings	
I <sub>FRMS</sub>		70	A
I <sub>FAV</sub>	T <sub>C</sub> = 130°C; rectangular, d = 0.5	35	A
I <sub>FAV</sub>	T <sub>C</sub> = 130°C; rectangular, d = 0.5; per device	70	A
I <sub>FSM</sub>	T <sub>VJ</sub> = 45°C; t <sub>p</sub> = 10 ms (50 Hz), sine	650	A
E <sub>AS</sub>	I <sub>AS</sub> = tbd A; L = 180 µH; T <sub>VJ</sub> = 25°C; non repetitive	tbd	mJ
I <sub>AR</sub>	V <sub>A</sub> = 1.5 • V <sub>RRM</sub> typ.; f=10 kHz; repetitive	tbd	A
(dV/dt) <sub>cr</sub>		tbd	V/µs
T <sub>VJ</sub>		-55...+150	°C
T <sub>VJM</sub>		150	°C
T <sub>stg</sub>		-55...+150	°C
P <sub>tot</sub>	T <sub>C</sub> = 25°C	115	W
M <sub>d</sub>	mounting torque	0.8...1.2	Nm
Weight	typical	6	g

### Features

- International standard package
- Very low V<sub>F</sub>
- Extremely low switching losses
- Low I<sub>RM</sub>-values
- Epoxy meets UL 94V-0

### Applications

- Rectifiers in switch mode power supplies (SMPS)
- Free wheeling diode in low voltage converters

### Advantages

- High reliability circuit operation
- Low voltage peaks for reduced protection circuits
- Low noise switching
- Low losses

Dimensions see Outlines.pdf

Symbol	Conditions	Characteristic Values	
		typ.	max.
I <sub>R</sub>	① T <sub>VJ</sub> = 25°C V <sub>R</sub> = V <sub>RRM</sub> T <sub>VJ</sub> = 100°C V <sub>R</sub> = V <sub>RRM</sub>	20	mA
		350	mA
V <sub>F</sub>	I <sub>F</sub> = 35 A; T <sub>VJ</sub> = 125°C I <sub>F</sub> = 35 A; T <sub>VJ</sub> = 25°C I <sub>F</sub> = 70 A; T <sub>VJ</sub> = 125°C	0.33 0.45 0.45	V
R <sub>thJC</sub>		1.1	K/W
R <sub>thCH</sub>		0.25	K/W

Pulse test: ① Pulse Width = 5 ms, Duty Cycle < 2.0 %  
Data according to IEC 60747 and per diode unless otherwise specified

IXYS reserves the right to change limits, Conditions and dimensions.




Fig. 1 Maximum forward voltage drop characteristics




Fig. 2 Typ. value of reverse current  $I_R$  versus reverse voltage  $V_R$




Fig. 3 Typ. junction capacitance  $C_T$  versus reverse voltage  $V_R$




Fig. 4 Average forward current  $I_{F(AV)}$  versus case temperature  $T_C$




Fig. 5 Forward power loss characteristics




Fig. 6 Transient thermal impedance junction to case at various duty cycles

Note: All curves are per diode

# X-ON Electronics

Largest Supplier of Electrical and Electronic Components

***Click to view similar products for Schottky Diodes & Rectifiers category:***

***Click to view products by IXYS manufacturer:***

Other Similar products are found below :

[CUS06\(TE85L,Q,M\)](#) [MA4E2039](#) [D1FH3-5063](#) [MBR0530L-TP](#) [MBR10100CT-BP](#) [MBR30H100MFST1G](#) [MMBD301M3T5G](#) [PMAD1103-LF](#) [PMAD1108-LF](#) [RB160M-50TR](#) [RB520S-30](#) [RB551V-30](#) [DD350N18K](#) [DZ435N40K](#) [DZ600N16K](#) [BAS16E6433HTMA1](#) [BAS 3010S-02LRH E6327](#) [BAT 54-02LRH E6327](#) [IDL02G65C5XUMA1](#) [NSR05F40QNXT5G](#) [NSVR05F40NXT5G](#) [JANS1N6640](#) [SB07-03C-TB-H](#) [SB1003M3-TL-W](#) [SBAT54CWT1G](#) [SBM30-03-TR-E](#) [SBS818-TL-E](#) [SK32A-LTP](#) [SK33A-TP](#) [SK34A-TP](#) [SK34B-TP](#) [SMD1200PL-TP](#) [ACDBN160-HF](#) [SS3003CH-TL-E](#) [STPS30S45CW](#) [PDS3100Q-7](#) [GA01SHT18](#) [CRS10I30A\(TE85L,QM](#) [MBR1240MFST1G](#) [MBRB30H30CT-1G](#) [BAS28E6433HTMA1](#) [BAS 70-02L E6327](#) [HSB123JTR-E](#) [JANTX1N5712-1](#) [VS-STPS40L45CW-N3](#) [DD350N12K](#) [SB007-03C-TB-E](#) [SB10015M-TL-E](#) [SB1003M3-TL-E](#) [SK110-LTP](#)