


PNP Transistors

2SB624

■ Features

- High DC current gain. $hFE:200$ TYP.($V_{CE}=-1V, I_C=100mA$)
- Complimentary to 2SD596.

■ Absolute Maximum Ratings $T_a = 25^\circ C$

Parameter	Symbol	Rating	Unit
Collector - Base Voltage	V_{CBO}	-30	V
Collector - Emitter Voltage	V_{CEO}	-25	
Emitter - Base Voltage	V_{EBO}	-5	
Collector Current - Continuous	I_C	-700	mA
Collector Power Dissipation	P_C	200	mW
Junction Temperature	T_J	150	$^\circ C$
Storage Temperature range	T_{Stg}	-55 to 150	

■ Electrical Characteristics $T_a = 25^\circ C$

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Collector-base breakdown voltage	V_{CBO}	$I_C = -100 \mu A, I_E = 0$	-30			V
Collector-emitter breakdown voltage	V_{CEO}	$I_C = -1 mA, I_B = 0$	-25			
Emitter-base breakdown voltage	V_{EBO}	$I_E = -100 \mu A, I_C = 0$	-5			
Collector-base cut-off current	I_{CBO}	$V_{CB} = -30 V, I_E = 0$			-100	nA
Emitter cut-off current	I_{EBO}	$V_{EB} = -5V, I_C = 0$			-100	
Collector-emitter saturation voltage (Note.1)	$V_{CE(sat)}$	$I_C = -700 mA, I_B = -70mA$			-0.6	V
Base-emitter saturation voltage (Note.1)	$V_{BE(sat)}$	$I_C = -700 mA, I_B = -70mA$			-1.2	
Base-emitter voltage (Note.1)	V_{BE}	$V_{CE} = -6V, I_C = -10mA$	-0.6		-0.7	
DC current gain (Note.1)	$h_{FE}(1)$	$V_{CE} = -1V, I_C = -100mA$	110		400	
	$h_{FE}(2)$	$V_{CE} = -1V, I_C = -700mA$	50			
Collector output capacitance	C_{ob}	$V_{CB} = -6V, I_E = 0, f = 1MHz$		17		pF
Transition frequency	f_T	$V_{CE} = -6V, I_C = -10mA$		160		MHz

Note.1:Pulse test : Pulse width $\leq 350\mu s$, Duty Cycle $\leq 2\%$.

■ Classification of $h_{FE}(1)$

Type	2SB624-BV1	2SB624-BV2	2SB624-BV3	2SB624-BV4	2SB624-BV5
Range	110-180	135-220	170-270	200-320	250-400
Marking	BV1	BV2	BV3	BV4	BV5

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Bipolar Transistors - BJT category:

Click to view products by KEXIN manufacturer:

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [MJ15024/WS](#) [MJ15025/WS](#) [BC546/116](#) [BC556/FSC](#) [BC557/116](#) [BSW67A](#) [HN7G01FU-A\(T5L,F,T\)](#)
[NJVMJD148T4G](#) [NSVMMBT6520LT1G](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE2353](#) [NTE316](#) [IMX9T110](#) [NTE63](#) [NTE65](#)
[C4460](#) [SBC846BLT3G](#) [2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA1727TLP](#) [2SA2126-E](#) [2SB1202T-TL-E](#) [2SB1204S-TL-E](#) [2SC5488A-TL-H](#)
[2SD2150T100R](#) [SP000011176](#) [FMC5AT148](#) [2N2369ADCSM](#) [2SB1202S-TL-E](#) [2SC2412KT146S](#) [2SC4618TLN](#) [2SC5490A-TL-H](#)
[2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#) [BC557B](#) [TTC012\(Q\)](#) [BULD128DT4](#) [JANTX2N3810](#)
[Jantx2N5416](#) [US6T6TR](#) [KSF350](#) [068071B](#)