


NEW ENGLAND SEMICONDUCTOR

**SMALL SIGNAL
NPN TRANSISTOR
TO-18**

PACKAGE	DEVICE TYPE	V _{CEO} (sus) VOLTS	I _C (max) AMPS	h _{FE} @ I _C /V _{CE} min/max @ mA/V	V _{CE(sat)} @ I _C /I _B V @ mA/mA	C _{QBP}	f _T (MHz)
TO-18 TO206AA 	2N2481	15	0.05	40/120@10/1	0.25@10/1	5	300
	2N2484	60	0.05	250/350@1/5	0.35@1/0.1	6	60
	2N2895	65	1.0	40/120@150/10	0.6@150/15	15	120
	2N2896	90	1.0	60/200@150/10	0.6@150/15	15	120
	2N2897	45	1.0	50/200@150/10	1.0@150/15	15	100
	2N3013	15	0.2	30/100@30/0.4	0.18@30/3	5	350**
	2N3014	20	0.2	25@10/0.4	0.35@100/10	5	350**
	2N3302	30	0.5	100/300@150/10	0.22@150/15	8	250
	2N3700 [^]	80	1.0	100/300@150/10	0.2@150/15	12	100
	2N3946	40	0.2	50/150@10/1	0.2@10/1	4	250
	2N3947	40	0.2	100/300@10/1	0.2@10/1	4	300
	2N4013	30	1.0	25@1000/5	0.52@500/50	10	300
	2N4014	50	1.0	30@1000/5	0.42@500/50	12	300
	2N6430	200	0.05	50/200@30/10	0.5@20/2	4	50
	2N6431	300	0.05	50/200@30/10	0.5@20/2	4	50

^h V_{CER}

[^]Available in JAN, JANTX, JANTXV

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bipolar Transistors - BJT category](#):

Click to view products by [Microchip manufacturer](#):

Other Similar products are found below :

[619691C](#) [MCH4017-TL-H](#) [BC546/116](#) [BC557/116](#) [BSW67A](#) [NTE158](#) [NTE187A](#) [NTE195A](#) [NTE2302](#) [NTE2330](#) [NTE63](#) [C4460](#)
[2SA1419T-TD-H](#) [2SA1721-O\(TE85L,F\)](#) [2SA2126-E](#) [2SB1204S-TL-E](#) [2SC5488A-TL-H](#) [2SD2150T100R](#) [SP000011176](#) [FMMTA92QTA](#)
[2N2369ADCSM](#) [2SC2412KT146S](#) [2SC5490A-TL-H](#) [2SD1816S-TL-E](#) [2SD1816T-TL-E](#) [CMXT2207 TR](#) [CPH6501-TL-E](#) [MCH4021-TL-E](#)
[US6T6TR](#) [732314D](#) [CMXT3906 TR](#) [CPH3121-TL-E](#) [CPH6021-TL-H](#) [873787E](#) [UMX21NTR](#) [EMT2T2R](#) [MCH6102-TL-E](#) [FP204-TL-E](#)
[NJL0302DG](#) [2N3583](#) [2SA1434-TB-E](#) [2SC3143-4-TB-E](#) [2SD1621S-TD-E](#) [NTE103](#) [30A02MH-TL-E](#) [NSV40301MZ4T1G](#) [NTE101](#) [NTE13](#)
[NTE15](#) [NTE16001](#)