

To get started with development, download and extract the Audio Development Board compressed archive file from [www.microchip.com/adb](http://www.microchip.com/adb). Connect a debugger or programmer such as the MPLAB® REAL ICE™ In-Circuit Emulator or ICD 3 to the RJ-45 (J3) connector. Open MPLAB and load the ADB Demo workspace. Compile, program and run the demo. For more information on the hardware, refer to the Audio Development Board User's Guide (DS70662).

## Audio Development Board Information Sheet

### Features

The Audio Development Board is a high quality audio development platform using a 16-bit or 32-bit microcontroller (MCU). The on-board high-performance MCU is ideal for complex audio algorithms, which are computation intensive.

Features of the Audio Development Board are:

- High-performance microcontroller
- Wolfson WM8960 audio codec with up to 48 kHz sampling rate and up to 24-bit resolution, headphone out and line-in jacks, and an on-board microphone
- TFT Color Display with 220x176 resolution
- USB and UART communication interfaces
- PICtail™ Plus expansion connector for Made for iPod®

### Getting Started

The Audio Development Board is preprogrammed with an audio demonstration. Use the following procedure to run this demonstration:

1. Power the ADB by connecting the 9V power brick provided with the ADB in the power connector (J1).
2. Connect a pair of headphones or powered speakers into the jack labeled HP OUT (J6).
3. A line-in input to the Line IN (J5) jack can be connected or the on-board microphone (MIC) can be used for audio input. MIC is the default audio input, but it can be changed to Line-in in the settings.
4. A USB Flash drive must be plugged into the USB receptacle (J7) to use the record and playback features in the demonstration.
5. Press switch S3 to navigate between the individual applications. Navigation is indicated by the red bevel around the application icon. Descriptions of the applications are provided in [Table 1](#).
6. Press switch S2 to select the application. The selection is confirmed by the red bevel turning green before the next application screen is presented.
7. While the application is running, switch S1 can be pressed to return to the main menu, which closes the application. Or alternatively, switch S4 can be used to perform a specific action depending on the application, as described in [Table 1](#).

TABLE 1:

Action	Description	Switch S4	Switch S2, S3	Switch S1
<b>Record</b>	Audio from line-in or on-board microphone is recorded and stored on a USB Flash drive.	Stop or resume recording.	—	Back to main screen
<b>Playback</b>	Audio stored on a USB Flash drive is played back.	Pause or resume playback.	—	
<b>Loopback</b>	Audio from line-in or microphone is output to the headphones. Frequency spectrum of audio is displayed on screen.	Mute or un-mute playback.	—	
<b>Settings</b>	Change audio input, audio in and out volume, and sampling frequency.	Switch between settings options.	Change audio input between line-in and the on-board microphone. Increase or decrease audio in and out volume. Change audio sampling frequency.	

#### Americas

Atlanta - 678-957-9614  
 Boston - 774-760-0087  
 Chicago - 630-285-0071  
 Cleveland - 216-447-0464  
 Dallas - 972-818-7423  
 Detroit - 248-538-2250  
 Indianapolis - 317-773-8323  
 Los Angeles - 949-462-9523  
 Phoenix - 480-792-7200  
 Santa Clara - 408-961-6444  
 Toronto - 905-673-0699

#### Europe

Austria - Wels - 43-7242-2244-39  
 Denmark - Copenhagen - 45-4450-2828  
 France - Paris - 33-1-69-53-63-20  
 Germany - Munich - 49-89-627-144-0  
 Italy - Milan - 39-0331-742611  
 Netherlands - Drunen - 31-416-690399  
 Spain - Madrid - 34-91-708-08-90  
 UK - Wokingham - 44-118-921-5869

#### Asia/Pacific

Australia - Sydney - 61-2-9868-6733  
 China - Beijing - 86-10-8569-2100  
 China - Chengdu - 86-28-8665-5511

#### Asia/Pacific (Continued)

China - Chongqing - 86-23-8980-9588  
 China - Hangzhou - 86-571-2819-3180  
 China - Hong Kong SAR - 852-2401-1200  
 China - Nanjing - 86-25-8473-2460  
 China - Qingdao - 86-532-8502-7355  
 China - Shanghai - 86-21-5407-5533  
 China - Shenyang - 86-24-2334-2829  
 China - Shenzhen - 86-755-8203-2660  
 China - Wuhan - 86-27-5980-5300  
 China - Xiamen - 86-592-2388138  
 China - Xian - 86-29-8833-7252  
 China - Zhuhai - 86-756-3210040  
 India - Bangalore - 91-80-3090-4444  
 India - New Delhi - 91-11-4160-8631  
 India - Pune - 91-20-2566-1512  
 Japan - Yokohama - 81-45-471-6166  
 Korea - Daegu - 82-53-744-4301  
 Korea - Seoul - 82-2-554-7200  
 Malaysia - Kuala Lumpur - 60-3-6201-9857  
 Malaysia - Penang - 60-4-227-8870  
 Philippines - Manila - 63-2-634-9065  
 Singapore - 65-6334-8870  
 Taiwan - Hsin Chu - 886-3-6578-300  
 Taiwan - Kaohsiung - 886-7-213-7830  
 Taiwan - Taipei - 886-2-2500-6610  
 Thailand - Bangkok - 66-2-694-1351

05/02/11



**MICROCHIP**

Microchip Technology Inc. • 2355 West Chandler Blvd. • Chandler, AZ 85224-6199

[www.microchip.com](http://www.microchip.com)

The Microchip name and logo, the Microchip logo, and MPLAB are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries. All other trademarks mentioned herein are property of their respective companies. © 2011, Microchip Technology Incorporated, Printed in the U.S.A. All Rights Reserved. 05/11

DS51969B



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Audio IC Development Tools](#) category:*

*Click to view products by [Microchip](#) manufacturer:*

Other Similar products are found below :

[1580/5171-DEMO](#) [LM4935RLEVAL](#) [LM4923LQBD](#) [MAX9738EVKIT+](#) [EVAL-ADAV803EBZ](#) [CDBWM8725-M-1](#) [CDBWM8533-M-1](#)  
[EV\\_ICS-40740-FX](#) [SDCK3](#) [PIM524](#) [DEV-17737](#) [EVALAHNBIM69D130V01TOBO1](#) [1063](#) [TAS5756MDCAEVM](#)  
[TLV320ADC3101EVM-K](#) [TLV320AIC3105EVM-K](#) [TLV320DAC32EVM-PDK](#) [TPA2016D2EVM](#) [TPA2035D1EVM](#)  
[TPA2051D3YFFEVM](#) [TPA3107D2EVM](#) [TPA6120A2EVM](#) [TPA6132A2EVM2](#) [MIKROE-2454](#) [1381](#) [MIKROE-2477](#) [1712](#) [175](#) [1788](#)  
[PGA2505EVM](#) [LM4780TABD/NOPB](#) [2130](#) [2220](#) [EVAL-ADAU1442EBZ](#) [AD8273-EVALZ](#) [2341](#) [2342](#) [TPA2100P1EVM](#)  
[TPA203XD1EVM](#) [TPA2031D1EVM](#) [TPA2014D1EVM](#) [TPA2006D1EVM](#) [DEM-PCM2912AEVM](#) [TLV320AIC3204EVM-K](#)  
[TLV320AIC3120EVM-U](#) [TLV320AIC3106EVM-K](#) [TLV320AIC3101EVM-K](#) [PCM2906CEVM-U](#) [TAS5132DDV2EVM](#) [2716](#)