

# Panasonic

ideas for life

CE  
Conforming to  
Low Voltage and  
EMC Directive

## Multi-functional & compact PLC

Body equipped with combined relay and transistor output



L30R



Built-in 2-axis pulse output  
50 kHz max.



Built-in calendar/clock



Built-in 2-channel multi-functional  
analog input  
Voltage, thermistor and potentiometer input




Built-in RS485 communication port



L14R



L40R/L40MR



L60R/L60MR

## Network

### **Maximum 2-channel communication port**

One RS232C programming port is equipped on the body. And RS485 communication port is also built-in L40MR and L60MR.

### **Modbus-RTU**

Non-program communication with the devices (such as the temperature controller and the inverter etc.) using global universal industry standard Modbus-RTU (binary) can be realized simply.

### **Profibus DP**

One of the world's most popular open fieldbusses. 12Mbit/s high-speed communications. Transmission up to 12km is possible by using a repeater.

### **PLC link**

If L40MR and L60MR are used, the sharing of bit data and word data among 16 PLCs (max.) can be realized.

### **Computer link**

Non-program communication with the devices (such as the display, image processor, temperature controller and wattmeter etc.) using Panasonic open protocol "MEWTOCOL" can be realized simply.

### **Universal serial communication**

It can generate or send the corresponding commands according to the communication protocol used by the pairing device. In addition, it can also receive the flow data, such as the data from the measuring instrument, bar code reader and RF-ID etc.

## Performance

### **Super-high processing speed**

Super-high speed of 80 ns/step for 0 to 3000 steps (ST command). 580 ns/step processing speed for 3001 steps or more (only for L40 and L60).

### **Program memory**

L14 and L30: 2.5k steps  
L40 and L60: 8k steps

### **The maximum number of I/O points**

One control unit can be connected with up to 3 expansion units. Therefore, the maximum number can reach 150 points.

In addition, if the expansion FP0 adaptor is used, the maximum number can reach 216 points when the FP0R expansion unit is used. (only for L40R, L40MR, L60R and L60MR)



**Rich functions, high cost-effective.  
Strong line-up, wide application.**

## Line up

### 6 kinds of control units

L14R, L30R, L40R and L60R: Ry+Tr, AC  
L40MR, L60MR: Ry+Tr, RS485, AC

### 11 kinds of expansion units (FP-X)

(16 points) × (Ry, NPN, PNP)

(30 points) × (Ry, NPN, PNP) (AC, DC)

Specific unit for input (E16X)

Specific unit for output (E14YR)

3 units max. can be added.

E16X, E16T, E16P upgraded to Ver.3 or later can be connected (The number of connected units is limited.)

### 56 kinds of combinations (of I/O number)

14 to 150 points (FP0R expansion units excluded)

## Positioning/function

### Built-in 2-axis pulse output function

L14 is 1-axis pulse output, while L30/L40/L60 are 2-axis, and the pulse output function is built-in the body of the controller.

Built-in 2-axis type can realize linear interpolation (only for L40 and L60).

Analog input function

### Multi-functional analog input (10 bit, 2-channel)

Voltage input (0 to 10 V), thermistor input and adjustable potentiometer input.

### Built-in calendar/clock

L40R, L40MR, L60R and L60MR are equipped with built-in real-time clock functions.






# Basic performance (expansion)

Plenty of I/O points -150 points max.  
(If further expansion is made to FP0R expansion unit, the number can be expanded to 216 points max.)

If the customer can not predict the number of I/O points needed by his machineries and devices in the future, he will feel hesitant and uncomfortable. But, the I/O number of FP-X0 can reach 150 points max. by using the FP-X expansion unit. Therefore, the customer's discomfort and hesitation can be eliminated. And the number of I/O points can be expanded to 216 by using the FP0R expansion unit.  
(L14R and L30R don't have the expansion function, so they can not be expanded.)

The maximum number of expansion units is up to 3 units.



Expansion: E16X, E16T and E16P upgraded to Ver.3 or later can be connected in series up to 3 units. But, E14 and E16 expansion units can not be connected at the right sides of E16X/E16T/E16P (Ver.2 earlier) or E16R/E14YR.

## Further expansion and more functions achieved by using the existing FP0R expansion unit easily

The maximum number of FP0R expansion unit is up to 3 after all the control units are equipped with adaptors.

A wider range of application can be achieved by using [transistor output], [analog I/O], [thermocouple input] and [I/O LINK (network)].

Only one FP0 expansion adaptor can be installed on the control unit.


In addition, two FP-X expansion units can be installed after the adaptor is installed.



Besides the supplied expansion cable of 8cm, 30cm and 80cm types are also sold separately. They can be bent or straightened. (The total extension length is within 160cm.)



FP0 expansion adaptor (AFPX-EFP0)



Both of them are 90 mm and can be installed in the cabinet.



The cable between the units can be bent to realize the side-by-side installation, thus saving the installation space.


Model	Power supply	Specifications
AFPX-E16X	-	DC input, 16 points
AFPX-E14YR	-	2A relay output, 14 points
AFPX-E16R	-	DC input, 8 points 2 A relay output, 8 points
AFPX-E30R	AC	16-point DC input 14-point 2A relay output
AFPX-E30RD	DC	16-point DC input 14-point 2A relay output
AFPX-E16T	-	8-point DC input 8-point transistor (NPN) output
AFPX-E16P	-	DC input, 8 points 8-point transistor (PNP) output
AFPX-E30T	AC	DC input, 16 points 14-point transistor (NPN) output
AFPX-E30TD	DC	16-point DC input 14-point transistor (NPN) output
AFPX-E30P	AC	16-point DC input 14-point transistor (PNP) output
AFPX-E30PD	DC	16-point DC input Transistor (PNP) output, 14 points

Model	Specifications
AFP0RE8X	8-point DC input MIL connector
AFP0RE16X	16-point DC input MIL connector
AFP0RE8YT	8-point transistor output MIL connector
AFP0RE8YRS	8-point relay output screw terminal block
AFP0RE16YT	16-point transistor output MIL connector
AFP0RE16T	8-point DC input, 8-point transistor output, MIL connector
AFP0RE32T	16-point DC input, 16-point transistor output, MIL connector
AFP0RE8RS	4-point DC input, 4-point relay output, screw terminal block
AFP0RE16RS	8-point DC input, 8-point relay output, screw terminal block
FP0E32RSD	16-point DC input, 16-point relay output, MC connector

Model	Specifications
FP0-A21	Analog 2-point input , 1-point output
FP0-A80	Analog 8-point input
FP0-A04V	Analog (voltage) 4-point output
FP0-A04I	Analog (current) 4-point output
FP0-TC4	Thermocouple 4-point input
FP0-TC8	Thermocouple 8-point input
FP0-IOL	I/O LINK unit
FP0-CCLS	CC-Link slave unit

## Pulse output function / High-speed counter function


The pulse output function of FP-X0 (1-axis for L14 and 2-axis for L30/L40/L60) is built-in the body of the control unit. Compared with the previous PLC that must use the advanced or specific positioning units or more than two multi-axis control devices, FP-X0 only uses one unit basically, thus saving the space and reducing the cost.



Items	Specifications
Max. frequency of pulse output	L14: 20kHz(CH0) L30: 20kHz(CH0,1) L40 L60: 50kHz(CH0,1)
Output mode	CW / CCW, Pulse/Sign output
Function	Trapezoidal control, multi-speed operation, JOG operation, original position return, 2-axis linear interpolation (Only L40 and L60)

## L40 and L60 adopting 2-axis linear interpolation

2-axis linear interpolation is a kind of function that controls 2 motor axes and makes the robot arm and tool head carry out diagonal line moving simultaneously, which is applied in the stacker's picking & mounting components, the control of XY workbench and the baseplate cutting etc.



Body equipped with combined relay and transistor output. The load capacity of the transistor is up to 0.5 A.

(All the outputs can be enabled simultaneously.)



## Built-in 4-point high-speed counter



4-point for 1-phase or 2-point for 2-phase (X0 to X3)



Model	HSC input mode	Pulse output (1-axis)	When HSC using 1 channel	When HSC using all the channels
L14	1-phase	Stopping	20 kHz	20 kHz
		Outputting	20 kHz	20 kHz
	2-phase	Stopping	20 kHz	20 kHz
		Outputting	17 kHz	16 kHz
Model	HSC input mode	Pulse output (2-axis)	When HSC using 1 channel	When HSC using all the channels
L30	1-phase	Stopping	20 kHz	20 kHz
		Outputting	20 kHz	14 kHz
	2-phase	Stopping	20 kHz	20 kHz
		Outputting	13 kHz	12 kHz
L40/L60	1-phase	Stopping	50 kHz	33 kHz
		Outputting	36 kHz	24 kHz
	2-phase	Stopping	20 kHz	16 kHz
		Outputting	16 kHz	13 kHz

## Built-in PID command (F356 EZPID)

A wider range of temperature control applications is achieved through the use of PLC, such as the multi-section temperature control, temperature control linked with the timer, variable temperature control based on the data calculation results and multi-point temperature control etc. Using new PID commands (F356 EZPID) makes the PID control program simplified substantially than before. It was considered relatively hard to carry out temperature control through PLC before, but now it becomes quite easy. The example shown at the right side is a simple constant temperature control. If you use the F356 command together with the combination operation of touch screen, only one line of program is needed, thus making PID control amazingly simple.



## 1) Performance specifications

Items		L14R	L30R	L40R	L40MR	L60R	L60MR	
Controllable I/O points	Control unit	DC input 8 points, Relay output 4 points, Transistor output 2 points	DC input 16 points, Relay output 10 points, Transistor output 4 points	DC input 24 points, Relay output 12 points, Transistor output 4 points		DC input 32 points, Relay output 24 points, Transistor output 4 points		
	When using FP-X E16 expansion I/O units	-	-	88 points max. (3 expansion units max.)		108 points max.		
	When using FP-X E30 expansion I/O units	-	-	130 points max. (3 expansion units max.)		150 points max. (3 expansion units max.)		
	When using FP0R expansion units	-	-	196 points max. (3 expansion units max.)		216 points max. (3 expansion units max.)		
Programming method		IEC 61131-3						
Program memory		Built-in Flash-ROM (Free of backup battery)						
Program capacity		2.5 k steps		8 k steps				
No of instruction	Basic commands	Approx. 114 kinds						
	High-level commands	Approx. 230 kinds						
Processing speed		0.08 μs/step for basic commands 0.32 μs for high-level commands (MV commands)		3k steps: 0.08 μs/step for basic commands, 0.32 μs for high-level commands (MV commands) After 3k steps: 0.58 μs/step for basic commands, 1.62 μs for high-level commands (MV commands)				
Basic time		0.15 ms or less	0.18 ms or less	0.31 to 0.35 ms or less		0.34 to 0.39 ms or less		
I/O refreshing + basic time		When using E16: 0.4 ms × No. of units When using E30: 0.5 ms × No. of units When using FP0 expansion adaptors: 1.4 ms + the refreshing time of the FP0 expansion unit						
Memory for processing	Relays	External input (X) <sup>Note 1)</sup>	960 points		1760 points			
		External output (Y) <sup>Note 1)</sup>	960 points		1760 points			
		Internal relay (R)	1008 points		4096 points			
		Special internal relay (R)	224 points					
		Timer:Counter (T/C)	256 points <sup>Note 2)</sup>		1024 points <sup>Note 2)</sup>			
			Timer: (1 ms, 10 ms, 100 ms, 1 s) × 32767, Counter: 1 to 32767					
	Memory area	Link relay (L)	No		2048 points			
		Data register (DT)	2500 words		8192 words			
		Special data register (DT)	420 words					
		Link data register (LD)	No		256 words			
Index register (I)		14 words (IO to ID)						
Differential points		Equivalent to program capacity						
Master control relay (MCR)		32 points		256 points				
Label number (JP+LOOP)		100 points		256 points				
No. of subroutines		100		500				
No. of interrupt programs		Input: 8 programs, timing: 1 program						
PLC link function		No		Yes				
Constant scan		In unit of 0.5 ms: 0.5 ms to 600 ms						
Password		Available (4 or 8 digits)						
Upload protection		Available						
Self-diagnosis function		Checks of the watchdog timer and the program syntax						

Items	L14R	L30R	L40R	L40MR	L60R	L60MR
Program editing during Run	Available (Capacity modified simultaneously: 128 steps) But comments cannot be modified during the process.		Available (Capacity modified simultaneously: 512 steps) But comments can be modified during the process.			
Downloading during Run	Available					
High-speed counter <sup>Note 2), Note 3)</sup>	1-phase, 4-channel (20 kHz max.) and 2-phase, 2-channel (20 kHz max.)		1-phase, 4-channel (50 kHz max.) and 2-phase, 2-channel (20 kHz max.)			
Pulse output/PWM output <sup>Note 2), Note 3)</sup>	Pulse: 1-channel (20 kHz max.) PWM: 1-channel (1.6 kHz max.)		Pulse: 2-channel (20 kHz max.) PWM: 2-channel (1.6 kHz max.)		Pulse: 2-channel (50 kHz) PWM: 2-channel (3.0 kHz max.)	
Pulse catch input/Interrupt program	8 points (High-speed counting and interrupt input included)					
Periodical interrupt	0.5 ms unit: 0.5 ms to 1.5 s, 10 ms unit: 10 ms to 30 s					
Analog input	No		2-channel (For inputting any of the following items in each channel)  Potentiometer input Min. resistance value of potentiometer: 5 kΩ 10-bit resolution (K0 to K1000)  Thermistor input For inputting the resistance value of the thermistor (Min. resistance value of external thermistors + external resistance value > 2 kΩ) 10-bit resolution (K0 to K1023)  Voltage input Absolute max. input voltage: 10 V 10-bit resolution (K0 to K1023)			
Calendar/clock	No		Yes			
Flash ROM backup <sup>Note 4)</sup>	Data memory (2500 words)		Data memory (8192 words)			
Backup battery	No		Yes			
RS485 communication port	No		Yes		No Yes	

Note 1) The points of the timer can be added as required.

Note 2) The rated voltage is 24 V DC at 25 °C. The frequency may fall according to the changes of the voltage, temperature and operating conditions.

Note 3) The maximum frequency may vary with the difference of the operating method.

Note 4) The allowable writing operation is within 10000 times. Areas to be held and not held can be specified using the system registers.

## 2) General specifications

Items	Specifications
Operating temperature	0 to +55°C
Conformed EC Directives	EMC Directive: EN61131-2, Low Voltage Directive: EN61131-2

### 3) Power supply specifications

#### AC power supply

Items	L14R	L30R,L40R,L40MR,L60R,L60MR
Rated voltage	100 to 240 V AC	
Applied voltage range	85 to 264 V AC	
Inrush current	35A max.(at 240 V AC and 25°C)	40A max.(at 240 V AC and 25°C)
Momentary power off time	10 ms (when 100 V AC used)	
Frequency	50/60 Hz(47 to 63 Hz)	
Leakage current	0.75 mA max.between the input and protective ground terminals	
Service life of built-in power supply	20000 h (at 55°C)	
Fuse	Build-in, not operator accessible	
Insulation system	Transformer isolation	
Screw of terminal block	M3	

#### Univeral power supply for input (output) (L30/L40/L60 only)

Items	Specifications
Rated output voltage	24 V DC
Applied voltage range	21.6 to 26.4 V DC
Rated output current	0.3A
Overcurrent protection <sup>(Note)</sup>	Yes
Screw of terminal block	M3

Note) Output short protection is a temporary overcurrent protection. When the short is detected, all the power supplies of PLC will be turned OFF.

If the current load out of this specification is connected and in consecutive over-loaded status, failures may occur.


### 4) Input specifications

Items	L14R	L30R	L40R	L40MR	L60R	L60MR
Insulation method	Optical coupler					
Rated input voltage	24 V DC					
Applied voltage range	21.6 V DC to 26.4 V DC					
Rated input current	Approx. 3.5 mA (Control unit: X0 to X3); Approx. 4.3 mA (Control unit: X4 and the following ones)					
Input points per common	8 points/COM (L14R), 16 points/COM (L30R), 24 points/COM (L40R), 16 points/COMx2 (L60R). (Input power supply +/- are both available.)					
Min. ON voltage/Min. ON current	19.2 V DC/3 mA					
Max. OFF voltage/Max. OFF current	2.4 V DC/1.0 mA					
Input impedance	Approx. 6.8 kΩ (Control units: X0 to X3), Approx.5.6 kΩ (control unit X4 and the following ones)					
Response time	OFF→ON	For X0 to X3, 1 ms max.: common input 25 μs max. <sup>(Note)</sup> ; When setting high-speed counter, pulse catching input and interrupt input X4 and the following ones: 1 ms max.				
	ON→OFF	For X0 to X3, 1 ms max.: common input 10 μs max. <sup>(Note)</sup> ; When setting high-speed counter, pulse catching input and interrupt input X4 and the following ones: 1 ms max.				
Action indicator	Same as the above LED indication					
EN61131-2 application type	TYPE 3 standard (Depending on the above-mentioned specifications)					

Note) The specifications mentioned above are at rated 24 V DC and operating temperature of 25°C.

#### Circuit diagram

X0 to X3 :  
R1 = 6.8 kΩ, R2 = 820 Ω  
X4 and the following :  
R1 = 5.6 kΩ, R2 = 1 kΩ



### 5) Output specifications

#### Relay output specifications

Items	L14R	L30R	L40R	L40MR	L60R	L60MR
Insulation method	Relay					
Output form	1a output (Relay replacement disabled)					
Rated control capacity, (Resistance load) <sup>(Note)</sup>	2A 250 V AC, 2A 30 V DC (per point)					
Output points per common	1 point/COMx2 2 points/COMx1	2 points/COMx1 4 points/COMx2	1 point/COMx2 2 points/COMx1 4 points/COMx2	4 points/COMx6		
Response time	OFF→ON	Approx. 10 ms				
	ON→OFF	Approx. 8 ms				
Life	Mechanical	20,000,000 times min.(Switching frequency 180 times/minute)				
	Electrical	100,000 times min. (Depending on the rated control capacity, switching frequency of 20 times/minute)				
Surge absorber	No					
Action indicator	LED indication					

Note) There are restrictions on the rated current for each output block. Each usable rated current is as below.


L14:Y2 to Y5(4 points) Max. 6A in total

L30:Y4 to YD(10 points) Max. 8A in total

L40:Y4 to YFD(12 points) Max. 8A in total

L60:Y4 to YB(8 points) Max. 8A in total, YC to Y1B(16 points) Max. 8A in total

#### Circuit diagram




#### Transistor (NPN) output specifications

Items	L14R	L30R	L40R	L40MR	L60R	L60MR
Insulation method	Optical coupler					
Output method	Open-collector					
Rated load voltage	5 to 24 V DC					
Allowable range of load voltage	4.75 to 26.4 V DC					
Max.load current	0.5 A					
Max.impact current	1.5 A					
Output points per common	2 points/COM	4 points/COM				
Leakage current at OFF status	1 μA max.					
Max. voltage drop at ON status	0.3 V DC max.					
Response time (at 25°C)	OFF→ON	10μs max. (Load current over 15 mA)	5 μs max. (Load current over 15 mA)			
	ON→OFF	40 μs max. (Load current over 15 mA)	15 μs max. (Load current over 15 mA)			
External power supply (Positive and negative terminals)	Voltage	21.6 to 26.4 V DC				
	Current	15 mA max.				
Surge absorber	Zener diode					
Action indicator	LED indication					

#### Circuit diagram

[NPN output]  
[Y0 to Y3]





# Part number list

## 1) Control unit

Product name	Power supply	Specifications	Specifications			Part No.
			Program capacity	Analog input	RS485 communication	
FP-X0 L14R	100 to 240 V AC	24 V DC input, 8 points 0.5 A/5 to 24 V DC transistor output, 2 points 2 A relay output, 4 points	2.5 k steps	-	-	AFPX0L14R
FP-X0 L30R	100 to 240 V AC	24 V DC input, 16 points 0.5 A/5 to 24 V DC transistor output, 4 points 2 A relay output, 10 points	2.5 k steps	-	-	AFPX0L30R
FP-X0 L40R	100 to 240 V AC	24 V DC input, 24 points 0.5 A/5 to 24 V DC transistor output, 4 points 2 A relay output, 12 points	8 k steps	10 bits, 2 channel	-	AFPX0L40R
FP-X0 L40MR	100 to 240 V AC	24 V DC input, 24 points 0.5 A/5 to 24 V DC transistor output, 4 points 2 A relay output, 12 points	8 k steps	10 bits, 2 channel	Available	AFPX0L40MR
FP-X0 L60R	100 to 240 V AC	24 V DC input, 32 points 0.5 A/5 to 24 V DC transistor output, 4 points 2 A relay output, 24 points	8 k steps	10 bits, 2 channel	-	AFPX0L60R
FP-X0 L60MR	100 to 240 V AC	24 V DC input, 32 points 0.5 A/5 to 24 V DC transistor output, 4 points 2 A relay output, 24 points	8 k steps	10 bits, 2 channel	Available	AFPX0L60MR

## 3) Software tools (refer to operation manual for the details)

Part Number	Description
FPWINPRO6-FULL	Control FPWIN Pro programming software, version 6, full version for all FP-Series PLCs
FPWINPRO6-SMALL	Control FPWIN Pro programming software, version 6, small version (cannot be used with FP2/FP2SH)
FPWINPRO6-UPGRADE	Control FPWIN Pro V6 programming software update from version 3 to 6 for all control units, manual as PDF file on CD
FPWINPRO6-UPGRADE	Control FPWIN Pro V6 programming software update from version 3 to 6 for FP0/FP0R/FP-e/FP-G/FP-X, manual as PDF file on CD

## 2) Expansion unit



FP-X expansion I/O unit and FP0R unit can be used. But FP0 adaptors for FP-X expansion are required when FP0R expansion units are used.

## 4) Other cables and maintenance parts



Product name	Specifications	Part No.
Backup battery	For data storage backup and calendar/clock backup	AFP8801
FP-X expansion cable	8cm	AFPX-EC08
	30cm	AFPX-EC30
	80cm	AFPX-EC80
Cable for GT and FP TOOL port	(MiniDIN 5-pin, wound) <-> PC/FPWEB/GN-Series (SUB-D9), 3m	AFC8513D
Power cable for FP0	For the adaptor for FP0 expansion, 1 m long	AFP0581
Installation bracket for FP0 (Long-strip type)	For FP0 expansion unit, 10 pieces per package	AFP0803

## Dimensions of FP-X0 programmable controller (unit: mm)



### ● AFPX0L14R





### ● AFPX0L30R



### ● AFPX0L40R AFPX0L40MR



### ● AFPX0L60R AFPX0L60MR



You can find further information on our homepage: [www.panasonic-electric-works.com](http://www.panasonic-electric-works.com)

Panasonic Electric Works Europe AG • Rudolf-Diesel-Ring 2 • 83607 Holzkirchen • Tel.: +49 (0) 8024 648-0

**Panasonic**®

Copyright © 2012 • Printed in Germany  
4225 euen 05/12



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Controllers](#) category:*

*Click to view products by [Panasonic](#) manufacturer:*

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)  
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)  
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)  
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)  
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)  
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)