

TESTER

# DALItest





# Thank you for purchasing the DALItest tester

Please, read the operation manual and follow the rules thereof.

## Table of contents

Intended use and mode of operation	4
Device launching and description of functions	5
Device power supply	6
Tester connection	6



fig. 1

## 1. INTENDED USE AND MODE OF OPERATION

The DALItest device servers to verify proper operation of lamps adjusted to be controlled via the DALI interface. Testing may be performed in two ways. The first - automatic. In this mode, the lamp's power at the test's initial stage is smoothly adjusted from a minor value to the maximum value (ramping). At the next stage, a lamp is turn on and off several times. The entire test takes 10 seconds.

The other mode is a non-automated manual mode. It comprises manual, 5-step adjustment of the lamp power with "+" and "-" buttons.

### The device has 4 buttons:

- ON/OFF
- AUTO
- +
- -



fig. 2

There is a light-emitting diode besides each button.

## 2. DEVICE LAUNCHING AND DESCRIPTION OF FUNCTIONS

Turning the device on or off, you need to press the ON/OFF button without holding. Turning on is confirmed by activating the LED next to the ON/OFF button.

While launching the autotest mode, you need to make sure that the LED beside the ON/OFF button is on as well as press and hold for about 2 second the AUTO button, until the LED beside the AUTO button turns on. When the test is completed, the LED turns off.

The autotest mode may be canceled during its course by holding the AUTO button for about 2 seconds or by pressing the “+” or “-” button. The tester may be switched off completely while operating by the ON/OFF button.

Operating power of the luminaire may be adjusted manually by using “+” and “-” buttons.

There are 6 levels of power adjustment.

At the minimum level, the “-” LED is continuously on, however at the maximum level the “+” LED is continuously on. At intermediate levels, single pressing of a button causes the LED to flash.

### **Additional protection:**

Should the user not turn the device off having finished the test, the device shall turn off automatically after 2 minutes of inactivity.

### 3. DEVICE POWER SUPPLY

The tester is supplied from a 9V battery. The manufacturer recommends the ER9V battery with 1200 mAh capacity.

### 4. TESTER CONNECTION

#### **Connecting the tester to a lamp with power supply adapted to a DALI interface.**

The device has two single-color wires with connectors adapted to be braced on DALI bus wires. It is possible to connect wires to a single lamp without maintaining any polarity, in contrary to the 1-10 standard, where maintenance thereof has a significant influence on proper control of the lamp's power.

---

# WARRANTY CARD

---

## WARRANTY CONDITIONS

1. The manufacturer assures the highest quality of products included in this Warranty Card.
2. The warranty period is 2 years from the sale date.
3. The warranty condition is to deliver the claimed product with intact seal to the service company with the warranty card and purchase proof.
4. Defects or damages occurring during the warranty period will be removed free of charge during 14 days from delivering the device to the service company.
5. The warranty period is prolonged with time during which the device is unsuitable for use. When user receives new product instead of the defective one, the warranty period starts from the beginning. When the product part is replaced, the above principle is valid for that part.
6. The warranty does not include damages resulting from:
  - incorrect connection,
  - short-circuits in controlled circuits,
  - lightning,
  - mechanical damages and resulting defects,
  - using the device in contrary to the operation manual
7. To all matters not settled herein provisions of the Civil Code shall apply.

# WARRANTY CARD

DEVICE NAME AND TYPE

DALitest

SALE DATE

.....

IDENTIFICATION NO.

.....



## SERVICE COMPANY ADDRESS

Rabbit Sp. z o.o.  
ul. Krakowska 141-155  
50-428 Wrocław  
tel./fax: +48 71 328 50 65  
e-mail: rabbit@rabbit.pl  
[www.rabbit.pl](http://www.rabbit.pl)

.....  
AUTHORIZED PERSON STAMP AND SIGNATURE



# **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Power Management IC Development Tools](#) category:*

*Click to view products by [RABBIT](#) manufacturer:*

Other Similar products are found below :

[EVAL6482H-DISC](#) [EVAL-AD5522EBUZ](#)

EVAL-ADM1060EBZ EVAL-  
ADM1073MEBZ EVAL-ADM1166TQEBZ  
EVAL-ADM1168LQEBZ EVAL-  
ADM1171EBZ EVAL-ADM1276EBZ EVB-  
EN5319QI EVB-EN5365QI EVB-EN6347QI  
EVB-EP5348UI MIC23158YML EV  
MIC23451-AAAYFL EV MIC5281YMME  
EV ADM00513 ADM8611-EVALZ  
ADM8612-EVALZ ADM8613-EVALZ

ADM8615-EVALZ ADP1046ADC1-EVALZ

ADP1055-EVALZ ADP122-3.3-EVALZ

ADP130-0.8-EVALZ ADP130-1.2-EVALZ

ADP130-1.5-EVALZ ADP130-1.8-EVALZ

ADP160UJZ-REDYKIT ADP166UJ-EVALZ

ADP1712-3.3-EVALZ ADP1714-3.3-EVALZ

ADP1715-3.3-EVALZ ADP1716-2.5-EVALZ

ADP1740-1.5-EVALZ ADP1752-1.5-EVALZ

ADP1754-1.5-EVALZ ADP1828LC-EVALZ

ADP1870-0.3-EVALZ ADP1871-0.6-EVALZ

ADP1873-0.6-EVALZ ADP1874-0.3-EVALZ

ADP1876-EVALZ ADP1879-1.0-EVALZ

ADP1882-1.0-EVALZ ADP1883-0.6-EVALZ

ADP197CB-EVALZ ADP199CB-EVALZ

ADP2102-1.25-EVALZ ADP2102-1.2-

EVALZ ADP2102-1.875EVALZ