



EN Operating instructions. pages 1 to 2
Original

1. About this document

1.1 Function

This operating instructions manual provides all the information required for the mounting, set-up and commissioning to ensure the safe operation and disassembly of the switchgear. The operating instructions must be available in a legible condition and a complete version in the vicinity of the device.

1.2 Target group: authorised qualified personnel

All operations described in this operating instructions manual must be carried out by trained specialist personnel, authorised by the plant operator only.

1.3 Exclusion of liability

For safety reasons, invasive work on the device as well as arbitrary repairs, conversions and modifications to the device are strictly forbidden; the manufacturer shall accept no liability for damages resulting from such invasive work, arbitrary repairs, conversions and/or modifications to the device.

1.4 General safety instructions

The user must observe the safety instructions in this operating instructions manual, the country specific installation standards as well as all prevailing safety regulations and accident prevention rules.

2. Product description

2.1 Ordering code

This operating instructions manual applies to the following types:

BNS 20-①Z

No.	Option	Description
①	01	1 NC
	02	2 NC
	10	1 NO
	20	2 NO
	11	1 NC / 1 NO
	R	1 bistable contact
	2R	2 bistable contact
	11R	2 bistable contact NC / NO

2.2 Special versions

For special versions, which are not listed in the order code below 2.1, these specifications apply accordingly, provided that they correspond to the standard version.

2.3 Purpose

The magnetic reed switches BN 20 with two contacts are designed to monitor the position of movable safety guards according to ISO 14119.



The magnetic reed switches are classified according to ISO 14119 as uncoded type 3 switchgear.

Only the listed magnets may be used for actuation of the magnetic reed switch. Only these magnets can guarantee flawless function and repeat accuracy.

With suitable evaluation and concealed installation, the requirements for safety applications up to PL e in accordance with ISO 13849-1 can be satisfied.

2.4 Technical data

Standards:	IEC 60947-5-1
Enclosure:	AISI 12 die-casting, painted
Protection class:	IP67 to IEC 60529
Operating principle:	magnetic
Cable entry:	2x M16
Connection:	screw terminals
Switching voltage:	max. 250 VAC/DC
Switching current:	max. 3 A
Switching capacity:	max. 120 VA/W
Dielectric strength:	> 600 VAC (50 Hz)
Actuating speed:	max. 18 m/s
Switching frequency:	max. 300/s
Switching time "Close":	0.3 ms ... 1.5 ms
Switching time "Open":	max. 0.5 ms
Bounce duration:	0.3 ms ... 0.6 ms
Ambient temperature:	- 25 °C ... + 90 °C
Mechanical life:	10 ⁹ operations
Electrical life:	10 ⁶ ... 10 ⁹ operations, depending on load
Resistance to vibration:	50 g on sine wave oscillation
Switching point accuracy:	± 0.25 mm, T = constant
Resistance to shock:	30 g / 11 ms
Tightening force:	
- Cover screws:	min. 0.6 Nm
- Cable gland:	min. 1.2 Nm
- Blocking screws:	min. 1.2 Nm
B _{10D} to ISO 13849-1:	
- NC contacts (at 20 % contact load):	20.000.000
- NO contacts (at 20 % contact load):	20.000.000



Further technical information can be found in the Schmersal catalogues or in the online catalogue on the Internet: www.schmersal.net.

The information contained in this operating instructions manual is provided without liability and is subject to technical modifications.

3. mounting

3.1 General mounting instructions



When mounting to protective equipment, the requirements of standard ISO 14119 must be taken into account.

Two elongated holes are available for fastening the enclosure. Any mounting position, provided that the active surfaces are opposite


Magnetic reed switches and actuators

- Do not use as limit stops.
- Do not install in strong magnetic fields.
- Do not install on ferromagnetic material.
- Do not expose to strong vibrations or shocks.
- Inseparably fix to the safety guard.

The use of a protective ground wire is imperative. Keep away from metal chips

3.2 Dimensions

All measurements in mm.



4. Electrical connection

4.1 General information for electrical connection




The electrical connection may only be carried out by authorised personnel in a de-energised condition.

The contact labelling can be found in the wiring compartment of the switch.


Cable glands (included in delivery) are only authorised for permanent cables. The constructor must provide for the necessary strain relief. After wiring, dust and soiling must be removed from the wiring compartment.

4.2 Contact variants and switch travel


1 NO contact BN 20-10Z
or
1 NC contact BN 20-01Z
with actuating magnet BP 20



1 bistable contact BN 20-RZ
with actuating magnet BP 20N




1 bistable contact BN 20-RZ
with actuating magnet BP 20S



In version -10 and -01: When the switches and actuators come together, the colours must coincide: Red (S) to red (S) and green (N) to green (N).

4.3 Switching capacity



5. Maintenance

In case of correct installation in accordance with the instructions described above, the component requires little maintenance. For use in extreme conditions, we recommend routine maintenance including the following steps:

- Check the actuator and the magnetic reed switch for correct seating
- Remove particles of dust and soiling.
- Check that the cable glands are fitted in accordance with the applicable operating instructions manual



Do not open the device when live.

Damaged or defective components must be replaced.

6. Disassembly and disposal

6.1 Disassembly

The switch must be disassembled in a de-energised condition only.

6.2 Disposal

The switch must be disposed of in an appropriate manner in accordance with the national prescriptions and legislations.

K.A. Schmersal GmbH & Co. KG
Mödinghofe 30, 42279 Wuppertal
Germany

Phone: +49 202 6474-0
Telefax: +49 202 6474-100
E-Mail: info@schmersal.com
Internet: www.schmersal.com



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Schmersal](#) manufacturer:

Other Similar products are found below :

[AES1135 \(24VDC\)](#) [AES1235 \(24VDC\)](#) [A-K5P-M12-S-G-10M-BK-2-X-A-4-69](#) [A-K8P-M12-S-G-10M-BK-2-X-A-4-69](#) [A-K8P-M12-S-G-5M-BK-2-X-A-4-69](#) [AZ 15/16-B1](#) [AZ 15/16-B1-1747](#) [AZ 15/16-B1-2053](#) [AZ15/16-B1-2053 BALL LATCH](#) [AZ 15/16-B1-2177](#) [AZ 15/16-B1-2245](#) [AZ 15/16-B2](#) [AZ 15/16-B3](#) [AZ15/16-B6](#) [AZ 15 ZVK-M16](#) [AZ 15 ZVRK](#) [AZ15ZVRK-M20](#) [AZ 16-02ZVK-M16](#) [AZ 16-02ZVRK](#) [AZ16-02ZVRK-M20](#) [AZ 16-02ZVRK-ST](#) [AZ 16-03ZVK-M20](#) [AZ 16-03ZVRK](#) [AZ 16-12ZIB1-M16](#) [AZ 16-12ZVK](#) [AZ 16-12ZVRK](#) [AZ16-12ZVRK-2254](#) [AZ16-12ZVRK-M20](#) [AZ 16 ZVK-M16](#) [AZ 16 ZVK-M20-1762](#) [AZ 16 ZVRK-M16](#) [AZ16ZVRK-M20](#) [AZ 17-02ZK](#) [AZ 17-02ZK-ST](#) [AZ 17-02ZRK](#) [AZ 17-11ZI B5](#) [AZ 17-11ZK](#) [AZ17-11ZRK](#) [AZ 17/170-B1](#) [AZ 17/170-B11](#) [AZ 17/170-B15](#) [AZ 17/170-B5](#) [AZ17/AZM170-B5](#) [AZ 17-B6](#) [AZ/AZM201-B30-RTAG1P1](#) [AZ/AZM201-B30-RTAG1P1-SZ](#) [AZ/AZM300-B1](#) [AZ/AZM 415-B2](#) [AZ/AZM 415-B3](#) [AZM 161-B1](#)