ATV12H037M3

variable speed drive ATV12 - 0.37kW - 0.55hp - 200..240V - 3ph - with heat sink





Main

Range of Product	Altivar 12
Product or Component Type	Variable speed drive
Product Specific Application	Simple machine
Mounting Mode	Cabinet mount
Communication Port Protocol	Modbus
Supply frequency	50/60 Hz +/- 5 %
[Us] rated supply voltage	200240 V - 1510 %
Nominal output current	2.4 A
Maximum Horse Power Rating	0.55 hp
Motor power kW	0.37 kW
Maximum Horse Power Rating	0.55 hp
EMC filter	Without EMC filter
IP degree of protection	IP20

Complementary

Complementary	
Discrete input number	4
Discrete output number	2
Analogue input number	1
Analogue output number	1
Relay output number	1
Physical interface	2-wire RS 485
Connector Type	1 RJ45
Continuous output current	2.4 A 4 kHz
Method of access	Server Modbus serial
Speed drive output frequency	0.5400 Hz
Speed range	120
Sampling duration	20 Ms +/- 1 ms logic input 10 ms analogue input
Linearity error	+/- 0.3 % of maximum value analogue input
Frequency resolution	Analog input converter A/D, 10 bits Display unit 0.1 Hz
Time constant	20 ms +/- 1 ms for reference change
Transmission Rate	9.6 kbit/s 19.2 kbit/s 38.4 kbit/s
Transmission frame	RTU
Number of addresses	1247
Data format	8 bits, configurable odd, even or no parity
Communication service	Read holding registers (03) 29 words Write single register (06) 29 words Write multiple registers (16) 27 words Read/Write multiple registers (23) 4/4 words Read device identification (43)
Type of polarization	No impedance
-	

Asynchronous motor control profile Cludidatic voltagelfrequency ratio Volting Sensoriess flux vector control A kHz Transient overtorque 150170 % of nominal motor torque depending on drive rating and type of motor silve control Acceleration and deceleration ramps S Linear from 0 to 999.9 s Whotor slip compensation Adjustable Preset in factory Switching frequency A kHz A to No Newy duty) A conditional frequency A paparent power 12 kWA 240 V heavy duty) Maximum unput Current per Phase 12 kWA 240 V heavy duty) Maximum unput current A 8 80 s heavy duty) A 12 kWA 240 V heavy duty) Maximum and work frequency tolerance A 8 8 8 8 8 8 8 8 8 8 8 8 8 8 8 8 8 8		
Voltage/Frequency ratio (Vrf) Sensorless bux vector control	4 quadrant operation possible	False
Maximum output frequency 1 4 kHz Transient overtorque 155170 % of nominal motor torque depending on drive rating and type of miles of the second of the s	Asynchronous motor control profile	Voltage/Frequency ratio (V/f)
Transient overtorque 150170 % of nominal motor torque depending on drive rating and type of m Acceleration and deceleration ramps S Linear from 0 to 999.9 s U Concentration and deceleration ramps Acceleration and deceleration ramps S Linear from 0 to 999.9 s U Concentration of the State of State	Marian and a day of fact and a second	
Acceleration and deceleration ramps Sultinear from 0 to 999.9 s Unable of the present in factory Switching frequency 216 kHz adjustable 416 kHz with derating factor Nominal switching frequency 4 kHz Braking to standstill By DC injection Brake chopper integrated False Line current 3.6 A 100 V heavy duty) 3.0 A 120 V heavy duty) 3.0 A 120 V heavy duty) 4.0 A 20 V heavy duty) 4.0 A 2 s heavy duty) 4.0 A 2 s heavy duty) Network Frequency 5-6-00 Hz Relative symmetric network frequency tolerance 5 KA Base load current at high overload 2.4 A Prospective line Isc 5 KA Base load current at high overload 2.4 A Prower dissipation in W With safety function Safe brake management (SBC) SBT) With safety function Safe Operating Stop (SOS) False With safety function Safe Position (SP) With safety function Safe Stop 1 (SS1) False With safety function Safe Derating Stop (SOS) False With safety function Safe Stop 1 (SS1) False With safety function Safe Derating Stop (SOS) False With safety function Safe Stop 1 (SS1) False With safety function Safe Derating Stop (SOS) False With safety function Safe Derating Stop (SOS) False With safety function Safe Derating Stop (SOS) False With safety function Safe Stop 1 (SS1) False With safety function Safe Direction (SDI) False With safety function Safe Direction (SDI) False With safety function Safe Direction (SDI) False Line supply undervoltage Current between output phases and earth Overheading protection Short-irruit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of P1 Tightening torque False With the Safe Stop 1 (SS I) False With safety or via the Safe Stop 1 (SS I) False False False False False False False False	-	
Motor slip compensation Adjustable Present in factory Switching frequency 216 kHz adjustable 416 kHz with derating factor Nominal switching frequency 4 kHz Braking to standstill By DC injection Brake chopper integrated False Line current 3.6 A 100 V heavy duty) Maximum land Current per Phase 3.0 A Maximum land Current per Phase 3.0 A Maximum land Current per Phase 240 V Maximum transient current 3.6 A 60 S heavy duty) Maximum transient current 3.6 A 60 S heavy duty) Maximum transient current 3.6 A 60 S heavy duty) Melative symmetric network frequency tolerance 5 % Prospective line Isc 5 kA Base load current at high overload 2.4 A Power dissipation in W Natural 24.0 W With safety function Safely Limited Speed (SLS) False With safety function Safe Operating Stop (SOS) False With safety function Safe Operating Stop (SOS) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False		
Switching frequency 216 kHz adjustable 416 kHz adjustable 516 kHz adjustable 610 kHz adjustable 6.	Acceleration and deceleration ramps	Linear from 0 to 999.9 s
A16 kHz with derating factor	Motor slip compensation	·
Braking to standstill By DC Injection Brake chopper integrated False Line current 3.6 A 100 V heavy duty) 3.0 A 120 V heavy duty) Maximum Input Current per Phase 3.0 A Maximum output voltage 240 V Maximum transient current 3.6 A 60 s heavy duty) Maximum transient current 3.6 A 60 s heavy duty) Maximum transient current 3.6 A 60 s heavy duty) Metwork Frequency 50-60 Hz Relative symmetric network frequency tolerance 5 % Prospective line Isc Base load current at high overload 2.4 A Power dissipation in W Natural 24.0 W With safety function Safely Limited Speed (SLS) False With safety function Safe brake management (SBC/SBT) With safety function Safe Position (SP) False With safety function Safe Position (SP) False With safety function Safe programmable logic False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Ison 2 (SS2) False With safety function Safe December (SSM) False With safety function Safe December (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe December (SSM) False With safety function Safe Ison 2 (SS2) False With safety function Safe Ison 3 (SSM) False With safety function Safe Ison 4 (SSM) False With safety function Safe Ison 5 (SSM) False With safety function Safe Ison 6 (SSM) False With safety function Safe Ison 6 (SSM) False With safety function Safe Ison 6 (SSM) False With safety function 5 (SSM) False False False False False Fals	Switching frequency	
Brake chopper integrated Line current 3.6 A 100 V heavy duty) 3.0 A 120 V heavy duty) Maximum Input Current per Phase 3.0 A Maximum output voltage 240 V Apparent power 1.2 kVA 240 V heavy duty) Maximum transient current 3.6 A 60 s heavy duty) Maximum transient current 3.6 A 60 s heavy duty) Maximum transient current 5.6 A 60 s heavy duty) Network Frequency 50-60 Hz Relative symmetric network frequency tolerance 5.6 K Base load current at high overload 2.4 A Power dissipation in W Natural 24.0 W With safety function Safely Limited Speed (SLS) Braise With safety function Safe brake management (SBC/SBT) With safety function Safe Position (SP) False With safety function Safe Position (SP) False With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Drogrammable logic False With safety function Safe Stop 1 (SS1) False With safety function Safe Drogrammable logic False With safety function Safe Stop 1 (SS1) False False With safety function Safe Stop 1 (SS1) False False With safety function Safe Stop 1 (SS1) False False False With safety function Safe Stop 1 (SS1) False Fals	Nominal switching frequency	4 kHz
Line current 3.6 A 100 V heavy duty) 3.0 A 120 V heavy duty) 3.0 A 120 V heavy duty) 3.0 A 120 V heavy duty) Maximum Input Current per Phase 3.0 A Maximum cutput voltage 240 V Apparent power 1.2 kVA 240 V heavy duty) Maximum transient current 3.6 A 60 s heavy duty) Network Frequency 50-60 Hz Relative symmetric network frequency tolerance 5 % Prospective line Isc 5 kA Base load current at high overload 2.4 A Power dissipation in W With safety function Safely Limited Speed (SLS) Balse With safety function Safe brake management (SBC/SBT) With safety function Safe Operating Stop (SOS) False With safety function Safe Position (SP) False With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS2) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS2) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 2 (SS2) False With safety function Safe Stop 2 (SS2) False With safety function Safe Stop 2 (SS2) False With safety function Safe brace off (STO) False With safety function Safe Direction (SDP) False With safety function Safe brace off (STO) False With safety function Safe Direction (SDI) False Tightening torque Line supply overvoltage Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of Pt Tothering torque Fine supply overvoltage Line supply overvoltage Thermal motor protection via the drive by continuous calculation of Pt Tothering torque Fine supply suppl	Braking to standstill	By DC injection
Maximum Input Current per Phase 3.0 A 120 V heavy duty) Maximum output voltage 240 V Apparent power 1.2 kVA 240 V heavy duty) Maximum transient current 3.6 A 60 s heavy duty) 4.0 A 2 s heavy duty) Network Frequency 50-60 Hz Relative symmetric network frequency tolerance 5 % Prospective line Isc 5 kA Base load current at high overload 2.4 A Power dissipation in W With safety function Safeby Limited Speed (SLS) False With safety function Safe Dosition (SP) With safety function Safe Position (SP) With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS2) False With safety function Safe Stop 1 (SS2) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 2 (SS2) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 2 (SS2) False With safety function Safe Stop 2 (SS2) False With safety function Safe Direction (SDI) False With safety function Safe Direction (SDI) False Tightening torque False Tightening torque False Tightening torque False False False Tightening torque False False False Tightening torque False	Brake chopper integrated	False
Maximum output voltage 240 V Apparent power 1.2 kVA 240 V heavy duty) Maximum transient current 3.6 A 80 s heavy duty) ALO A 2 s heavy duty) Network Frequency 50-60 Hz Relative symmetric network frequency tolerance 5 % Prospective line Isc 5 kA Base load current at high overload 2.4 A Power dissipation in W Natural 24.0 W With safety function Safely Limited Speed (SLS) False With safety function Safe brake management (SBC/SBT) With safety function Safe Derating Stop (SOS) False With safety function Safe Position (SP) False With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS2) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS2) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS2) False With safety function Safe Stop 2 (SS2) False With safety function Safe Direction (SID) False With safety function Safe Direction (SID) False With safety function Safe Direction (SID) False Tightening tongue Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of Pt Tightening torque Set of 1 Width Set of 1	Line current	
Apparent power 1.2 kVA 240 V heavy duty) Maximum transient current 3.6 A 60 s heavy duty) 4.0 A 2 s heavy duty) 4.0 A 2 s heavy duty) Network Frequency S0-60 Hz Relative symmetric network frequency tolerance 5 % Prospective line Isc 5 kA Base load current at high overload 2.4 A Power dissipation in W With safety function Safely Limited Speed (SLS) Base load current at high overload With safety function Safe brake management (SBC/SBT) With safety function Safe Departing Stop (SOS) False With safety function Safe Operating Stop (SOS) With safety function Safe Position (SP) With safety function Safe Speed Monitor (SSM) False With safety function Safe Direction (SDI) False Tightenitor Safe Direction (SDI) False Line supply overvoltage Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of Pt Tightening torque Insulation Electrical between power and control Quantity per Set Set of 1 Width	Maximum Input Current per Phase	3.0 A
Maximum transient current 3.6 A 60 s heavy duty) 4.0 A 2 s heavy duty) Network Frequency 50-60 Hz Felative symmetric network frequency tolerance 5 % Prospective line Isc 5 KA Base load current at high overload 2.4 A Power dissipation in W Natural 24.0 W With safety function Safe by Limited Speed (SLS) SBT) With safety function Safe brake management (SBC/SBT) With safety function Safe Derating Stop (SOS) False With safety function Safe Position (SP) False With safety function Safe Speed Monitor (SSM) With safety function Safe Speed Monitor (SSM) With safety function Safe Stop 1 (SS1) With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Direction (SIP) False With safety function Safe Intervention Safe Stop 1 (SS1) False With safety function Safe Intervention Safe	Maximum output voltage	240 V
Network Frequency 50-60 Hz Relative symmetric network frequency tolerance 5 % Prospective line Isc Base load current at high overload 2.4 A Power dissipation in W Natural 24.0 W With safety function Safely Limited Speed (SLS) False With safety function Safe brake management (SBC/SBT) With safety function Safe Operating Stop (SOS) False With safety function Safe Position (SP) False With safety function Safe Position (SP) False With safety function Safe Speed Monitor (SSM) False With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe Interception (SDI) False With safety function Safe Direction (SDI) False With safety function Safe Direction (SDI) False Protection type Line supply overvoltage Line supply undervoltage Covercurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of Pt Tightening torque Insulation Electrical between power and control Quantity per Set Width	Apparent power	1.2 kVA 240 V heavy duty)
Relative symmetric network frequency tolerance 5 % Prospective line Isc 5 kA Base load current at high overload 2.4 A Power dissipation in W Natural 24.0 W With safety function Safely Limited Speed (SLS) False With safety function Safe brake management (SBC/SBT) With safety function Safe Operating Stop (SOS) False With safety function Safe Operating Stop (SOS) False With safety function Safe Position (SP) False With safety function Safe Position (SP) False With safety function Safe speed Monitor (SSM) False With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 2 (SS2) False With safety function Safe torque off (STO) False With safety function Safe Direction (SLP) False With safety function Safe Direction (SDI) False Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of Pt Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set With the safety function Safe Direction (SDI) Set of 1 Width Safety Safe Safe Safe Safe Safe Safe Safe Safe	Maximum transient current	• •/
Prospective line Isc 5 kA Base load current at high overload 2.4 A Power dissipation in W Natural 24.0 W With safety function Safely Limited Speed (SLS) False With safety function Safe brake management (SBC/SBT) With safety function Safe Operating Stop (SOS) False With safety function Safe Operating Stop (SOS) False With safety function Safe Position (SP) False With safety function Safe Position (SP) False With safety function Safe Speed Monitor (SSM) False With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 2 (SS2) False With safety function Safe Iorque off (STO) False With safety function Safe Direction (SLP) False With safety function Safe Direction (SDI) False Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of IPt Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Width Safety function Safe Direction Set of 1 Width 2.83 in (72 mm)	Network Frequency	50-60 Hz
Base load current at high overload 2.4 A Power dissipation in W With safety function Safely Limited Speed (SLS) With safety function Safe brake management (SBC/SBT) With safety function Safe Operating Stop (SOS) With safety function Safe Position (SP) With safety function Safe Position (SP) With safety function Safe Position (SP) With safety function Safe Speed Monitor (SSM) False With safety function Safe Speed Monitor (SSM) With safety function Safe Stop 1 (SS1) With safety function Safe Stop 1 (SS1) With safety function Safe torque off (STO) With safety function Safe torque off (STO) With safety function Safe Direction (SDI) Protection type Line supply overvoltage Line supply undervoltage Cine supply overvoltage Cin	Relative symmetric network frequency tolerance	5 %
Power dissipation in W With safety function Safely Limited Speed (SLS) With safety function Safe brake management (SBC/SBT) With safety function Safe Operating Stop (SOS) With safety function Safe Position (SP) With safety function Safe Position (SP) With safety function Safe Position (SP) With safety function Safe Speed Monitor (SSM) With safety function Safe Stop 1 (SS1) With safety function Safe Stop 1 (SS1) With safety function Safe Stop 1 (SS1) With safety function Safe torque off (STO) With safety function Safe Unimited Position (SLP) With safety function Safe Direction (SDI) Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of IPt Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set With the Safe Stop 1 (SLS) False False False False False With safety function Safe Direction (SDI) False Line supply overvoltage Line supply overvoltage Line supply protection Short-circuit between notor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of IPt Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set	Prospective line Isc	5 kA
With safety function Safely Limited Speed (SLS) With safety function Safe brake management (SBC/SBT) With safety function Safe Operating Stop (SOS) False With safety function Safe Position (SP) False With safety function Safe Position (SP) False With safety function Safe programmable logic False With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 2 (SS2) False With safety function Safe torque off (STO) False With safety function Safe Direction (SDI) False With safety function Safe Direction (SDI) False Unine supply overvoltage Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque Tightening torque To 8 Ibf. in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width	Base load current at high overload	2.4 A
With safety function Safe Direction (SDI) With safety function Safe Operating Stop (SOS) With safety function Safe Position (SP) With safety function Safe Position (SP) With safety function Safe programmable logic With safety function Safe Speed Monitor (SSM) With safety function Safe Speed Monitor (SSM) With safety function Safe Stop 1 (SS1) With safety function Safe Stop 1 (SS1) With safety function Safe Stop 1 (SS1) With safety function Safe torque off (STO) With safety function Safe I Direction (SLP) With safety function Safe Direction (SDI) False With safety function Safe Direction (SDI) False Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width	Power dissipation in W	Natural 24.0 W
With safety function Safe Direction (SDI) With safety function Safe Operating Stop (SOS) With safety function Safe Position (SP) With safety function Safe Position (SP) With safety function Safe programmable logic With safety function Safe Speed Monitor (SSM) With safety function Safe Speed Monitor (SSM) With safety function Safe Stop 1 (SS1) With safety function Safe Stop 1 (SS1) With safety function Safe Stop 1 (SS1) With safety function Safe torque off (STO) With safety function Safe I Direction (SLP) With safety function Safe Direction (SDI) False With safety function Safe Direction (SDI) False Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width	With safety function Safely Limited Speed (SLS)	False
With safety function Safe Position (SP) False With safety function Safe programmable logic With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) False With safety function Safe Stop 1 (SS1) False With safety function Safe torque off (STO) False With safety function Safe torque off (STO) False With safety function Safely Limited Position (SLP) False With safety function Safe Direction (SDI) False Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque T.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width		False
With safety function Safe programmable logic With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) With safety function Safe Stop 2 (SS2) With safety function Safe torque off (STO) False With safety function Safe torque off (STO) With safety function Safe Direction (SLP) False With safety function Safe Direction (SDI) False Protection type Line supply overvoltage Line supply undervoltage Covercurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width	With safety function Safe Operating Stop (SOS)	False
With safety function Safe Speed Monitor (SSM) False With safety function Safe Stop 1 (SS1) With safety function Safe Stop 2 (SS2) With safety function Safe torque off (STO) False With safety function Safe torque off (STO) With safety function Safely Limited Position (SLP) False With safety function Safe Direction (SDI) False Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width 2.83 in (72 mm)	With safety function Safe Position (SP)	False
With safety function Safe Stop 1 (SS1) With safety function Safe torque off (STO) With safety function Safe torque off (STO) With safety function Safe torque off (STO) With safety function Safe Direction (SLP) With safety function Safe Direction (SDI) False Vith safety function Safe Direction (SDI) False Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width 2.83 in (72 mm)	With safety function Safe programmable logic	False
With safety function Safe torque off (STO) False With safety function Safely Limited Position (SLP) With safety function Safe Direction (SDI) False With safety function Safe Direction (SDI) False Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width 2.83 in (72 mm)	With safety function Safe Speed Monitor (SSM)	False
With safety function Safe torque off (STO) With safety function Safely Limited Position (SLP) False With safety function Safe Direction (SDI) False Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width 2.83 in (72 mm)	With safety function Safe Stop 1 (SS1)	False
With safety function Safely Limited Position (SLP) With safety function Safe Direction (SDI) Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width 2.83 in (72 mm)	With sft fct Safe Stop 2 (SS2)	False
With safety function Safe Direction (SDI) Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width 2.83 in (72 mm)	With safety function Safe torque off (STO)	False
With safety function Safe Direction (SDI) Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width 2.83 in (72 mm)	With safety function Safely Limited Position (SLP)	False
Protection type Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase Thermal motor protection via the drive by continuous calculation of I²t Tightening torque 7.08 lbf.in (0.8 N.m) Insulation Electrical between power and control Quantity per Set Set of 1 Width 2.83 in (72 mm)		False
Insulation Electrical between power and control Quantity per Set Set of 1 Width 2.83 in (72 mm)		Line supply overvoltage Line supply undervoltage Overcurrent between output phases and earth Overheating protection Short-circuit between motor phases Against input phase loss in three-phase
Quantity per Set Set of 1 Width 2.83 in (72 mm)	Tightening torque	7.08 lbf.in (0.8 N.m)
Width 2.83 in (72 mm)	Insulation	Electrical between power and control
Width 2.83 in (72 mm)	Quantity per Set	·
<u></u>		
g	Height	5.63 in (143 mm)
Depth 4.77 in (121.2 mm)		
Net Weight 1.76 lb(US) (0.8 kg)		

Environment

Operating altitude	<= 3280.84 ft (1000 m) without derating > 3280.849842.52 ft (> 10003000 m) with current derating 1 % per 100 m
Operating position	Vertical +/- 10 degree
Product Certifications	NOM CSA C-tick UL GOST RCM KC
Marking	CE
Standards	UL 508C UL 618000-5-1 EN/IEC 61800-5-1 EN/IEC 61800-3
Assembly style	With heat sink
Electromagnetic compatibility	Electrical fast transient/burst immunity test level 4 EN/IEC 61000-4-4 Electrostatic discharge immunity test level 3 EN/IEC 61000-4-2 Immunity to conducted disturbances level 3 EN/IEC 61000-4-6 Radiated radio-frequency electromagnetic field immunity test level 3 EN/IEC 61000-4-3 Surge immunity test level 3 EN/IEC 61000-4-5 Voltage dips and interruptions immunity test EN/IEC 61000-4-11
Environmental class (during operation)	Class 3C3 according to IEC 60721-3-3 Class 3S2 according to IEC 60721-3-3
Maximum acceleration under shock impact (during operation)	150 m/s² at 11 ms
Maximum acceleration under vibrational stress (during operation)	10 m/s² at 13200 Hz
Maximum deflection under vibratory load (during operation)	1.5 mm at 213 Hz
Overvoltage category	Class III
Regulation loop	Adjustable PID regulator
Electromagnetic emission	Radiated emissions environment 1 category C2 EN/IEC 61800-3 216 kHz shielded motor cable Conducted emissions with additional EMC filter environment 1 category C2 EN/IEC 61800-3 412 kHz shielded motor cable <65.62 ft (20 m) Conducted emissions with additional EMC filter environment 2 category C3 EN/IEC 61800-3 412 kHz shielded motor cable <65.62 ft (20 m)
Vibration resistance	1 gn 13200 Hz)EN/IEC 60068-2-6 1.5 mm peak to peak 313 Hz) - drive unmounted on symmetrical DIN rail - EN/IEC 60068-2-6
Shock resistance	15 gn 11 ms EN/IEC 60068-2-27
Relative humidity	595 % without condensation IEC 60068-2-3 595 % without dripping water IEC 60068-2-3
Noise level	0 dB
Pollution degree	2
Ambient air transport temperature	-13158 °F (-2570 °C)
Ambient air temperature for operation	14104 °F (-1040 °C) without derating 104140 °F (4060 °C) with current derating 2.2 % per °C
Ambient Air Temperature for Storage	-13158 °F (-2570 °C)

Ordering and shipping details

Category	22042-ATV12 DRIVE AND ACCESSORIES
Discount Schedule	CP4B
GTIN	3606480071157
Returnability	Yes
Country of origin	ID

Packing Units

3	
Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.72 in (12 cm)
Package 1 Width	7.36 in (18.7 cm)
Package 1 Length	7.68 in (19.5 cm)
Package 1 Weight	2.22 lb(US) (1.006 kg)
Unit Type of Package 2	P06
Number of Units in Package 2	45
Package 2 Height	29.53 in (75 cm)
Package 2 Width	23.62 in (60 cm)
Package 2 Length	31.50 in (80 cm)
Package 2 Weight	128.46 lb(US) (58.27 kg)

Offer Sustainability

Sustainable offer status	Green Premium product	
California proposition 65	WARNING: This product can expose you to chemicals including: Lead and lead compounds, which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov	
REACh Regulation	REACh Declaration	
EU RoHS Directive	Pro-active compliance (Product out of EU RoHS legal scope)	
Mercury free	Yes	
China RoHS Regulation	☑ China RoHS Declaration	
RoHS exemption information	€ Yes	
Environmental Disclosure	Product Environmental Profile	
Circularity Profile	☐ End Of Life Information	
WEEE	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.	

Contractual warranty


Warranty	18 months

Product data sheet Dimensions Drawings

ATV12H037M3

Dimensions

Drive without EMC Conformity Kit




Dimensions in mm

b	С	Н
130	121.2	120

Dimensions in in.

b	С	н
5.12	4.77	4.72

Drive with EMC Conformity Kit



Dimensions in mm

c1	
53	


Dimensions in in.

c1	
2.09	


ATV12H037M3

Mounting Recommendations


Clearance for Vertical Mounting



Mounting Type A




Mounting Type B



Remove the protective cover from the top of the drive.


Mounting Type C



Remove the protective cover from the top of the drive.

ATV12H037M3

Three-Phase Power Supply Wiring Diagram




A1 Drive

KM1 Contactor (only if a control circuit is needed)

Q1 Circuit breaker


Recommended Schemes

2-Wire Control for Logic I/O with Internal Power Supply




LI1 : Forward LI• : Reverse A1 : Drive

3-Wire Control for Logic I/O with Internal Power Supply



LI1: Stop LI2: Forward LI•: Reverse A1: Drive


Analog Input Configured for Voltage with Internal Power Supply



(1) 2.2 $k\Omega$...10 $k\Omega$ reference potentiometer

A1: Drive


Analog Input Configured for Current with Internal Power Supply



0-20 mA 4-20 mA supply (2)


A1: Drive

Connected as Positive Logic (Source) with External 24 vdc Supply



(1) 24 vdc supply A1: Drive

Connected as Negative Logic (Sink) with External 24 vdc supply




(1) 24 vdo A1 : Drive 24 vdc supply

Product data sheet Performance Curves

ATV12H037M3

Torque Curves



- 1: Self-cooled motor: continuous useful torque (1)
- 2: Force-cooled motor: continuous useful torque
- 3: Transient overtorque for 60 s
- 4: Transient overtorque for 2 s
- 5: Torque in overspeed at constant power (2)
- (1) For power ratings ≤ 250 W, derating is 20% instead of 50% at very low frequencies.
- (2) The nominal motor frequency and the maximum output frequency can be adjusted from 0.5 to 400 Hz. The mechanical overspeed capability of the selected motor must be checked with the manufacturer.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Motor Drives category:

Click to view products by Schneider manufacturer:

Other Similar products are found below:

GMA02 R7DBP02L 1300920283 GMA20 R88ACRKN020CRE R88DUA03LAAC100V30W R88DUP03LAAC100V30W

MFECA0050EAM MFECA0030EAM 1300920078 R88D-GT04H R88D-KT01H R7D-BP01H R88ACR1A005CF R88D1SN04HECT

R88D1SN08HECT R88ACR1A003CFRA K6CMISZBI52 KLC35BE R88A-CA1A010B ST10-IP-EE ST10-Q-RN 103H7121-0410P

103H7123-0440P 103H7126-0740P 103H7126-5740P 103H7823-5740P SMCV6150 U-PKZ0(480V60HZ) ODE-3-120070-1F1A-01 ODE-3-240041-3F4B ODE-3-120070-1F1B-01 132B0107 68581737 3AUA0000072069 3AUA0000089109 ODE-3-220105-1F4B

1SFA897103R7000 1SFA897102R7000 3AUA0000058190 68581974 68581796 MCD 201-007-T4-CV1 3AUA0000039627

3AXD50000031889 ATS22D17Q 3AXD50000716630 3AUA0000058169 ATV610U55N4 ATV310H075N4E