



- USB stick connected to laptop
- Sigfox radio via SMA connector
- Suitable for all radio configurations
- Compatible with Sigfox Network Emulator and Radio Signal Analyser software packages

**Sigfox SDR dongle** is an USB device associated to a Software package that emulates the Sigfox network. It is intended solely for product or software designers for use in a research and development setting.

**Sigfox SDR Dongle runs** in conducted mode with the object under development and is compatible with all European and FCC bands. Depending on the software used, it allows to develop applications without concern for network coverage issues or analyse radio signals.

More information about the software packages available and download instructions can be found on: [www.support.sigfox.com/products/SDR-dongle](http://www.support.sigfox.com/products/SDR-dongle).

RF CONDUCTED CHARACTERISTICS	
Operating frequency	865-870 MHz, 902-928 MHz software configurable
Monitored spectrum	192kHz
Receiver Sensitivity	-64dBm @ 100bps
Transmit Power	14dBm
Uplink bit rate	100b/s and 600b/s software configurable
Connector	SMA female
INTERFACES	
USB port	USB 2.0 HS
POWER	
Power Consumption	0.2A typ. @5VDC
Max. rating input voltage	6V
MECHANICAL AND ENVIRONMENTAL	
Product dimensions	80 x 25 x 10 mm (3.1 x 1 x 0.4 in)
Product weight	20g (0.7 oz.)
Storage temperature	-20°C to +75°C
Operating temperature & relative humidity	0°C to +40°C 30% to 70%
Max. operating altitude	2000 m above sea level
Environment	Pollution Degree 2
Casing material	ABS
COMPLIANCE	
Safety	EN 60950-1, IEC 60950-1 EN 60950-22, IEC60950-22





# About Sigfox

Sigfox is the world's leading provider of connectivity for the Internet of Things (IoT). The company has built a global network to connect billions of devices to the Internet while consuming as little energy as possible, as simply as possible.

+33 (0)5 82 08 07 10  
Bâtiment E-volution  
425, rue Jean Rostand  
31670 Labège – France  
[sigfox.com](http://sigfox.com)

The information presented is subject to change without notice. Sigfox assumes no responsibility for inaccuracies contained herein.  
[www.sigfox.com](http://www.sigfox.com), Sigfox and the Sigfox logo are trademarks of Sigfox. All other trademarks are the property of their respective owners.  
Copyright © 2017 Sigfox. All rights reserved.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [RF Development Tools](#) category:*

*Click to view products by [Sigfox](#) manufacturer:*

Other Similar products are found below :

[MAAM-011117](#) [MAAP-015036-DIEEV2](#) [EV1HMC1113LP5](#) [EV1HMC6146BLC5A](#) [EV1HMC637ALP5](#) [EVAL-ADG919EBZ](#) [ADL5363-EVALZ](#) [LMV228SDEVAL](#) [SKYA21001-EVB](#) [SMP1331-085-EVB](#) [EV1HMC618ALP3](#) [EVAL01-HMC1041LC4](#) [MAAL-011111-000SMB](#)  
[MAAM-009633-001SMB](#) [107712-HMC369LP3](#) [107780-HMC322ALP4](#) [SP000416870](#) [EV1HMC470ALP3](#) [EV1HMC520ALC4](#)  
[EV1HMC244AG16](#) [124694-HMC742ALP5](#) [SC20ASATEA-8GB-STD](#) [MAX2837EVKIT+](#) [MAX2612EVKIT#](#) [MAX2692EVKIT#](#)  
[SKY12343-364LF-EVB](#) [108703-HMC452QS16G](#) [EV1HMC863ALC4](#) [EV1HMC427ALP3E](#) [119197-HMC658LP2](#) [EV1HMC647ALP6](#)  
[ADL5725-EVALZ](#) [106815-HMC441LM1](#) [EV1HMC1018ALP4](#) [UXN14M9PE](#) [MAX2016EVKIT](#) [EV1HMC939ALP4](#) [MAX2410EVKIT](#)  
[MAX2204EVKIT+](#) [EV1HMC8073LP3D](#) [SIMSA868-DKL](#) [SIMSA868C-DKL](#) [SKY65806-636EK1](#) [SKY68020-11EK1](#) [SKY67159-396EK1](#)  
[SKY66181-11-EK1](#) [SKY65804-696EK1](#) [SKY13396-397LF-EVB](#) [SKY13380-350LF-EVB](#) [SKY13373-460LF-EVB](#)