

**S P Q**  
power  
measurement

$R_{ISO}$   $Z_S$   $R_E$   
 $E$   $R_{CONT}$   
complex  
measurements of  
installations



 **IP54**

**CAT III**

**CAT IV**

**600 V**

**300 V**

## Professional measurements for every budget

### Features

The meter offers a **wide range** of functionalities. It combines the measuring capabilities of several devices, while ensuring equally good accuracy. The device can be used for all measurements for commissioning of electrical installations in accordance with applicable regulations:

- » short circuit loop impedance (also in circuits secured with RCDs),
- » RCD parameters,
- » insulation resistance,
- » earth resistance (3-pole method),
- » continuity of protective and equipotential bondings,
- » phase sequence test,
- » AC voltage and AC current, frequency,
- »  $\cos\phi$ , active (P), reactive (Q) and apparent (S) power (using clamp).

**MPI-520 Start** does not include accessories for earth resistance measurements.

### Additional functions

- Checking the correctness of PE connection using a contact electrode.
- Measurement of voltage (0 ... 500 V) and network frequency.
- Memory of 990 results.
- Wireless data transmission to a computer.



## Application areas

---

MPI-520 is simple in design and use, providing user with many measurement options. It may be successfully used to test household and industrial electrical systems.

## Inspection of electrical safety

---

Measurements can be easily automated with:

- auto mode of residual current devices (RCD) tests,
- the WS adapter that can be used for testing systems via standard 230 V sockets,
- AutoISO-1000C adapter for automatic insulation resistance test of 3-, 4- and 5-conductor cables, without switching.

## Increased resistance to environmental conditions

---

The meter will cope well in difficult environmental conditions. Protection against penetration of dust and water is ensured by a unique housing with a level of protection IP54. It is resistant to mechanical damage, and a special design allows you to easily protect the screen by shielding using the cover of the meter. In addition to the fact that it protects against damage, it also allows you to conveniently carry and use the device in different positions.

## Communication and software

---

You can easily transfer measurement data to your computer via USB port or wireless communication. In order to generate a report on measurements for electric shock protection, use **Sonel Reports PLUS** software. Saving the downloaded data to the simplest formats and printing is provided by free **Sonel Reader** software.



# Specifications

Measurement functions	Measurement range	Display range	Resolution	Accuracy $\pm$ (% m.v. + digits)
<b>Fault loop impedance</b>				
Fault loop $Z_{L-PE}$ , $Z_{L-N}$ , $Z_{L-L}$	0.13 $\Omega$ ...1999 $\Omega$ acc. to IEC 61557	0.00 $\Omega$ ...1999 $\Omega$	from 0.01 $\Omega$	$\pm$ (5% m.v. + 3 digits)
Fault loop $Z_{L-PE}$ in RCD mode	from 0.50 $\Omega$ ...1999 $\Omega$ acc. to IEC 61557	0.00 $\Omega$ ...1999 $\Omega$	from 0.01 $\Omega$	from $\pm$ (6% m.v. + 5 digits)
<b>Measurements of RCD parameters</b>				
RCD tripping test and measurement of tripping time $t_A$ measuring current $0.5 I_{\Delta n}$ , $1 I_{\Delta n}$ , $2 I_{\Delta n}$ , $5 I_{\Delta n}$				
general and short-time delay RCD	0 ms...300 ms	0 ms...300 ms	1 ms	$\pm$ (2% m.v. + 2 digits)
selective RCD	0 ms...500 ms	0 ms...500 ms	1 ms	$\pm$ (2% m.v. + 2 digits)
Measurement of RCD tripping current $I_A$ measuring current $0.2 I_{\Delta n}$ ... $2.0 I_{\Delta n}$				
for sinusoidal residual current (AC type)	3.0 mA...1000 mA	3.0 mA...1000 mA	from 0.1 mA	$\pm$ 5% $I_{\Delta n}$
for unidirectional residual current and unidirectional with the 6 mA DC bias (type A)	3.5 mA...700 mA	3.5 mA...700 mA	from 0.1 mA	$\pm$ 10% $I_{\Delta n}$
for direct residual current (type B)	2.0 mA...1000 mA	2.0 mA...1000 mA	from 0.1 mA	$\pm$ 10% $I_{\Delta n}$
<b>Earth resistance</b>				
3-pole method	from 0.5 $\Omega$ ...1.99 k $\Omega$ acc. to IEC 61557-5	0.00 $\Omega$ ...1.99 k $\Omega$	from 0.01 $\Omega$	from $\pm$ (2% m.v. + 3 digits)
<b>Insulation resistance</b>				
Measuring voltage 50 V	50 k $\Omega$ ...250 M $\Omega$ acc. to IEC 61557-2	0 k $\Omega$ ...250 M $\Omega$	from 1 k $\Omega$	from $\pm$ (3% m.v. + 8 digits)
Measuring voltage 100 V	100 k $\Omega$ ...500 M $\Omega$ acc. to IEC 61557-2	0 k $\Omega$ ...500 M $\Omega$	from 1 k $\Omega$	from $\pm$ (3% m.v. + 8 digits)
Measuring voltage 250 V	250 k $\Omega$ ...999 M $\Omega$ acc. to IEC 61557-2	0 k $\Omega$ ...999 M $\Omega$	from 1 k $\Omega$	from $\pm$ (3% m.v. + 8 digits)
Measuring voltage 500 V	500 k $\Omega$ ...2.00 G $\Omega$ acc. to IEC 61557-2	0 k $\Omega$ ...2.00 G $\Omega$	from 1 k $\Omega$	from $\pm$ (3% m.v. + 8 digits)
Measuring voltage 1000 V	1000 k $\Omega$ ...3.00 G $\Omega$ acc. to IEC 61557-2	0 k $\Omega$ ...3.00 G $\Omega$	from 1 k $\Omega$	from $\pm$ (3% m.v. + 8 digits)
<b>Resistance of protective conductors and equipotential bondings</b>				
Measurement of resistance of protective conductors and equipotential bondings with $\pm$ 200 mA current	0.12 $\Omega$ ...400 $\Omega$ acc. to IEC 61557-4	0.00 $\Omega$ ...400 $\Omega$	from 0.01 $\Omega$	$\pm$ (2% m.v. + 3 digits)
Measurement of resistance with low current	0.0 $\Omega$ ...1999 $\Omega$	0.0 $\Omega$ ...1999 $\Omega$	from 0.1 $\Omega$	$\pm$ (3% m.v. + 3 digits)
<b>Phase sequence indication</b>				
	in the same direction (correct), opposite direction (incorrect). $U_{LL}$ voltage: 95 V...500 V (45 Hz...65 Hz)			
<b>Power measurement</b>				
	0.0 VA...200 000 VA 0.0 W...200 000 W 0.0 var...200 000 var	0.0 VA...200 000 VA 0.0 W...200 000 W 0.0 var...200 000 var	from 0.1 VA from 0.1 W from 0.1 var	from $\pm$ (7% m.v. + 3 digits)

"m.v." - measured value

## Other technical data

### Safety and work conditions

Measuring category according to EN 61010	IV 300 V, III 600 V
Ingress protection	IP54
Type of insulation according to EN 61010-1 and IEC 61557	double
Dimensions	288 x 223 x 75 mm
Weight	ca. 2.2 kg
Operating temperature	0...+50°C
Storage temperature	-20...+70°C
Humidity	20...90%
Nominal temperature	23 ± 2°C
Reference humidity	40%...60%

### Memory and communication

Memory of measurement results	990 cells, 57 500 records
Data transmission	USB 2.0, radio

### Other information

Quality standard – development, design and production	ISO 9001
The product meets the EMC (emission for industrial environment) requirements according to standards	EN 61326-1 EN 61326-2-2

## Standard accessories



**Test lead 1.2 m (banana plugs) red / blue / yellow**

WAPRZ1X2REBB  
WAPRZ1X2BUBB  
WAPRZ1X2YEBB



**Crocodile clip 1 kV 20 A red / yellow**

WAKRORE20K02  
WAKROYE20K02



**Pin probe 1 kV (banana socket) red / blue / yellow**

WASONREOGB1  
WASONBUOGB1  
WASONYEOGB1 optional for MPI-520 Start



**Test lead 15 m, blue (on a reel)**

optional for MPI-520 Start

WAPRZ015BUBBSZ



**Test lead 30 m, red (on a reel)**

optional for MPI-520 Start

WAPRZ030REBBSZ



**WS-03 adapter with START button with UNI-Schuko plug (CAT III 300 V)**

WAADAWS03



**2x earth contact test probe (rod), 30 cm**

optional dla MPI-520 Start

WASONG30



**USB cable**

WAPRZUSB



**Battery pack 4xLR14**

WAPOJ1



**L2 hanging straps (set)**

WAPOZSZEKPL



**L2 carrying case standard for MPI-520 optional for MPI-520 Start**

WAFUTL2



**L4 carrying case optional for MPI-520 standard for MPI-520 Start**

WAFUTL4



**Calibration certificate**

## Optional accessories



**EVSE-01 adapter for testing vehicle charging stations**

WAADAEVSE01



**AutoISO-1000C adapter**

WAADAAISO10C



**WS-04 adapter with UNI-SCHUKO angular plug**

WAADAWS04



**TWR-1J RCD breaker testing adapter**

WAADATWR1J



**AC-16 line splitter**

WAADAAC16



**C-3 clamp (Ø 52 mm)**

WACEGC30KR



**PRS-1 resistance test probe**

WASONPRS1GB



**Foldable pin probe, 1 kV, 2 m (banana socket)**

WASONSP2M



**Crocodile clip 1 kV 20 A blue**

WAKROBU20K02



**Test lead for fault loop measurement (banana plugs) 5 m / 10 m / 20 m**

WAPRZ005REBB  
WAPRZ010REBB  
WAPRZ020REBB



**Test lead for earth resistance measurement 25 m red / blue**

WAPRZ025REBBSZ  
WAPRZ025BUBBSZ



**Test lead for earth resistance measurement 50 m**

WAPRZ050YEBBSZ



**Cramp with banana socket**

WAZACIMA1



**Earth contact test probe 80 cm**

WASONG80



**L-3 carrying case (for 80 cm test probes)**

WAFUTL3



**Industrial socket adapter 16 A / 32 A**

WAADAAGT16T  
WAADAAGT32T



**Three-phase socket adapter 16 A / 32 A**

WAADAAGT16C  
WAADAAGT32C



**Three-phase socket adapter 16 A / 32 A**

WAADAAGT16P  
WAADAAGT32P



**Three-phase socket adapter 63 A**

WAADAAGT63P



**Test wire reel**

WAPQZSZP1



**CS-1 cable simulator**

WAADACS1



### Charging

**Mains cable with IEC C7 plug**

WAPRZLAD230

**Z7 power supply**

WAZASZ7



**Ni-MH battery 4.8 V 4.2 Ah**

WAAKU07



**MPI charging set (charger + battery)**

WAKPLADMPI520



**Cable for battery charging from car cigarette lighter socket (12 V)**

WAPRZLAD12SAM



**OR-1 USB wireless receiver**

WAADAUSBOR1



**Calibration certificate with accreditation**

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Sonel](#) manufacturer:*

Other Similar products are found below :

[AGT-16P](#) [AGT-32P](#) [C-3](#) [C-6A](#) [C-7A](#) [F-3A](#) [K-01](#) [K-02](#) [N-1](#) [S-2](#) [WAKROYE20K02](#) [WAPOZSZE2](#) [WAPRZ050YEBBSZ](#)  
[WAPRZ1X2BUBB](#) [WAPRZ1X2REBB](#) [WAPRZ1X2YEBS](#) [WAPRZ1X8BLBB](#) [WAPRZ1X8REBB](#) [WAPRZCMP1](#) [WASONBUOGB1](#)  
[WASONG30](#) [WASONYEOGB1](#) [WMDEMPI535](#) [WMGBCMM10](#) [WMGBCMM11](#) [WMGBCMM30](#) [WMGBCMM40](#) [WMGBCMP200](#)  
[WMGBCMP2000](#) [WMGBCMP3000](#) [WMGBCMP400](#) [WMGBCMP401](#) [WMGBLKZ720](#) [WMGBLXP2](#) [WMGBMPI506](#) [WMGBP4](#)  
[WMGBP5](#) [WMGBP6](#) [WMGBTG1](#) [WMGBTKF12](#) [WMGBTKF13](#)