

Simple Motor and Encoder Kit



The new simple motor and encoder kit from DAGU combines low cost, reliable encoders with powerful geared motors and 65mm diameter wheels with soft rubber tires and foam rubber inserts. Perfect for any hobbyist or student.

The new geared motors offer two shafts that the magnetic encoder disc can be attached to. When attached to the output shaft the encoder output will change state (high to low or low to high) 8 times per wheel revolution. When the encoder disc is fitted onto the motor shaft the resolution of the encoder is 948 state changes per revolution.

Specifications:

Encoder type:	8-pole neodymium magnet and hall-effect sensor
Encoder output:	Open drain with short circuit protection
Encoder voltage:	3V – 24V with reverse polarity protection
Encoder resolution:	8 state changes / revolution when mounted on the output shaft 948 state changes / revolution when mounted on the motor shaft
Motor voltage:	3V – 6V
No load current:	200mA
Stall Current:	3A @ 6V 1.5A @ 3V
Gearbox ratio:	48:1
Wheel Speed:	135rpm @6V unloaded

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [SparkFun Accessories](#) category:

Click to view products by [SparkFun](#) manufacturer:

Other Similar products are found below :

[DEV-17119](#) [SEN-16474](#) [COM-11450](#) [BOB-00495](#) [BOB-00497](#) [PRT-08619](#) [PRT-12702](#) [SEN-13582](#) [TOL-11468](#) [ROB-09065](#) [COM-12999](#)
[COM-12986](#) [COM-11120](#) [ROB-11965](#) [COM-11222](#) [PRT-12845](#) [CAB-13685](#) [PRT-10210](#) [PRT-14490](#) [TOL-10603](#) [COM-09278](#) [PRT-08023](#)
[COM-08033](#) [DEV-14052](#) [PRT-00111](#) [PRT-08432](#) [TOL-09317](#) [TOL-10997](#) [PRT-00743](#) [PRT-14492](#) [TOL-14228](#) [COM-13247](#) [PRT-11026](#)
[CAB-10646](#) [TOL-08964](#) [PRT-00116](#) [PRT-08506](#) [CAB-09741](#) [COM-10800](#) [SEN-14282](#) [DEV-14012](#) [CAB-14043](#) [COM-14452](#) [TOL-14508](#)
[DEV-13814](#) [GPS-00574](#) [PRT-14417](#) [PRT-08231](#) [COM-09939](#) [PRT-13839](#)