

Discovery kit with STM32F412ZG MCU



Picture is not contractual.

Product status link

[32F412GDISCOVERY](#)

Features

- STM32F412ZGT6 microcontroller with 1 Mbyte of Flash memory and 256 Kbytes of RAM, in an LQFP144 package
- 1.54-inch 240×240 pixel TFT color LCD with parallel interface and capacitive touch panel
- USB OTG FS
- I²S audio codec
- Stereo digital ST-MEMS microphones
- 128-Mbit Quad-SPI NOR Flash memory
- Reset push-button and joystick
- 4 color user LEDs
- Board connectors:
 - microSD™ card
 - User USB with Micro-AB
 - Stereo headset jack with analog microphone input and a loudspeaker output
 - I²C expansion connector
 - ARDUINO® Uno V3 expansion connectors
 - 2.54 mm pitch expansion connector for direct access to various features of the STM32F412ZGT6 microcontroller
- Flexible power-supply options: ST-LINK USB V_{BUS}, user USB FS connector, or external sources
- Comprehensive free software libraries and examples available with the STM32Cube MCU Package
- On-board ST-LINK/V2-1 debugger/programmer with USB re-enumeration capability: mass storage, Virtual COM port, and debug port
- Support of a wide choice of Integrated Development Environments (IDEs) including IAR Embedded Workbench®, MDK-ARM, and STM32CubeIDE

Description

With the STM32F412 Discovery kit ([32F412GDISCOVERY](#)), users develop applications easily on the STM32F412 high-performance MCUs with Arm® Cortex®-M4 core. The Discovery kit combines the STM32F412 features with 1.54-inch 240×240 pixel TFT color LCD with touch panel, LEDs, joystick, I²S audio codec, MEMS microphones, USB OTG FS, Quad-SPI NOR Flash memory, and microSD™ card connector.

An embedded ST-LINK/V2-1 debugger/programmer is included. Specialized add-on boards can be connected by means of the ARDUINO® Uno or expansion connectors.

1 Ordering information

To order the 32F412GDISCOVERY Discovery kit, refer to [Table 1](#). For a detailed description, refer to its user manual on the product web page. Additional information is available from the datasheet and reference manual of the target microcontroller.

Table 1. List of available products

Order code	Board reference	User manual	Target STM32
STM32F412G-DISCO	MB1209	UM2032	STM32F412ZGT6

1.1 Product marking

The stickers located on the top or bottom side of the PCB provide product information:

- Product order code and product identification for the first sticker
- Board reference with revision, and serial number for the second sticker

On the first sticker, the first line provides the product order code, and the second line the product identification.

On the second sticker, the first line has the following format: "MBxxx-Variant-yyz", where "MBxxx" is the board reference, "Variant" (optional) identifies the mounting variant when several exist, "y" is the PCB revision and "zz" is the assembly revision, for example B01. The second line shows the board serial number used for traceability.

Evaluation tools marked as "ES" or "E" are not yet qualified and therefore not ready to be used as reference design or in production. Any consequences deriving from such usage will not be at ST charge. In no event, ST will be liable for any customer usage of these engineering sample tools as reference designs or in production.

"E" or "ES" marking examples of location:

- On the targeted STM32 that is soldered on the board (For an illustration of STM32 marking, refer to the STM32 datasheet "Package information" paragraph at the www.st.com website).
- Next to the evaluation tool ordering part number that is stuck or silk-screen printed on the board.

1.2 Codification

The meaning of the codification is explained in [Table 2](#).

Table 2. Codification explanation

STM32F4XXY-DISCO	Description	Example: STM32F412G-DISCO
STM32F4	MCU series in STM32 32-bit Arm Cortex MCUs	STM32F4 Series
XX	MCU product line in the series	STM32F412
Y	STM32 Flash memory size: • G for 1 Mbyte	1 Mbyte
DISCO	Discovery kit	Discovery kit

2 Development environment

The 32F412GDISCOVERY runs with the STM32F412ZGT6 32-bit microcontroller based on the Arm[®] Cortex[®]-M4 core.

Note: Arm is a registered trademark of Arm Limited (or its subsidiaries) in the US and/or elsewhere.



2.1 System requirements

- Multi-OS support: Windows[®] 10, Linux[®] 64-bit, or macOS[®]
- USB Type-A or USB Type-C[®] to Micro-B cable

Note: macOS[®] is a trademark of Apple Inc. registered in the U.S. and other countries.

Linux[®] is a registered trademark of Linus Torvalds.

All other trademarks are the property of their respective owners.

2.2 Development toolchains

- IAR Systems[®] - IAR Embedded Workbench^{®(1)}
- Keil[®] - MDK-ARM⁽¹⁾
- STMicroelectronics - STM32CubeIDE

1. On Windows[®] only.

Revision history

Table 3. Document revision history

Date	Revision	Changes
29-Jul-2016	1	Initial release.
27-Oct-2021	2	Removed <i>Technology partner</i> and <i>Demonstration software</i> . Revised the entire document: <ul style="list-style-type: none"> • Updated Features, Description, Ordering information, System requirements and Development toolchains • Added Product marking and Codification

IMPORTANT NOTICE – PLEASE READ CAREFULLY

STMicroelectronics NV and its subsidiaries (“ST”) reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST’s terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers’ products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. For additional information about ST trademarks, please refer to www.st.com/trademarks. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2021 STMicroelectronics – All rights reserved

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Development Boards & Kits - ARM category](#):

Click to view products by [STMicroelectronics manufacturer](#):

Other Similar products are found below :

[SAFETI-HSK-RM48](#) [PICOHOBBITFL](#) [CC-ACC-MMK-2443](#) [TWR-MC-FRDMKE02Z](#) [EVALSPEAR320CPU](#) [EVB-SCMIMX6SX](#)
[MAX32600-KIT#](#) [TMDX570LS04HDK](#) [TXSD-SV70](#) [OM13080UL](#) [EVAL-ADUC7120QSPZ](#) [OM13082UL](#) [TXSD-SV71](#)
[YGRPEACHNORMAL](#) [OM13076UL](#) [PICODWARFFL](#) [YR8A77450HA02BG](#) [3580](#) [32F3348DISCOVERY](#) [ATTINY1607](#) [CURIOSITY](#)
[NANO](#) [PIC16F15376](#) [CURIOSITY NANO BOARD](#) [PIC18F47Q10](#) [CURIOSITY NANO](#) [VISIONSTK-6ULL V.2.0](#) [80-001428](#) [DEV-17717](#)
[EAK00360](#) [YR0K77210B000BE](#) [RTK7EKA2L1S00001BE](#) [MAX32651-EVKIT#](#) [SLN-VIZN-IOT](#) [LV18F V6 DEVELOPMENT SYSTEM](#)
[READY FOR AVR BOARD](#) [READY FOR PIC BOARD](#) [READY FOR PIC \(DIP28\)](#) [EVB-VF522R3](#) [AVRPLC16 V6 PLC SYSTEM](#)
[MIKROLAB FOR AVR XL](#) [MIKROLAB FOR PIC L](#) [MINI-AT BOARD - 5V](#) [MINI-M4 FOR STELLARIS](#) [MOD-09.Z](#) [BUGGY +](#)
[CLICKER 2 FOR PIC32MX + BLUETOOT](#) [1410](#) [LETS MAKE PROJECT PROGRAM. RELAY PIC](#) [LETS MAKE - VOICE](#)
[CONTROLLED LIGHTS](#) [LPC-H2294](#) [DSPIC-READY2 BOARD](#) [DSPIC-READY3 BOARD](#) [MIKROBOARD FOR ARM 64-PIN](#)
[MIKROLAB FOR AVR](#)