

CGHV14500F

500 W, DC - 1800 MHz, GaN HEMT for L-Band Radar Systems



Package Types: 440117, 440133
PNs: CGHV14500F, CGHV14500P

Description

Cree's CGHV14500 is a gallium nitride (GaN) high electron mobility transistor (HEMT) designed specifically with high efficiency, high gain and wide bandwidth capabilities, which makes the CGHV14500 ideal for DC - 1.8 GHz L-Band radar amplifier applications. The transistor could be utilized for band specific applications ranging from 800 through 1600 MHz. The package options are ceramic/metal flange and pill package.

Typical Performance Over 1.2 - 1.4 GHz (TC = 25 °C) of Demonstration Amplifier

Parameter	1.2 GHz	1.25 GHz	1.3 GHz	1.35 GHz	1.4 GHz	Units
Output Power	545	540	530	530	530	W
Gain	16.4	16.3	16.2	16.2	16.2	dB
Drain Efficiency	69	69	68	66	65	%

Note: Measured in the CGHV14500-AMP amplifier circuit, under 500 µs pulse width, 10% duty cycle, PIN = 41 dBm.

Features

- Reference design amplifier 1.2 - 1.4 GHz Operation
- FET tuning range UHF through 1800 MHz
- 500 W Typical Output Power
- 16 dB Power Gain
- 68% Typical Drain Efficiency
- <0.3 dB Pulsed Amplitude Droop
- Internally pre-matched on input, unmatched output



Large Signal Models Available for ADS and MWO

RoHS
COMPLIANT



Absolute Maximum Ratings (not simultaneous)

Parameter	Symbol	Rating	Units	Conditions
Drain-Source Voltage	V_{DSS}	150	Volts	25 °C
Gate-to-Source Voltage	V_{GS}	-10, +2	Volts	25 °C
Storage Temperature	T_{STG}	-65, +150	°C	
Operating Junction Temperature	T_J	225	°C	
Maximum Forward Gate Current	I_{GMAX}	84	mA	25 °C
Maximum Drain Current ¹	I_{DMAX}	36	A	25 °C
Soldering Temperature ²	T_s	245	°C	
Screw Torque	τ	40	in-oz	
Pulsed Thermal Resistance, Junction to Case ³	$R_{\theta JC}$	0.28	°C/W	$P_{DISS} = 334 \text{ W}, 500 \mu\text{sec}, 10\%, 85 \text{ °C}$
Pulsed Thermal Resistance, Junction to Case ⁴	$R_{\theta JC}$	0.31	°C/W	$P_{DISS} = 334 \text{ W}, 500 \mu\text{sec}, 10\%, 85 \text{ °C}$
Case Operating Temperature ⁵	T_c	-40, +130	°C	$P_{DISS} = 334 \text{ W}, 500 \mu\text{sec}, 10\%$

Notes:

¹ Current limit for long term, reliable operation² Refer to the Application Note on soldering at www.wolfspeed.com/rf/document-library³ Measured for the CGHV14500P⁴ Measured for the CGHV14500F⁵ See also, the Power Dissipation De-rating Curve on Page 5

Electrical Characteristics ($T_c = 25 \text{ °C}$)

Characteristics	Symbol	Min.	Typ.	Max.	Units	Conditions
DC Characteristics¹						
Gate Threshold Voltage	$V_{GS(th)}$	-3.8	-3.0	-2.3	V_{DC}	$V_{DS} = 10 \text{ V}, I_D = 83.6 \text{ mA}$
Gate Quiescent Voltage	$V_{GS(Q)}$	-	-2.7	-	V_{DC}	$V_{DS} = 50 \text{ V}, I_D = 500 \text{ mA}$
Saturated Drain Current ²	I_{DS}	54.3	77.7	-	A	$V_{DS} = 6.0 \text{ V}, V_{GS} = 2.0 \text{ V}$
Drain-Source Breakdown Voltage	V_{BR}	125	-	-	V_{DC}	$V_{GS} = -8 \text{ V}, I_D = 83.6 \text{ mA}$
RF Characteristics³ ($T_c = 25 \text{ °C}$, $F_0 = 1.4 \text{ GHz}$ unless otherwise noted)						
Output Power	P_{OUT}	400	500	-	W	$V_{DD} = 50 \text{ V}, I_{DQ} = 500 \text{ mA}, P_{IN} = 41 \text{ dBm}$
Drain Efficiency	D_E	60	68	-	%	$V_{DD} = 50 \text{ V}, I_{DQ} = 500 \text{ mA}, P_{IN} = 41 \text{ dBm}$
Power Gain	G_p	15.25	16.2	-	dB	$V_{DD} = 50 \text{ V}, I_{DQ} = 500 \text{ mA}, P_{IN} = 41 \text{ dBm}$
Pulsed Amplitude Droop	D	-	-0.3	-	dB	$V_{DD} = 50 \text{ V}, I_{DQ} = 500 \text{ mA}$
Output Mismatch Stress	VSWR	-	5 : 1	-	Y	No damage at all phase angles, $V_{DD} = 50 \text{ V}, I_{DQ} = 500 \text{ mA}, P_{IN} = 41 \text{ dBm}$ Pulsed
Dynamic Characteristics						
Input Capacitance	C_{GS}	-	295	-	pF	$V_{DS} = 50 \text{ V}, V_{GS} = -8 \text{ V}, f = 1 \text{ MHz}$
Output Capacitance	C_{DS}	-	27	-	pF	$V_{DS} = 50 \text{ V}, V_{GS} = -8 \text{ V}, f = 1 \text{ MHz}$
Feedback Capacitance	C_{GD}	-	2.7	-	pF	$V_{DS} = 50 \text{ V}, V_{GS} = -8 \text{ V}, f = 1 \text{ MHz}$

Notes:

¹ Measured on wafer prior to packaging² Scaled from PCM data³ Measured in CGHV14500-AMP. Pulsed Width = 500 μs , Duty Cycle = 10%.



Typical Performance of the CGHV14500F

Test conditions unless otherwise noted: $V_D = 50 \text{ V}_D$, $I_{DQ} = 500 \text{ mA}$, $PW = 500 \mu\text{s}$, $DC = 10\%$, $\text{Pin} = 42 \text{ dBm}$, $T_{\text{BASE}} = +25^\circ\text{C}$

Figure 1. Output Power vs Frequency as a Function of Temperature




Figure 2. Drain Current vs Frequency as a Function of Temperature




Figure 3. Power Added Eff. vs Frequency as a Function of Input Power




Figure 4. Output Power vs Frequency as a Function of Input Power





Figure 5. Drain Current vs Frequency as a Function of Input Power





Typical Performance of the CGHV14500F

Test conditions unless otherwise noted: $V_D = 50$ V, $ID_Q = 500$ mA, $PW = 500$ us, $DC = 10\%$, $Pin = 42$ dBm, $T_{BASE} = +25$ °C

Figure 6. Output Power vs Frequency as a Function of Voltage




Figure 7. Output Power vs Frequency as a Function of IDQ




Figure 8. Power Added Eff. vs Frequency as a Function of Voltage




Figure 9. Power Added Eff. vs Frequency as a Function of IDQ




Figure 10. Drain Current vs Frequency as a Function of Voltage





Figure 11. Drain Current vs Frequency as a Function of IDQ





Typical Performance of the CGHV14500F

Test conditions unless otherwise noted: $V_D = 50$ V, $ID_Q = 500$ mA, $PW = 500$ us, $DC = 10\%$, $Pin = 42$ dBm, $T_{BASE} = +25$ °C

Figure 12. Output Power vs Input Power as a Function of Frequency




Figure 13. Power Added Eff. vs Input Power as a Function of Frequency




Figure 14. Large Signal Gain vs Input Power as a Function of Frequency




Figure 15. Drain Current vs Input Power as a Function of Frequency





Figure 16. Gate Current vs Input Power as a Function of Frequency





Typical Performance of the CGHV14500F

Test conditions unless otherwise noted: $V_D = 50$ V, $IDQ = 500$ mA, $PW = 500$ us, $DC = 10\%$, $Pin = 42$ dBm, $T_{BASE} = +25$ °C

Figure 17. Output Power vs Input Power as a Function of Temperature




Figure 18. Large Signal Gain vs Input Power as a Function of Temperature




Figure 19. Drain Current vs Input Power as a Function of Temperature





Figure 20. Gate Current vs Input Power as a Function of Temperature





Typical Performance of the CGHV14500F

Test conditions unless otherwise noted: $V_D = 50 \text{ V}_D$, $I_{DQ} = 500 \text{ mA}$, $PW = 500 \mu\text{s}$, $DC = 10\%$, $\text{Pin} = 42 \text{ dBm}$, $T_{\text{BASE}} = +25^\circ\text{C}$

Figure 21. Output Power vs Input Power as a Function of IDQ




Figure 22. Power Added Eff. vs Input Power as a Function of IDQ




Figure 23. Large Signal Gain vs Input Power as a Function of IDQ




Figure 24. Drain Current vs Input Power as a Function of IDQ





Figure 25. Gate Current vs Input Power as a Function of IDQ





Typical Performance of the CGHV14500F

Test conditions unless otherwise noted: $V_D = 50 \text{ V}_D$, $I_{DQ} = 500 \text{ mA}$, CW, Pin = -20 dBm, $T_{\text{BASE}} = +25^\circ\text{C}$

Figure 26. Gain vs Frequency as a Function of Temperature




Figure 27. Gain vs Frequency as a Function of Temperature




Figure 28. Input RL vs Frequency as a Function of Temperature




Figure 29. Input RL vs Frequency as a Function of Temperature




Figure 30. Output RL vs Frequency as a Function of Temperature





Figure 31. Output RL vs Frequency as a Function of Temperature





Typical Performance of the CGHV14500F

Test conditions unless otherwise noted: $V_D = 50 \text{ V}_D$, $I_{DQ} = 500 \text{ mA}$, CW, Pin = -20 dBm, $T_{\text{BASE}} = +25^\circ\text{C}$

Figure 32. Gain vs Frequency as a Function of Voltage




Figure 33. Gain vs Frequency as a Function of IDQ




Figure 34. Input RL vs Frequency as a Function of Voltage




Figure 35. Input RL vs Frequency as a Function of IDQ




Figure 36. Output RL vs Frequency as a Function of Voltage








Figure 37. Output RL vs Frequency as a Function of IDQ



CGHV14500F-AMP Demonstration Amplifier Circuit Bill of Materials

Designator	Description	Qty
R1	RES, 1/16W, 0603, 1%, 562 OHMS	1
R2	RES, 5.1 OHM, +/-1%, 1/16W, 0603	1
R3	RES, 1/16W, 0603, 1%, 4700 OHMS	1
L1	INDUCTOR, CHIP, 6.8 nH, 0603 SMT	1
C1, C23	CAP, 27pF, +/- 5%, 250V, 0805, ATC 600F	2
C2	CAP, 2.0pF, +/- 0.1pF, 0603, ATC	1
C3, C4	CAP, 1.5pF, +/-0.05pF, 250V, 0805, ATC 600F	2
C5,C6	CAP, 1.8pF, +/-0.1pF, 250V, 0805, ATC 600F	2
C7,C8	CAP, 4.3pF, +/-0.1pF, 250V, 0805, ATC 600F	2
C9,C10	CAP, 7.5pF, +/-0.1pF, 250V, 0805, ATC 600F	2
C11,C24	CAP, 47pF,+/-5%, 250V, 0805, ATC 600F	2
C12,C25	CAP, 100pF, +/-5%, 250V, 0805, ATC 600F	2
C13,C26	CAP, 33000PF, 0805,100V, X7R	2
C14	CAP 10uF 16V TANTALUM	1
C15,C16	CAP, 5.6pF, +/-0.1pF, 250V, 0805, ATC 600F	2
C17,C18	CAP, 3.6pF, +/-0.1pF, 250V, 0805, ATC 600F	2
C19,C20	CAP, 2.0pF, +/-0.1pF, 250V, 0805, ATC 600F	2
C21,C22	CAP, 0.7pF, +/-0.05pF, 0805, ATC 600F	2
C27	CAP, 1.0UF, 100V, 10%, X7R, 1210	1
C28	CAP, 3300 UF, +/-20%, 100V, ELECTROLYTIC	1
J1,J2	CONN, SMA, PANEL MOUNT JACK, FL	2
J3	HEADER RT>PLZ .1CEN LK 9POS	1
J4	CONNECTOR ; SMB, Straight, JACK,SMD	1
W1	CABLE ,18 AWG, 4.2	1
	PCB, RO4350B, 0.020" MIL THK, CGHV14500, 1.2-1.4GHZ	1
Q1	CGHV14500F	1

CGHV14500F-AMP Demonstration Amplifier Circuit

CGHV14500-AMP Demonstration Amplifier Circuit Outline**CGHV14500-AMP Demonstration Amplifier Circuit Schematic**




Typical Performance Over 0.96 GHz - 1.3 GHz (TC = 25 °C) of Demonstration Amplifier


Parameter	0.96 GHz	1.0 GHz	1.1 GHz	1.2 GHz	1.3 GHz	Units
Output Power	800	805	675	625	585	W
Gain	18	18.1	17.3	17.0	16.7	dB
Drain Efficiency	70	75	74	77	64	%

Note: Measured in the CGHV14500-AMP2 amplifier circuit, under 500 µs pulse width, 10% duty cycle, $P_{IN} = 41$ dBm.

Typical Performance - CGHV14500-AMP2

CGHV14500-AMP2 Typical Sparameters
 $V_{DD} = 50$ V, $I_{DQ} = 500$ mA




**Typical Performance - CGHV14500-AMP2**



CGHV14500F-AMP2 Demonstration Amplifier Circuit Bill of Materials


Designator	Description	Qty
R1	RES,1/16W,0603,1%,562 OHMS	1
R2	RES, 5.1,OHM, +/- 1%, 1/16W,0603	1
R3	RES,1/16W,0603,1%,4.99K OHMS	1
C1, C7, C8, C23	CAP, 10pF, +/-0.1pF, 250V, 0805, ATC600F	4
C2, C15, C16	CAP, 5.6pF, +/-0.1pF, 250V, 0805, ATC600F	3
C3, C4, C5, C6	CAP, 2.2pF, +/-0.1pF, 250V, 0805, ATC600F	4
C17, C18	CAP, 2.4pF, +/-0.1pF, 250V, 0805, ATC600F	2
C19, C20	CAP, 2.0pF, +/-0.1pF, 250V, 0805, ATC600F	2
C31, C32	CAP, 2.7pF, +/-0.1pF, 250V, 0805, ATC600F	2
C22, C33	CAP, 1.5pF, +/-0.1pF, 250V, 0805, ATC600F	2
C11, C24	CAP, 47 PF +/- 5%, 250V, 0805, ATC600F	2
C12, C25	CAP, 100 PF +/- 5%, 250V, 0805, ATC 600F	2
C13, C26	CAP,33000PF, 0805,100V, X7R	2
C14	CAP 10UF 16V TANTALUM	1
C27	CAP, 1.0UF, 100V, 10%, X7R, 1210	1
C28	CAP, 3300 UF, +/-20%, 100V, ELECTROLYTIC	1
J1, J2	CONN, SMA, PANEL MOUNT JACK, FL	2
J3	HEADER RT>PLZ .1CEN LK 9POS	1
J4	CONNECTOR ; SMB, Straight, JACK,SMD	1
W1	CABLE ,18 AWG, 4.2	1
	PCB, RO4350B, 0.020" THK, CGHV14500-TB1	1
	BASEPLATE, AL, 4.00 X 2.50 X 0.49, ALTERNATE HOLE PATTERN	1

CGHV14500F-AMP2 Demonstration Amplifier Circuit







CGHV14500-AMP2 Demonstration Amplifier Circuit Outline



CGHV14500-AMP2 Demonstration Amplifier Circuit Schematic



Source and Load Impedances




Frequency	Z Source	Z Load
900	0.3 - j0.3	2.1 + j1.4
1000	0.3 - j0.4	2.0 + j0.7
1100	0.6 - j0.4	1.8 + j0.9
1200	0.8 - j0.7	1.5 + j0.9
1300	1.1 - j0.7	1.3 + j0.7
1400	1.2 - j0.1	1.2 + j0.5
1500	1.8 - j0.1	1.1 + j0.4

Note 1. $V_{DD} = 50$ V, $I_{DQ} = 500$ mA in the 440117 package.

Note 2. Optimized for power gain, P_{SAT} and Drain Efficiency


Note 3. When using this device at low frequency, series resistors should be used to maintain amplifier stability.

CGHV14500 Power Dissipation De-rating Curve



Note 1. Area exceeds Maximum Case Operating Temperature (See Page 2)

Product Dimensions CGHV14500F (Package Type — 440117)




NOTES:

1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M - 1994.
2. CONTROLLING DIMENSION: INCH.
3. ADHESIVE FROM LID MAY EXTEND A MAXIMUM OF 0.020" BEYOND EDGE OF LID.
4. LID MAY BE MISALIGNED TO THE BODY OF PACKAGE BY A MAXIMUM OF 0.008" IN ANY DIRECTION.

DIM	INCHES		MILLIMETERS		NOTES
	MIN	MAX	MIN	MAX	
A	0.138	0.158	3.51	4.01	
A1	0.057	0.067	1.45	1.70	
A2	0.035	0.045	0.89	1.14	
b	0.495	0.505	12.57	12.83	2x
c	0.003	0.006	0.08	0.15	
D	1.335	1.345	33.91	34.16	
D1	1.095	1.105	27.81	28.07	
D2	0.773	0.787	19.63	20.00	
E	0.745	0.785	18.92	19.94	
E1	0.380	0.390	9.65	9.91	
E2	0.365	0.375	9.72	9.53	
E3	0.123	0.133	3.12	3.38	
L	0.170	0.210	4.32	5.33	2x
r	0.06	TYP	0.06	TYP	4x
alpha	45°	REF	45°	REF	

PIN 1. GATE
2. DRAIN
3. SOURCE

Product Dimensions CGHV14500P (Package Type — 440133)



NOTES:

1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
2. CONTROLLING DIMENSION: INCH.
3. ADHESIVE FROM LID MAY EXTEND A MAXIMUM OF 0.020" BEYOND EDGE OF LID.
4. LID MAY BE MISALIGNED TO THE BODY OF PACKAGE BY A MAXIMUM OF 0.008" IN ANY DIRECTION.

DIM	INCHES		MILLIMETERS	
	MIN	MAX	MIN	MAX
A	0.805	0.815	20.45	20.70
B	0.380	0.390	9.65	9.91
C	0.135	0.149	3.43	3.78
D	0.495	0.505	12.57	12.83
E	0.035	0.045	.89	1.14
H	0.057	0.067	1.45	1.70
J	0.003	0.006	.08	.15
K	0.170	0.210	4.32	5.33
M	45° REF		45° REF	
N	0.773	0.787	19.63	19.99
Q	0.020	REF	0.51	REF
R	0.364	0.374	9.25	9.50
S	0.030 REF		0.76 REF	
T	0.745	0.785	18.92	19.94

STYLE 1:
PIN 1. GATE
2. DRAIN
3. SOURCE



Part Number System

CGHV14500F




Table 1

Parameter	Value	Units
Upper Frequency ¹	1.4	GHz
Power Output	500	W
Type	F = Flanged P = Package	-

¹ Alpha characters used in frequency code indicate a value greater than 9.9 GHz. See Table 2 for value.

Table 2

Character Code	Code Value
A	0
B	1
C	2
D	3
E	4
F	5
G	6
H	7
J	8
K	9

Examples:

1A = 10.0 GHz
2H - 27.0 GHz

**Product Ordering Information**

Order Number	Description	Unit of Measure	Image
CGHV14500F	GaN HEMT	Each	
CGHV14500P	GaN HEMT	Each	
CGHV14500F-AMP	Test board with GaN HEMT installed	Each	



For more information, please contact:

4600 Silicon Drive
Durham, North Carolina, USA 27703
www.wolfspeed.com/RF

Sales Contact
RFSales@cree.com

Notes

Disclaimer

Specifications are subject to change without notice. "Typical" parameters are the average values expected by Cree in large quantities and are provided for information purposes only. Cree products are not warranted or authorized for use as critical components in medical, life-saving, or life-sustaining applications, or other applications where a failure would reasonably be expected to cause severe personal injury or death. No responsibility is assumed by Cree for any infringement of patents or other rights of third parties which may result from use of the information contained herein. No license is granted by implication or otherwise under any patent or patent rights of Cree.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for RF Development Tools category:

Click to view products by Wolfspeed manufacturer:

Other Similar products are found below :

[MAAM-011117](#) [MAAP-015036-DIEEV2](#) [EV1HMC1113LP5](#) [EV1HMC6146BLC5A](#) [EV1HMC637ALP5](#) [EVAL-ADG919EBZ](#) [ADL5363-EVALZ](#) [LMV228SDEVAL](#) [SKYA21001-EVB](#) [SMP1331-085-EVB](#) [EV1HMC618ALP3](#) [EVAL01-HMC1041LC4](#) [MAAL-011111-000SMB](#) [MAAM-009633-001SMB](#) [107712-HMC369LP3](#) [107780-HMC322ALP4](#) [SP000416870](#) [EV1HMC470ALP3](#) [EV1HMC520ALC4](#) [EV1HMC244AG16](#) [MAX2614EVKIT#](#) [124694-HMC742ALP5](#) [SC20ASATEA-8GB-STD](#) [MAX2837EVKIT+](#) [MAX2612EVKIT#](#) [MAX2692EVKIT#](#) [EV1HMC629ALP4E](#) [SKY12343-364LF-EVB](#) [108703-HMC452QS16G](#) [EV1HMC863ALC4](#) [EV1HMC427ALP3E](#) [119197-HMC658LP2](#) [EV1HMC647ALP6](#) [ADL5725-EVALZ](#) [106815-HMC441LM1](#) [EV1HMC1018ALP4](#) [UXN14M9PE](#) [MAX2016EVKIT](#) [EV1HMC939ALP4](#) [MAX2410EVKIT](#) [MAX2204EVKIT+](#) [EV1HMC8073LP3D](#) [SIMSA868-DKL](#) [SIMSA868C-DKL](#) [SKY65806-636EK1](#) [SKY68020-11EK1](#) [SKY67159-396EK1](#) [SKY66181-11-EK1](#) [SKY65804-696EK1](#) [SKY13396-397LF-EVB](#)