

## Triple Axis EMF Tester

✓ **Three axis (X,Y,Z) electromagnetic field measurement**  
For testing fans, electrical appliances, wiring, and power lines

### Features:

- Three axis ( X, Y, Z direction) electromagnetic field measurement
- Designed to provide user a quick, reliable and easy way to measure electromagnetic field radiation levels around power lines, electrical appliances and industrial devices
- Wide ranges (3 ranges of  $\mu$ Tesla or mGauss)
- Calibrated to measure EMF radiation at wide bandwidths from 30 Hz to 300 Hz
- Big digit LCD display
- Data hold freezes reading on display
- Easy to use remote probe
- Complete with sensor with 3ft (930mm) cable, 9V battery, and hard carrying case



Specifications	Range	Resolution	Basic Accuracy
$\mu$ Tesla	20 $\mu$ Tesla	0.01 $\mu$ Tesla	$\pm(4\% + 3d)$
	200 $\mu$ Tesla	0.1 $\mu$ Tesla	$\pm(5\% + 3d)$
	2000 $\mu$ Tesla	1 $\mu$ Tesla	$\pm(10\% + 5d)$
mGauss	200mGauss	0.1mGauss	$\pm(4\% + 3d)$
	2,000mGauss	1mGauss	$\pm(5\% + 3d)$
	20,000mGauss	10mGauss	$\pm(10\% + 5d)$
Number of Axis	Three axis X, Y, Z direction		
Band width	30Hz to 300Hz		
Sampling Time	Approx. 0.4 second		
Power Current	Approx. DC 2.7mA		
Dimensions	7.6x2.6x1.2" (195x68x30mm)		

### Ordering Information:

480826 .....Triple Axis EMF Meter



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Environmental Test Equipment](#) category:*

*Click to view products by [Extech](#) manufacturer:*

Other Similar products are found below :

[CW40](#) [F150C10E3DRT](#) [F150LTC20](#) [F150CD10E2](#) [F150L75](#) [F150LRS](#) [S-11](#) [FLUKE-LDG](#) [382153](#) [FM100](#) [RH210](#) [382253](#) [MO290-P](#)  
[GEO-CABLE-REEL-50M](#) [T197914](#) [RD300-L](#) [IR11BD](#) [IR11GM](#) [IR12GM](#) [IR21BD](#) [IR31CE](#) [IR32BC](#) [IR33BC](#) [MP7217TC](#) [NGM-1](#) [SGX-](#)  
[7NH3](#) [UT381](#) [F150-SLC50](#) [AW-CO-1000](#) [AW-NmHc-100](#) [3.000.401](#) [AX-7535](#) [CS-9S6SS-A](#) [P 2800 A](#) [P 2801](#) [P 2802](#) [P 5039](#) [P 5130](#) [P](#)  
[5055](#) [P 5060](#) [P 5065](#) [P 5086](#) [P 5090](#) [P 5110](#) [P 5115](#) [P 5135](#) [P 5140](#) [P 5145](#) [P 5150](#) [P 5160](#)