

GENERAL SPECIFICATION

Display :
 Voltage functions: 6000 counts LCD display
 Power, Ohm & Hz functions: 9999 counts LCD display
 ACA clamp-on function: 4000 counts LCD display
Update Rate :
 Power function: 2 per second nominal
 Voltage, ACA clamp-on & Ohm functions: 2 per second nominal
 Hz function: 1 per second nominal
Polarity : Automatic
Low Battery : Below approx. 2.4V
Operating Temperature : 0°C to 40°C
Relative Humidity : Maximum relative humidity 80% for temperature up to 31°C decreasing linearly to 50% relative humidity at 40°C
Altitude : Operating below 2000m
Storage Temperature : -20°C to 60°C, < 80% R.H. (with battery removed)

Temperature Coefficient : nominal 0.15 x (specified accuracy)/°C @ (0°C -18°C or 28°C -40°C), or otherwise specified
Sensing : True RMS sensing
Safety : Meets IEC61010-2-032(2002), EN61010-2-032(2002), UL61010B-2-032(2003)
Measurement Category : III 600 Volts ac & dc
Transient protection : 6.5kV (1.2/50µs surge)
Pollution degree : 2
E.M.C. : Meets EN61326(1997, 1998/A1), EN61000-4-2(1995, 2000/A2), and EN61000-4-3(2002)
In an RF field of 3V/m:
 Total Accuracy = Specified Accuracy + 50 digits
 Performance above 3V/m is not specified
Overload Protections :
 ACA Clamp-on jaws : AC 1000A rms continuous & COM terminals (all functions) : 600VDC/VAC rms
Power Supply : standard 1.5V AAA Size (NEDA 24A or IEC LR03) battery X 2

Power Consumption :
 Voltage, ACA, Hz & Power functions: 11mA typical
 Ohm function: 5.5mA typical
APO Timing : Idle for 30 minutes
APO Consumption : 4µA typical
Dimension : L224mm X W78mm X H40mm
Weight : 224 gm approx
Jaw opening & Conductor diameter : 45mm max
Special features : Backlight display; AutoVA™ (Auto Selection on ACV, DCV or ACA functions); selectable Power parameters of W, VAR & VA with Total Power Factor in dual-display; Total harmonic distortion THD%-F in dual-display; kWhr Recording; Display Hold; PEAK-rms HOLD; PC-Comm computer interface capabilities
Accessories : Test leads (pair), batteries installed, user's manual & soft carrying pouch
Optional accessories : BR157 PC interface kit (including BA-1XX optical adapter back, BC-100R cable & Bs157 software CD)

ELECTRICAL SPECIFICATION

Accuracy is ± (% reading digits + number of digits) or otherwise specified, at 23 °C ± 5 °C & less than 75% R.H.

True RMS ACV & ACA clamp-on accuracies are specified from 0% to 100% of range or otherwise specified. Maximum Crest Factor are as specified below, and with frequency spectrums, besides fundamentals, fall within the meter specified AC bandwidth for non-sinusoidal waveforms. Fundamentals are specified at 50Hz and 60Hz.

AC Voltage

RANGE	Accuracy
50Hz / 60Hz	
600.0V	0.5% + 5d
45Hz ~ 500Hz	
600.0V	1.5% + 5d
500Hz ~ 3.1kHz	
600.0V	2.5% + 5d

CMRR : >80dB @ DC to 60Hz, Rs=1kΩ
 Input Impedance: 2MΩ, 30pF nominal
 Crest Factor: < 2.3 : 1 at full scale & < 4.6 : 1 at half scale
 ACV AutoVA™ Threshold: 30VAC (40Hz ~ 500Hz only) nominal

ACA Current (Clamp-on)

RANGE	Accuracy ¹⁾²⁾
50Hz / 60Hz	
40.00A, 400.0A, 1000A	1.0% + 5d
45Hz ~ 500Hz	
40.00A, 400.0A	2.0% + 5d
1000A	2.5% + 5d
500Hz ~ 3.1kHz	
40.00A, 400.0A	2.5% + 5d
1000A	3.0% + 5d

ACA AutoVA™ Threshold: 1A AC (40Hz ~ 500Hz only) nominal
 Crest Factor:

< 2.5 : 1 at full scale & < 5.0 : 1 at half scale for 40.00A & 400.0A ranges
 < 1.4 : 1 at full scale & < 2.8 : 1 at half scale for 1000A range

¹⁾Induced error from adjacent current-carrying conductor: < 0.06A/A

²⁾Specified accuracy is from 1% to 100% of range and for measurements made at the jaw center.

When the conductor is not positioned at the jaw center, position errors introduced are:

Add 1% to specified accuracy for measurements made WITHIN jaw marking lines (away from jaw opening)

Add 4% to specified accuracy for measurements made BEYOND jaw marking lines (toward jaws opening)

THD%-F

RANGE	Harmonic order	Accuracy ¹⁾
0.0% ~ 50.0%	Fundamental	1.5% + 6d
	2nd ~ 3rd	7% + 6d
	4th ~ 21st	2.5% + 6d ²⁾³⁾
	22nd ~ 51st	10% + 10d ⁴⁾
50.0% ~ 100%	2nd ~ 3rd	Unspecified
	4th ~ 21st	2.5% + 6d ⁵⁾⁶⁾
	22nd ~ 51st	10% + 10d ⁴⁾
100% ~ 450% ⁷⁾	2nd ~ 3rd	Unspecified
	4th ~ 21st	7% + 6d ²⁾⁴⁾
	22nd ~ 51st	Unspecified

THD%-F is defined as: (Total Harmonic RMS / Fundamental RMS) x 100%

¹⁾Accuracy specified @ fundamental ≥ 70V & Total RMS ≤ 600V for ACV THD%-F, fundamental ≥ 6A & Total RMS ≤ 1000A for ACA THD%-F, and Crest Factors @:

< 2.5 for 600V Range

< 2.5 for 40A Range

< 3.0 for 400A Range

< 1.6 for 1000A Range

²⁾Add 4d to specified accuracy @ 40A Range

³⁾Add 4.5% to specified accuracy @ 1000A range

⁴⁾Unspecified @ 1000A range

⁵⁾Add 1% + 4d to specified accuracy @ 40A Range

⁶⁾Add 4.5% to specified accuracy @ 400A ~ 750A; unspecified @ > 750A

⁷⁾~150% for 600V Range

PEAK-rms HOLD (ACA & ACV only)

Response: 65ms to >90%

Frequency

RANGE	Accuracy
5Hz ~ 500Hz	0.5%+4d

Sensitivity (Sine RMS)

40A range: > 4A

400A range: > 40A

1000A range: > 400A

600V range: > 30V

DC Voltage

RANGE	Accuracy
600.0V	0.5% + 5d
NMRR	>50dB @ 50/60Hz
CMRR	>120dB @ DC, 50/60Hz, Rs=1kΩ
Input Impedance:	2MΩ, 30pF nominal
DCV AutoVA™ Threshold:	2.4VDC nominal

Ohms

RANGE	Accuracy
999.9Ω	1.0% + 6d
Open Circuit Voltage :	0.4VDC typical

Audible Continuity Tester

Audible threshold: between 10Ω and 300Ω.

Response time: 250µs

Single-Phase & 3-Phase Balanced-Load Power

RANGE	Accuracy ¹⁾²⁾³⁾		
	F ~ 10th	11th ~ 45th	46th ~ 51st
0 ~ 600.0kVA			
@ PF = 0.99 ~ 0.1	2.0%+6d	3.5%+6d	5.5%+6d
RANGE	Accuracy ¹⁾²⁾⁴⁾		
0 ~ 600.0kW / kVAR	F ~ 10th	11th ~ 25th	26th ~ 45th
@ PF = 0.98 ~ 0.70	2.0%+6d	3.5%+6d	4.5%+6d
@ PF = 0.70 ~ 0.50	3.0%+6d		10%+6d
@ PF = 0.50 ~ 0.30		4.5%+6d	
@ PF = 0.30 ~ 0.20		10%+6d	15%+6d

¹⁾Specified accuracy is for ACA clamp measurement at the center of jaws. When the conductor is not positioned at the jaw center, position errors introduced are:

Add 1% to specified accuracy for ACA measurements made WITHIN jaw marking lines (away from jaw opening)

Accuracy is not specified for ACA measurement made BEYOND jaw marking lines (toward jaws opening)

²⁾Add 4d to specified accuracy for 3-Phase Balanced-Load Power measurements.

³⁾Add 1% to specified accuracy @ ACA fundamental < 6A or ACV fundamental < 90V. Accuracy is not specified @ ACA fundamental < 1A or ACV fundamental < 30V

⁴⁾Add 1% to specified accuracy @ ACA fundamental < 6A or ACV fundamental < 90V. Accuracy is not specified @ ACA fundamental < 2A or ACV fundamental < 50V

Total Power Factor (PF)

RANGE	Accuracy ¹⁾	
0.10 ~ 0.99	F ~ 21st	22nd ~ 51st
	3d	5d

¹⁾Specified accuracy @ ACA fundamental > 2A; ACV fundamental > 50V

A-lags-V Indication:

LCD annunciator A-lags-V turns on to indicate an inductive circuit, or Current A lags Voltage V (i.e., phase-shift angle θ is +).

A-lags-V Indication is specified at 50/60Hz fundamental without the presence of harmonics, and at ACV > 90V, ACA > 9A and PF < 0.95

kWhr (kilo-Watt-Hour Energy)

Time base accuracy: < 30ppm

Non-volatile memory: Separately stores one 3-Phase-Balanced-Load and one Single-Phase result

3-Phase Unbalanced-Load Power

This 3-Phase Unbalanced-Load Power measurement is achieved thru the calculation of discrete single-phase measurements that are taken one at a time manually. Since it is not real-time on all 3 phases simultaneously, it is intended only for stable power conditions without significant power fluctuations over the time of measurements. Result accuracy is hence the accumulated accuracy of the discrete single-phase measurements plus the associated fluctuations.

BRYMEN TECHNOLOGY CORPORATION

http://www.brymen.com

TEL: +886 2 2226 3396 (rep)

FAX: +886 2 2225 0025

Copyright © MMVI B.T.C. All rights reserved

Specifications subject to change without notice

Patents pending PRINTED IN TAIWAN



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [Brymen](#) manufacturer:

Other Similar products are found below :

[I800](#) [FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#)
[TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#)
[TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [I410](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [ACD-14-PRO](#)
[MA610](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#)