

BM22, BM25 & BM27 GENERAL SPECIFICATIONS

Display:

BM22: 3-3/4 digits 4000 counts
BM25 & BM27: 3-5/6 digits 6000 counts

Update Rate:

BM22: 3 per second nominal
BM25 & BM27: 5 per second nominal

Polarity:

Automatic

Operating Temperature:

0°C ~ 40°C
Maximum relative humidity 80% for temperature up to 31°C decreasing linearly to 50% relative humidity at 40°C

Altitude:

Operating below 2000m

Storage Temperature:

-20°C ~ 60°C, < 80% R.H. (with battery removed)

Temperature Coefficient:

Nominal 0.15 x (specified accuracy)/°C @ (0°C ~ 18°C or 28°C ~ 40°C), or otherwise specified

Sensing:

Average sensing on all models

Pollution Degree:

2

Safety: Meets IEC61010-1 (First Edition with Amendment 1 & 2), UL61010B-1 (First Edition), CAN/CSA-C22.2 No. 1010.1-92

Measurement Category:

BM22 & BM27: CAT II 600V, CAT III 300V
BM25: CAT II 450V, CAT III 300V

Transient Protection:

4kV lightning surge (1.2/50µs)

E.M.C.:

Meets EN61326 (1997, 1998/A1), EN61000-4-2 (1995), & EN61000-4-3 (1996)

In an RF Field of 3V/m:

Capacitance function is not specified

Other function ranges:

Total accuracy = Specified accuracy + 45d
Performance above 3V/m is not specified

Overload Protection:

600VDC & VAC rms for BM22 & BM27
450VDC & VAC rms for BM25

Low Battery:

Below approx. 2.4V

Power Supply: 3V standard button battery x 1 (IEC-CR2032; ANSI-NEDA-5004LC)

Power Consumption (typical):

BM22 & BM25: 2mA
BM27: 6mA for Voltage functions on Auto-V Ω position; 2mA for other functions

APO Consumption:

1µA typical

APO Timing:

BM22: Idle for 30 minutes

BM25 & BM27: Idle for 3 minutes

Dimension:

L113mm x W53mm x H10.2mm

Weight:

approx. 78 gm

Special Features:

BM22: Data Hold; 30ms MAX Hold
BM25 & BM27: AutoCheck™ (Automatic V & Ω Selection); EF-Detection

Accessories:

battery installed, user's manual

Optional Accessories:

protective holster, soft carrying pouch

BM22, BM25 & BM27 ELECTRICAL SPECIFICATIONS

Accuracy is \pm (% of reading digits + number of digits) or otherwise specified, at 23°C \pm 5°C & less than 75% R.H.

DC Voltage (BM22)

RANGE	Accuracy
400.0mV	1.0%+2d
4.000V, 40.00V, 400.0V	2.0%+2d
600V	2.5%+4d

NMR: > 50dB @ 50Hz/60Hz
CMRR: > 120dB @ DC, 50Hz/60Hz; Rs=1k Ω
Input Impedance: 10 M Ω , 30pF nominal;
(1000M Ω for 400.0mV range)

DC Voltage (BM25 & BM27)

RANGE	Accuracy
6.000V	0.5%+3d
60.00V	1.0%+5d
450.0V ¹⁾	1.2%+5d
600.0V ²⁾	2.0%+5d
600.0V ³⁾	1.5%+5d

NMR: > 30dB @ 50Hz/60Hz
CMRR: > 100dB @ DC, 50Hz/60Hz; Rs=1k Ω

BM25 Input Impedance:

AutoCheck™ Lo-Z DCV:
160k Ω , 160pF nominal

BM27 Input Impedance:

AutoCheck™ Lo-Z DCV:
833k Ω (4.2k Ω when displaying Auto),
90pF nominal

Hi-Z DCV:

5M Ω , 90pF nominal
DCV AutoCheck™ Threshold:
> +1.2VDC or < -0.6VDC nominal

¹⁾BM25 AutoCheck™ DCV only

²⁾BM27 AutoCheck™ DCV only

³⁾BM27 Hi-Z DCV only

Ohms (BM22)

RANGE	Accuracy
400.0 Ω	1.5%+6d
4.000k Ω , 40.00k Ω , 400.0k Ω	1.0%+4d
4.000M Ω	1.5%+4d
40.00M Ω	2.5%+4d

Open Circuit Voltage: 0.4VDC typical

Ohms (BM25 & BM27)

RANGE ¹⁾	Accuracy
600.0 Ω	2.0%+6d ²⁾
6.000k Ω	1.2%+6d ²⁾
60.00k Ω , 600.0k Ω	1.0%+4d
6.000M Ω	2.0%+4d

Open Circuit Voltage: 0.4VDC typical

¹⁾AutoCheck™ is for 6.000k Ω ~ 6.000M Ω ranges;
600.0 Ω is an independent range for BM27 only

²⁾Specified accuracy plus 40d while reading is below 20% of range

Diode Tester (BM22 & BM27 only)

Test Current (Typical)	Open Circuit Voltage
0.25mA for BM22	< 1.6VDC
0.48mA for BM27	

AC Voltage (BM22)

RANGE	Accuracy
50Hz -- 60Hz	
4.000V, 40.00V, 400.0V	2.0%+5d
60Hz -- 500Hz	
4.000V, 40.00V, 400.0V	3.0%+5d
50Hz -- 500Hz	
600V	3.5%+5d

Input Impedance: 10 M Ω , 30pF nominal
CMRR: > 60dB @ DC to 60Hz, Rs=1k Ω

AC Voltage (BM25 & BM27)

RANGE	Accuracy
50Hz -- 60Hz	
6.000V, 60.00V, 450.0V ¹⁾ , 600.0V ²⁾	1.5%+5d

CMRR: > 60dB @ DC to 60Hz, Rs=1k Ω

BM25 Input Impedance:

AutoCheck™ Lo-Z ACV:
160k Ω , 160pF nominal

BM27 Input Impedance:

AutoCheck™ Lo-Z ACV:
833k Ω (4.2k Ω when displaying Auto),
90pF nominal

Hi-Z ACV:

5M Ω , 90pF nominal
ACV AutoCheck™ Threshold:
> 1.5VAC (50/60Hz) nominal

¹⁾Range for BM25 only

²⁾Range for BM27 only

Capacitance (BM22)

RANGE ¹⁾	Accuracy ²⁾
500.0nF, 5.000µF, 50.00µF, 500.0µF, 3000µF	3.5%+6d ³⁾

¹⁾Additional 50.00nF range accuracy is not specified.

²⁾Accuracies with film capacitor or better.

³⁾Specified with battery voltage above 2.8V (half full battery). Accuracy decreases gradually to 12% at low battery warning voltage of approx 2.4V

Capacitance (BM25 & BM27)

RANGE ¹⁾	Accuracy ²⁾
100.0nF, 1000nF, 10.00µF, 100.0µF, 2000µF ³⁾	3.5%+6d ⁴⁾

¹⁾Accuracy below 50nF is not specified

²⁾Accuracies with film capacitor or better.

³⁾BM27 only

⁴⁾Specified with battery voltage above 2.8V (half full battery). Accuracy decreases gradually to 12% at low battery warning voltage of approx 2.4V

DC μ A Current (BM27 only)

RANGE	Accuracy	Burden Voltage
400.0µA	1.5%+3d	3mV/µA
2000µA	1.2%+3d	3mV/µA

AC μ A Current (BM27 only)

RANGE	Accuracy	Burden Voltage
50Hz -- 60Hz		
400.0µA	2.0%+3d	3mV/µA
2000µA	1.5%+3d	3mV/µA

Audible Continuity Tester

Open Circuit Voltage: 0.4VDC typical

BM22:

Audible Threshold: between 10 Ω and 120 Ω

BM25 & BM27:

Audible Threshold: between 50 Ω and 150 Ω

Hz Frequency (BM22)

RANGE	Accuracy
5.000Hz -- 1.000MHz	0.5%+4d

Operating Input Voltage: < 20VAC rms

Input Signal: Sine Wave, or square wave with duty cycle > 40% & < 70%

Sensitivity:

5Hz -- 100kHz : > 1.3Vp

100kHz -- 500kHz : > 2.2Vp

500kHz -- 1MHz : > 4.2Vp

Hz Frequency (BM25 & BM27¹⁾)

RANGE	Accuracy
10.00Hz -- 30.00kHz	0.5%+4d

Sensitivity (Sine RMS):

Hz (Auto-V Ω position): > 3V

¹⁾6.000VAC range (V position): > 4V

¹⁾60.00VAC range (V position): > 30V

¹⁾600.0VAC range (V position): > 60V

Electric Field EF-Detection (BM25 & BM27)

Typical Voltage	Bar Graph Indication
15V to 55V	-
30V to 85V	--
55V to 145V	---
85V to 190V	----
above 120V	-----

Indication: Bar graph segments & audible beeper tone proportional to the field strength

Detection Frequency: 50/60Hz

Detection Antenna: Top left corner of the meter

(Measurement can also be made through single test lead (+) for live line detection)



BRYMEN TECHNOLOGY CORPORATION

http://www.brymen.com

TEL: +886 2 2226 3396 (rep)

FAX: +886 2 2225 0025

Copyright © MMIII B.T.C. All rights reserved
Specifications subject to change without notice
Patented & Patents pending. Printed in Taiwan.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Digital Multimeters](#) category:

Click to view products by [Brymen](#) manufacturer:

Other Similar products are found below :

[8009](#) [6111-517](#) [FS881](#) [40705X](#) [USB390A](#) [780417A](#) [GPT-9904](#) [382099](#) [589250](#) [780418](#) [C.A 6131](#) [C.A 6133](#) [30XR](#) [34XR](#) [35XP](#) [TESTO](#)
[745](#) [0590 7450](#) [TESTO 760-3](#) [0590 7603](#) [440012](#) [AX-155](#) [AX-174](#) [AX-178](#) [AX-18B](#) [AX-190A](#) [AX-503](#) [AX-507B](#) [AX-572](#) [AX-594](#) [AX-](#)
[LCR41A](#) [AX-MS8221A](#) [AX-MS8250](#) [AX-PDM01](#) [AX-T520](#) [AX-T901](#) [AX-T903](#) [BAT-250-EUR](#) [BM233](#) [BM805S](#) [BM807S](#) [BM817S](#)
[BM827S](#) [BM829S](#) [BM857S](#) [BM859S](#) [BM867S](#) [BM905S](#) [BM906S](#) [33XR](#) [UNITEST TESTFIX 9023](#) [37XR](#) [UT56](#)