

True RMS AC Voltage/Current Datalogger

Datalog up to 16,350 readings

With user programmable sample rate from 1 second to 24 hours

Features:

- Measure True RMS AC Voltage (600V) or Current (200A)
- Readings can be downloaded to your PC via the USB interface and analyzed using the included software or exported to a spreadsheet
- LCD indicates time/date, current readings, and Min/Max
- Normal, Peak and Capture (user-specified trigger level) recording modes
- Auto Power off and battery check
- Complete with current clamp, test leads, USB cable, Windows[®] compatible software, universal AC Adaptor, and four AAA batteries



Datalog up to 16,350 True RMS Current or Voltage readings. Captured readings can be downloaded to your PC, using the included USB cable and software, for further analysis. Readings can also be exported into a spreadsheet for creating charts and graphs.

| Function | Range | Resolution | Basic Accuracy |
|---------------|------------------------------------|------------|------------------|
| AC Current | 10 to 200A | 0.1A | ±(2% rdg ± 1A) |
| AC Voltage | 10 to 600V | 0.1V | ±(1.5% rdg ± 1V) |
| Memory | 16,350 points | | |
| Sampling Rate | 1 second to 24 hours | | |
| PC Interface | USB includes software | | |
| Power | 4 x AAA batteries | | |
| Dimensions | 4.5 x 2.5 x 1.3" (114 x 63 x 34mm) | | |
| Weight | 8.7oz (248g) | | |

Ordering Information:

DL150True RMS AC Voltage/Current Datalogger



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Digital Multimeters](#) category:

Click to view products by [Extech](#) manufacturer:

Other Similar products are found below :

[8009](#) [6111-517](#) [FS881](#) [40705X](#) [USB390A](#) [780417A](#) [GPT-9904](#) [382099](#) [589250](#) [780418](#) [C.A 6131](#) [C.A 6133](#) [30XR](#) [34XR](#) [35XP](#) [TESTO](#)
[745](#) [0590 7450](#) [TESTO 760-3](#) [0590 7603](#) [440012](#) [AX-155](#) [AX-174](#) [AX-178](#) [AX-18B](#) [AX-190A](#) [AX-503](#) [AX-507B](#) [AX-572](#) [AX-594](#) [AX-](#)
[LCR41A](#) [AX-MS8221A](#) [AX-MS8250](#) [AX-PDM01](#) [AX-T520](#) [AX-T901](#) [AX-T903](#) [BAT-250-EUR](#) [BM233](#) [BM805S](#) [BM807S](#) [BM817S](#)
[BM827S](#) [BM829S](#) [BM857S](#) [BM859S](#) [BM867S](#) [BM905S](#) [33XR](#) [UNITEST TESTFIX 9023](#) [37XR](#) [UT56](#) [UT58C](#)