

ECO (10 A)

Solar Charge Controller



- Electronically regulated charging mode: boost, main and float charge
- Deep discharge protection
- PWM series regulation (PV panel is not short-circuited)
- Integrated temperature compensation
- Fully electronically protected against: panel surge voltage, wrong polarity (panel or battery), overload and short circuit at load
- Three LED indications: Charge Status, SOC, LVD, Overload/Short Circuit
- IP68 protection

Phoco's new solar charge controller, ECO, is especially designed for small solar systems requiring low-battery disconnect. The ECO is fully electronically protected and offers a LED display showing charge and load status.

Rural electrification systems are the typical applications for this product. It is a perfect solution for cost-sensitive systems.

Type	ECO 10
System voltage	12 V
Max. charge/load current	10 A
Float charge	13.8 V (25 °C)
Main charge	14.4 V (25 °C), 0.5 h (daily)
Boost charge	14.4 V (25 °C), 2 h Activation: battery voltage < 12.3 V
Deep discharge protection, Cut-off voltage	11.0 V
Overvoltage protection	15.5 V
Undervoltage protection	10.5 V
Max. PV panel voltage	30 V
Temperature compensation	-4.2 mV/cell*K
Idle self-consumption	4 mA
Grounding	Positive grounding
Ambient operating temperature	-40 to +60 °C
Max. altitude	4,000 m above sea level
Battery type	Lead acid (GEL, AGM, flooded)
Wire cross section	2.5 mm ²
Weight	110 g
Dimensions (W x H x D)	87 x 51 x 16 mm
Type of protection	IP68

Datasheet_ECO_1/1_e_2014-04-07_Subject to change without notice

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Modules Accessories](#) category:

Click to view products by [Phocos](#) manufacturer:

Other Similar products are found below :

[7010-0001](#) [F1UL16RISER2](#) [PEX-CABLEAD-KIT-8732](#) [AX98219](#) [iRIS-1010-R10](#) [A1UL8RISER](#) [F1UJPMICRISER](#) [FHW1U16RISER](#) [20-101-0440](#) [MBCDROM](#) [AX61221TM](#) [VM-105](#) [1000-PM](#) [76000958](#) [XPC100A002-01-B](#) [690-1002](#) [96HD500G-ST-WD7KE](#) [AMO-R022E](#) [RK-210E-B](#) [cPCIS-6400UA/AC](#) [E226171106](#) [AX60501WB](#) [88606200030E](#) [96RACK-3-SS-CR-B1](#) [UTC-300P-M10E](#) [UNO-2000G-VMKAE](#) [SI-HDMI-EDID-EM](#) [96HD3T-ST-SG7K](#) [AMO-I013E](#) [S10A-93-S10A6-001](#) [PWS-870-UCOVER00E](#) [PWS-770-VMOUNT00E](#) [PWS-870-CHDC00E](#) [MIT-W101-ACCDSW01E](#) [MIC-75M40-00A1E](#) [MIC-75M13-00A1E](#) [FPM-1000T-SMKE](#) [ASMB-FF404-04A1E](#) [AMK-V008E](#) [AMK-V005E](#) [AMK-R004E](#) [9896025601E](#) [96HD1TB-ST-WD7KE1](#) [96FMCF-ST2ADAPTER1](#) [9680015843](#) [1960030475S200](#) [1931031500](#) [AHWKPTP12GBGB](#) [850-13106](#) [P4304XXMUXX](#)