

# T5/7-600 Electrical Testers 1AC II VoltAlert

FLUKE®



Fluke T5-1000

Fluke 7-600



Fluke 1AC II

## The fast and easy solution to basic electrical testing

### Fluke T5-600 and T5-1000 Voltage, Continuity and Current Testers

The Fluke T5 testers let you check voltage, continuity and current with one compact tool. Select volts, ohms or current and the instrument does the rest. Model T5-600 measures 600 volts AC/DC, model T5-1000 is designed for 1000 volts. OpenJaw™ current technology lets you check current up to 100 A, without breaking the circuit. The optional H5 holster keeps the test probes and leads ready to test and lets you clip the T5 onto your belt.

### 7-600 Electrical Tester

The easiest way to check AC/DC continuity and resistance is with the Fluke 7-600. The Fluke 7-600 can measure up to 600V AC or DC. Just switch the unit on and it will automatically switch to the correct setting. An input impedance of 2KΩ distinguishes real voltage from voltage caused by leakage or capacitive coupling.

## Features and Specifications

	T5-600	T5-1000	7-600
Display Count	1000	1000	4000
Automatic Selection	●	●	●
Continuity and Beeper	●	●	●
Sleep Mode	●	●	●
AC Voltage	600V	1000V	600V
DC Voltage	600V	1000V	600V
AC Current	100A	100A	
Resistance	1000Ω	1000Ω	400Ω
Safety range	600V CAT III	1000V CAT III	600V CAT III

### T5-600/T5-1000

**Battery life:** 400 hours  
**Size (HxWxD):** 203 mm x 51 mm x 30.5 mm  
**Weight:** 0.38 kg  
**Two year warranty**

### 7-600

**Battery life:** Alkaline, 650 hours continuous, sleep mode  
**Size (HxWxD):** 142.3 mm x 70.5 mm x 34.6 mm  
**Weight:** 0.286 kg  
**Two year warranty**

## Fluke 1AC II VoltAlert™

The Fluke VoltAlert AC voltage detector is very easy to use – just touch the tip to a terminal strip, outlet or cord. When the tip glows red and the unit beeps, you know there is voltage on the line.

- It continually tests its battery and its circuit integrity with a periodic double flash visual indication.
- Highest safety rating: CAT IV 1000 V
- Detects voltage without metallic contact

**Operating range:** 200 – 1000 V AC  
**Batteries:** Two AAA Alkaline  
**Size (H):** 148 mm  
**Two Year Warranty**

**Fluke 1AC II VoltAlert™ 5-pack**  
• Buy 4 get 1 FREE



### Included Accessories

T5-600 and T5-1000:

TP4 4 mm detachable probes (detachable GS38 probes for the UK) and instruction sheet

Fluke 7-600:

TL75 Hard Point Test Leads, a 9 volt battery (installed) and owner's manual.

### Ordering Information

Fluke T5-600	Electrical Tester
Fluke T5-1000	Electrical Tester
Fluke 7-600	Electrical Tester
Fluke 1AC II	VoltAlert
Fluke 1AC II 5PK	VoltAlert (5-pack)

## Recommended Accessories T5



H5



ACC-T5-Kit



AC285



TP38



L210

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Digital Multimeters](#) category:*

*Click to view products by [Fluke](#) manufacturer:*

Other Similar products are found below :

[8009](#) [6111-517](#) [FS881](#) [40705X](#) [USB390A](#) [780417A](#) [GPT-9904](#) [382099](#) [589250](#) [780418](#) [C.A 6131](#) [C.A 6133](#) [30XR](#) [34XR](#) [35XP](#) [TESTO](#)  
[745](#) [0590 7450](#) [TESTO 760-3](#) [0590 7603](#) [440012](#) [AX-155](#) [AX-174](#) [AX-178](#) [AX-18B](#) [AX-190A](#) [AX-503](#) [AX-507B](#) [AX-572](#) [AX-594](#) [AX-](#)  
[LCR41A](#) [AX-MS8221A](#) [AX-MS8250](#) [AX-PDM01](#) [AX-T520](#) [AX-T901](#) [AX-T903](#) [BAT-250-EUR](#) [BM233](#) [BM805S](#) [BM807S](#) [BM817S](#)  
[BM827S](#) [BM829S](#) [BM857S](#) [BM859S](#) [BM867S](#) [BM905S](#) [33XR](#) [UNITEST TESTFIX 9023](#) [37XR](#) [UT56](#) [UT58C](#)