

Schneider Electric USA

1415 South Roselle Road

Palatine, IL 60067

Customer Care Center: 1-888-778-2733

Web: www.schneider-electric.us

Item # 9080LBA161101, Power Distribution Block LBA**Power Distribution Block LBA**

Power Distribution Block

**SPECIFICATIONS**

Ampere Rating	115A/90A (Cu/Al)
UL File	E60616 XCFR2
CSA File	70361 6228-01
RoHS	Yes
CE Marked	Yes
Flammability Rating	UL94V-0
Service Class	C
For Use With	Copper or Aluminum Wire
Maximum Voltage Rating	600VAC
Number of Poles	1
Terminal Type	Lugs
Wire Range - Main	(1)#14 to #2 AWG
Wire Range - Branch	(1)#14 to #2 AWG
Cover	N/A

Short Circuit Current Ratings with Circuit Breakers	Up to 65 kA
Short Circuit Current Ratings with Fuses	Up to 100kA
35mm Track Adapter	N/A

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [schneider manufacturer](#):

Other Similar products are found below :

[LU9M1](#) [7D](#) [7S](#) [7XA1](#) [FNQR2](#) [8501RS44V24](#) [8501RSD14P14V51](#) [8501XO20V03Y414](#) [9001KXRK](#) [9001SKR9P35RH25](#) [9001SKT35L31](#)
[9003K2C003GA](#) [9007AA1](#) [9007BA1](#) [9007C54D](#) [9007C62A2](#) [9007CA11](#) [9007FA3](#) [9007HA4](#) [9007HA6](#) [9007KA1](#) [9007KB11](#)
[9007MS01S0206](#) [9007MS02S0300](#) [9012GAR4](#) [9012GAW2](#) [9012GBW1](#) [9012GDW5E3](#) [9012GFW1](#) [9012GNG1](#) [9012GNG3](#) [9012GNG6](#)
[9013FHG39J69](#) [9013GHG2J30](#) [9050JCK2F30V14](#) [GV2ME32](#) [GVAN20](#) [GZ1E02](#) [A9F04102](#) [A9F04106](#) [A9F05110](#) [A9F07102](#)
[ABL8RPS24030](#) [DL1BLB](#) [ATS01N206QN](#) [RSL1PRJU](#) [9001KA35](#) [9001KA3G](#) [9001KA4](#) [9001KR1GH5](#)