

## Between Series Adaptor 33\_716-4310-50-1/133\_W

### Description

PIM Adaptor plug/jack  
7/16 plug (male) / 4.3-10 jack (female)

Interface standards  
Series 7/16 - IEC 61169-4\_CECC 22190\_DIN 47223\_VG 95250  
Series 4.3-10 - IEC 61169-54

### Benefits

Low passive intermodulation (PIM) adaptor  
For Test & Measurement applications



### Technical Data

#### Electrical Data

Impedance	50 Ω	
Interface frequency max.	7.5 GHz	
Frequency range	0 to 4 GHz	4 to 6 GHz
Return loss	27 dB	25 dB

PIM, 3rd order intermodulation distortion (IMD) max. Static -166 dBc at 2x 43 dBm / 20 W carrier

#### Mechanical Data

Number of matings	500
Weight	0.115 kg

#### Environmental Data

Operating temperature	-55 °C to 90 °C
2011/65/EU (RoHS)	compliant

#### Material Data

Interface - 7/16 plug (male)

Piece Parts	Material	Surface Plating
Centre contact	Copper Beryllium Alloy	SUCOPRO Plating
Outer contact	Brass	SUCOPLATE (R) Plating
Body	Brass	SUCOPLATE (R) Plating
Insulator	PFA / PTFE	
Coupling nut	Brass	

Interface - 4.3-10 jack (female)

Piece Parts	Material	Surface Plating
Centre contact	Copper Beryllium Alloy	SUCOPRO Plating
Outer contact	Bronze / Brass	SUCOPLATE (R) Plating
Body	Brass	SUCOPLATE (R) Plating
Insulator	PFA / PTFE	

### Related Documents

Outline drawing	DOU-00256775
-----------------	--------------

### Ordering Information

Single package	33_716-4310-50-1/133_WE
----------------	-------------------------

## Between Series Adaptor 33\_716-4310-50-1/133\_W

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [huber & suhner](#) manufacturer:*

Other Similar products are found below :

[31 MMBX-SMA-50-1/111\\_NE](#) [74Z-0-23-17](#) [32 MMBX-50-0-6 / 111 NE](#) [TL8A-11SMA-11SMA-03000-51](#) [TL8A-11SMA-11SMA-01500-51](#)  
[23\\_SMA-50-0-1/111\\_NE](#) [TL-8A-11N-11SMA-01500-51](#) [7404.17.0003](#) [24\\_BNT-50-2-1/103\\_NE](#) [5906.17.0005](#) [Microbend R-13](#) [16\\_SMA-](#)  
[50-2-55/199\\_NE](#) [16\\_SMA-50-2-43/133\\_NE](#) [11\\_716-50-7-31/033\\_-Y](#) [Minibend L-13](#) [74\\_Z-0-0-58](#) [6550.17.AA](#) [Microbend R-4.5](#) [74\\_Z-0-0-](#)  
[53](#) [6603\\_SMA-50-2/199\\_NE](#) [85\\_SMC-50-0-1/133\\_NE](#) [MF53/1x8A\\_21MXP/11SK/305](#) [1324.17.0114](#) [75\\_Z-0-0-51](#) [31\\_PC24-SK-50-](#)  
[1/199\\_NE](#) [65\\_BNC-50-0-2/133\\_NE](#) [76\\_Z-0-10-14](#) [65\\_MMCX-50-0-31/111\\_OE](#) [11\\_N-50-4-19/12-\\_NE](#) [80346275](#) [23\\_SHV-50-0-2/133\\_NE](#)  
[33\\_SMA-QMA-50-1/133\\_NE](#) [11\\_C-50-7-6/133\\_NE](#) [6806.19.A](#) [33\\_716-N-50-51/-33\\_NE](#) [5930\\_N-50-050/19-\\_NE](#) [16\\_BNC-50-7-6/133\\_NE](#)  
[11\\_SMB-50-2-41/111\\_NE](#) [Mini141 K-8](#) [33\\_BNC-N-50-1/133\\_NE](#) [6701.01.B](#) [25\\_N-50-7-8/133\\_NE](#) [22\\_BNC-50-0-5/133\\_NE](#) [6500\\_N-50-](#)  
[1/199\\_NE](#) [3401.17.0033](#) [6601\\_SMA-50-1/199\\_NE](#) [74\\_Z-0-0-56](#) [3401.00.0022](#) [MF53/1x8A\\_21MXP/21SK\\_erg/305](#) [32\\_N-SMA-50-51/1--](#)  
[\\_UE](#)