

**TBL70**

4W- 70V, 5 Taps at -3dB Levels



**GENERAL DESCRIPTION**

The **TBL70** is a 4W-70V transformer with 5 taps at -3dB levels and 7" color-coded, pre-cut leads.

**INTENDED USE - Indoor Environment**

<b>Primary Use</b>	Signal tones, voice and music
<b>Installation</b>	Desired tap / common primary leads connected to the output of a constant voltage amplifier. Secondary / common attached to a nominal 8 Ohm loudspeaker.

**AUDIO SPECIFICATIONS**




<b>Primary Volts</b>	70.7V
<b>Power Rating</b>	10W
<b>Primary Taps (-3 dB Steps)</b>	5
<b>Secondary Load</b>	8-Ohms, Nominal
<b>Frequency Response</b>	100 Hz- 15 kHz
<b>Insertion Loss</b>	1.0 dB

**MECHANICAL SPECIFICATIONS**

<b>Primary Connection</b>	7" Color-Coded, Pre-Cut
<b>Secondary Connection</b>	6" Color-Coded, Pre-Cut
<b>Shipping Weight</b>	10 Oz

**RECOMMENDED QUAM COMPONENTS**

<b>Loudspeakers</b>	Any 8-Ohm device (8C10DVPAX requires two transformers)
---------------------	---



## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [quam nichols](#) manufacturer:*

Other Similar products are found below :

[30C25Z450T](#) [8C5Z45](#) [8C10FECOB](#) [ERD-8](#) [4C3PA](#)