



COMPLETE : Three outputs available simultaneously.

PRATICAL : Digital voltage display.

USEFUL : Setting memory.

COMPATIBLE : RS232, USB* and LABVIEW interfaces.

PROTECTED : Short circuit protection.





*OPTION : USBRS232

48 WATTS

RS232 + LABVIEW + USB*

0 to ± 15V	1A
or 0 to 30V	1A
and 2 to 5,5V	3A
and -15 to +15V	0,2A



Specifications

Voltage

- Floating outputs on 4 mm safety sockets.
- Three outputs available simultaneously :
 - Power supply A : adjustable from 0 to ±15 Volts balanced. or 0 to 30V with the -15V terminal as reference.
 - Power supply B: adjustable from + 2 to + 5,5 Volts.
 - Power supply C: adjustable from - 15 to + 15Volts.
- Voltage adjustment : push-button selection of output A, B or C. Voltage incremented and decremented by four push-buttons : -1 V + 1 V - 0,1 V + 0,1V
Automatic storage of the three voltage settings.
- Regulation : < 20mV for a load change from 0 to 100%.
< 10mV for a 10% line change.
- Ripple : < 3 mV peak to peak or 1 mV rms.
- Indicators : Three red LEDs showing the selected output for display and adjustment.
- Display : 14 mm 3 digit LED digital voltmeter for the three outputs.
- Resolution : 100 mV.

Currents

- Max I : 1A on output A.
3A to 5,5 Volts and 1,5A to 2 Volts on output B.
0,2A on output C.
- Display : Current limiting on one output causes the display to blink ; it shows : "Ic.A", "Ic.b", "Ic.C" or "+Ic", depending on the overloaded output(s).

Protection

- Short circuit protection, by current limit.
- Transformer primary overcurrent protection, by fuse.
- Chassis ground output on 4 mm inverted safety socket.

Interface

- RS-232 link, 9-way male SUB-D plug.
- USB option: Kit includes an adaptor null modem and RS232 cable

Software

- LG991S for Windows95* or +
 - LG991S LV and base VI under LabVIEW**
- Softwares are available for download on website www.elc.fr
[*is a registered trademark of Microsoft Co.]
[** [*is a registered trademark of National Instruments.]

Other specifications

- Safety : Class I, enhanced safety between mains input and outputs. Complies with EN 61010-1, overvoltage category II, pollution degree 2.
- EMC : Complies with EN 61326-1, performance criteria B, and EN 55011, ISM Group I, Class B.
- Input voltage : 230V ±10%, 50 / 60 Hz.
- Mains input : EEC socket with 2 poles + earth cable
- Power consumption : 100 VA max.
- Dielectric strength : 2300V from input to output, 1350V from input to chassis.
- Presentation : screen-printed polycarbonate front panel, metal case, epoxy finish.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Bench Top Power Supplies](#) category:

Click to view products by [ELC](#) manufacturer:

Other Similar products are found below :

[NL200](#) [PR20](#) [ZUPNC403](#) [Z60-7-L-U](#) [ZUPNC402](#) [GDM-8342](#) [GPIB](#) [PSW 250-4.5](#) [CPX200DP](#) [AX-8450A](#) [TPM-3003](#) [HMP2020](#)
[HMP2030](#) [HMP4040](#) [1320](#) [1350](#) [UT804](#) [1405](#) [1410](#) [1513](#) [1514](#) [1513](#) [1550](#) [1651A](#) [1665](#) [1666](#) [1667](#) [SDP-2405-000G](#) [1673](#) [1693](#) [1694](#)
[MX100TP](#) [1737](#) [1739](#) [1762](#) [1788](#) [TPM-3005](#) [1900](#) [1902B](#) [9174B](#) [GDM-8245](#) [GDM-8255A](#) [GDM-8341](#) [PSW 160-7.2](#) [PSW 30-36](#) [PSW](#)
[80-13.5](#) [Z10-20-LAN-U](#) [PSW 30-72](#) [QL355P SII](#) [Z36-6-LAN-U](#) [HCS-3400-USB](#)