

PRIMETEST 50

BASIC, HAND-HELD SAFETY CHECKER

For those looking for an easy to use, portable appliance checker look no further. The Primetest 50 offers exceptional lightness and portability as well as a simplified range of tests. Simply choose the test you require; either earthed appliance, double insulated appliance, or mains cord testing. The simple display shows whether it's a Pass or Fail, it could be easier. If toughness is an issue, don't worry, the rugged outer casing will stand up to anything a normal working environment has to offer. A great choice for those needing a reliable, easy to use, portable safety tester.

Key Features

■ Easy to use

What can be easier than simple push-button operation? Connect your test appliance, pick your test mode, push the button. The display tells whether it has passed or failed. Done.

■ Hand-held – Highly Portable

The Primetest 50 is tiny compared to the competition. Measuring only 26 x 10cm, it fits easily in the palm of your hand.

■ Battery Powered

This means it's lighter, easier to use and more portable, as you no longer need a power supply nearby. Freedom to move.

■ PATGuard Compatible

To help make your life as a tester even easier, the Primetest 50 can be used with our industry acclaimed PATGuard Workabout software for mobile data input. Now you have the best of both worlds – easy testing and easy information management.

Primetest 50 Users

- Maintenance Staff
- Schools & Colleges
- Care Homes
- Leisure Industry



Web: www.seaward.co.uk **Email:** sales@seaward.co.uk

Seaward

Bracken Hill,
South West Industrial Estate,
Peterlee, SR8 2SW

Tel: +44 (0) 191 5863511

Fax: +44 (0) 191 5860227

PRIMETEST 50 SPECIFICATIONS

PAT TESTS

Earth Continuity

Test Current	+/- 200mA DC
PASS/FAIL Threshold	0.2ohms

Insulation Resistance

Test Voltages	500V DC
PASS/FAIL Threshold	2Mohms

IEC Lead Test

Tests Performed	Earth Continuity Insulation Resistance Live, Neutral Continuity and Polarity
-----------------	--

CIRCUIT TESTS

Power Socket Test

Input Voltage range	230V +10%, -15% AC
Indicators	Phase to Earth Voltage Phase to Neutral Voltage Neutral to Earth

ADDITIONAL INFORMATION

Weight / Dimensions

Weight & Dimensions	800g/ 26cm (l) x 10cm (w) x 5.5cm (d)
---------------------	---------------------------------------

Power Source

6 x AA Batteries

PART NO: (347A910)

Basic PATSolutions Package

PATSolutions is a total solutions philosophy that encompasses all aspects of electrical safety testing, from the testers themselves to information management software, through to label printers and much more.

Each tester and its accessories can be purchased separately or as an optional PATSolutions package which includes everything needed to run an efficient and effective PAT testing business.

Basic PATSolutions Package includes:

- Primetest 50 Tester
- Calibration Certificate
- PATGuard Lite
- PATGuard Support Contractor
- PATGuard Workabout
- Guide to Portable Appliance Testing
- Calibration Certificate

Optional Extras

Hardware:

Pass Label (91B038)
Log Cards (91B037)
Appliance Number Labels (194A308)
Custom Appliance Number Labels (194A323)
Battery Charger (339A950)
PATCheckbox (227A910)

Software:  (352A930)

 (336A910)

Training: **PATGUARD SOFTWARE TRAINING COURSE**

Services: **SERVICE & CALIBRATION JUMP START**



WORLD LEADERS IN SAFETY TEST AND MEASUREMENT

Seaward test and measurement companies include:

CLARE
INDUSTRIAL SAFETY INSTRUMENTS

RIGEL
MEDICAL

CROPICO
PRECISION INSTRUMENTS

SEAWARD
PORTABLE ELECTRICAL SAFETY INSTRUMENTS

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [seaward manufacturer](#):

Other Similar products are found below :

[SE809-LF-3.08V](#) [SE78L05-LF](#) [SE78M05](#) [SE9175-HF](#) [SE8633K2-HF](#) [SE8536X2-HF](#) [SE8250X2](#) [SE1122-LF-1.2V](#) [SE8117TA-HF-ADJ](#)
[SE8117T18HF](#) [SE5220-LF-ADJ](#) [SE8801EBK](#) [SE8542K2-HF](#) [SE8233K2](#) [SE8633X2-HF](#) [SE8250K2](#) [SE8117T15-HF-1.5V](#) [SE9019](#)
[SE8801EDK](#) [SE809-HF-2.93V](#) [SE3837B](#) [SE9018-HF](#) [SE8117T50HF](#) [SE8533K1-HF](#) [SE9029X](#) [SE8530-HF](#) [SE3578](#) [SE809-HF-3.08V](#)
[SE8650X2-HF](#) [SE3608](#) [SE2515-HF](#) [SE5218DLG-LF-1.8V](#) [SE601-HF](#) [SE8117T33HF](#) [SE8650K2-HF](#) [SE100-HF](#) [SE8533X2-HF](#) [SE9017-](#)
[HF](#) [SE431D-LF](#) [SE5218ALG-LF](#) [SE8536K2-HF](#) [SE2513-HF](#) [SE9016-HF](#) [SE432L-HF](#) [SE8550K2-HF](#) [SE8550X2-HF](#) [SE8533K2-HF](#)