

400-600A Digital Clamp Meter **TENMA™**

Description



This model is a 4,000 count AC/DC digital clamp meter with stable performance, high degree of safety and reliability. It is designed with large-scale integrated circuits and dual integral A/D converter as its core. Overload protection for all ranges and novel structure which make it a superb tool for electricians. The meter can measure AC/DC voltage, AC/DC current, resistance, diode, continuity, capacitance, frequency and temperature, etc.

Features

- Display Count : 3,999
- Auto Range
- Jaw Capacity : 28mm
- Diode Test
- Auto Power Off
- Continuity Buzzer
- Low Battery Indication
- Data Hold
- MAX Mode
- Setup
- Input Impedance for DCV : Around 10MΩ

Specifications

	Range	Best Accuracy
AC Current (A)	40A/600A	±(2.5%+5)
DC Current (A)	40A/600A	±(2%+5)
AC Voltage (V)	4V/40V/400V/600V	±(1%+5)
DC Voltage (V)	400mV/4V/40V/400V/600V	±(0.8%+1)
Resistance (Ω)	400Ω/4kΩ/40kΩ/400kΩ/4MΩ/40MΩ	±(1%+2)
Capacitance (F)	4nF/40nF/400nF/4μF/40μF/100μF	±(4%+3)
Frequency (Hz)	10Hz to 10MHz	±(0.5%+3)
Temperature (°C)	-40°C to 1,000°C	±(2.5%+3)

General Characteristic

Power	9V Battery (6F22)
LCD Size	35.6mm × 18mm
Product Colour	Orange and Grey
Product Net Weight	260g
Product Size	208mm × 76mm × 30mm
Standard Accessories	Battery, Test Lead, Carrying Bag, Point Contact Temperature Probe
Safety Rating	CAT II 600V
	CAT III 300V

Part Number Table

Description	Part Number
Multimeter, Digital, Clamp	72-9480

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

X-ON Electronics

Authorized Distributor

Click to view similar products for [Tenma manufacturer](#).

Other Similar products are found below :

[2110130UKEU](#) [2110140](#) [2110142](#) [2110144](#) [2110146](#) [2110148](#) [2110150](#) [2110152](#)
[2110154](#) [2110156](#) [2110158](#) [2110160](#) [2110162](#) [2110164](#) [2110168](#) [2110170](#) [211040](#)
[211041](#) [211042](#) [211045](#) [211046](#) [211047](#) [211050](#) [2110562](#) [2110563](#)