

Digital Multimeter



Description

The Digital multimeter model is a 2,000 count hand-held instrument with remarkable features, extra large LCD, steady operations, overload protection for all ranges and unique structure. The meter can measure AC/DC voltage, AC/DC current, resistance, capacitance, temperature, frequency, transistor, diode and continuity, and is equipped with data hold, full icon display and sleep mode functions.



Features

- Display Count : 2,000
- Manual Range
- Diode Test
- Transistor Test
- Auto Power Off
- Continuity Buzzer
- Data Hold
- Low Battery Indication
- Full Icon Display
- Input Impedance for DCV : Around 10MΩ
- Test Lead Connection Indications

Specifications

	Range	Best Accuracy
DC Voltage (V)	200mV/2V/20V/200V/1000V	±(0.5%+1)
AC Voltage (V)	2V/20V/200V/750V	±(0.8%+3)
DC Current (A)	2mA/200mA/20A	±(0.8%+1)
AC Current (A)	2mA/200mA/20A	±(1%+3)
Resistance (Ω)	200Ω/2kΩ/20kΩ/2MΩ/20MΩ	±(0.8%+1)
Capacitance (F)	2nF/200nF/100μF	±(4%+3)
Frequency (Hz)	2kHz/20kHz	±(1.5%+5)
Temperature (°C)	-40°C to 1,000°C	±(1%+3)

General Characteristic

Power	9V Battery (6F22)
LCD Size	60mm × 54mm
Product Colour	Orange and Grey
Product Net Weight	350g (Including holster)
Product Size	179mm × 88mm × 39mm
Standard Accessories	Battery, Test Lead, Holster, Multi-Purpose Socket, Point Contact Temperature Probe
Safety Rating	CAT II 1000V
	CAT III 600V

Part Number Table

Description	Part Number
General Digital Multimeter	72-9385

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.



X-ON Electronics

Authorized Distributor

Click to view similar products for [Tenma manufacturer](#).

Other Similar products are found below :

[2110130UKEU](#) [2110140](#) [2110142](#) [2110144](#) [2110146](#) [2110148](#) [2110150](#) [2110152](#)
[2110154](#) [2110156](#) [2110158](#) [2110160](#) [2110162](#) [2110164](#) [2110168](#) [2110170](#) [211040](#)
[211041](#) [211042](#) [211045](#) [211046](#) [211047](#) [211050](#) [2110562](#) [2110563](#)