


Digital Storage Oscilloscope



Features

- Dual analog channels width range 1mV/div ~ 20V/div
- 7 inches widescreen LCD display
- Special Print Screen Feature
- Supports plug-and-play USB storage device. Communication with and remote control of computer through the USB device
- USB drive system software upgrade
- Storage of waveforms setups and interfaces waveforms and setups reproduction
- Automatic measurement of 28 waveform parameters
- Unique waveform recording and replay function
- Multilingual menu displays

Specifications

Channels	: 2
Bandwidth	: 100MHz
Sample Rate	: 1GSPS
Rise Time	: $\leq 3.5\text{ns}$
Memory Depth	: 25kpts
Waveform Acquisition Rate	: $\geq 2,000\text{wfms/s}$
Vertical Sensitivity	: 1mV/div to 20V/div
Timebase Range	: 2ns/div to 50s/div
Storage	: Setup, Wave, Bitmap
Trigger Modes	: Edge, Pulse, Alternate
Interface	: USB OTG

General Characteristic

Power	: 100 - 240V AC, 45 - 440Hz
Display	: 7 Inches 64K Colour TFT LCD, 400 × 240
Product Colour	: White and Grey
Product Net Weight	: 2.2 kg
Product Size	: 306mm × 147mm × 122mm
Standard Accessories	: Probe×2 (1×, 10× switchable), Power Cord, USB Cable, PC Software CD
Safety Rating	: CAT II 300V

Part Number Table

Description	Part Number
Oscilloscope, 2CH, 50MHz, 1GSPS	72-8710

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.



Single Bench DC Power Supply **TENMA™**



Features:

- Complete digital control
- 10mV / 1mA resolution
- Low noise and ripple
- CV / CC constant voltage and constant current mode
- OCP and OVP settings, constant protection mode
- 5 sets of parameters can be stored and recalled
- Output switch control
- Power-off memory function
- Keyboard lock function

Specifications:

Voltage Range / Current Range	0 - 30V / 0 - 3A
Load Regulation	Voltage : $\leq 0.01\%$ +2mV / Current : $\leq 0.1\%$ +5mA
Line Regulation	Voltage : $\leq 0.01\%$ +3mV / Current : $\leq 0.1\%$ +3mA
Setup Resolution	Voltage : 10mV / Current : 1mA
Setup Accuracy (25°C $\pm 5^\circ\text{C}$)	Voltage : $\leq 0.5\%$ +20mV / Current : $\leq 0.5\%$ +5mA
Ripple (20Hz - 20MHz)	Voltage : $\leq 1\text{mV}_{\text{rms}}$ / Current : $\leq 3\text{mA}_{\text{rms}}$
Temp. Coefficient	Voltage : $\leq 100\text{ppm}$ +10mV / Current : $\leq 100\text{ppm}$ +5mA
Read Back Accuracy	Voltage : 10mV / Current : 1mA
Read Back Temp. Coefficient	Voltage : $\leq 100\text{ppm}$ +10mV / Current : $\leq 100\text{ppm}$ +5mA
Reaction Time (10% Rated load)	Voltage : $\leq 100\text{mS}$ / Current : $\leq 100\text{mS}$
Operation Environment	Indoor use Altitude : $\leq 2,000\text{m}$ Ambient temperature : 0 °C ~ 40°C Relative humidity : $\leq 80\%$
Weight and Dimension	3.5kg / 110mm(W) \times 156mm(H) \times 260mm(D)
Storage Environment	Ambient temperature : -10 °C to +70 °C Relative humidity : $\leq 70\%$
Accessories	User manual, UK Power cord (1.2m), Euro Power cord (1.2m)

Note: Input Voltage : 230V $\pm 10\%$

Part Number Table

Description	Part Number
DC Power Supply, Bench, Single, 3A, 30V	72-10480

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

X-ON Electronics

Authorized Distributor

Click to view similar products for [Tenma manufacturer](#).

Other Similar products are found below :

[2110130UKEU](#) [2110140](#) [2110142](#) [2110144](#) [2110146](#) [2110148](#) [2110150](#) [2110152](#)
[2110154](#) [2110156](#) [2110158](#) [2110160](#) [2110162](#) [2110164](#) [2110168](#) [2110170](#) [211040](#)
[211041](#) [211042](#) [211045](#) [211046](#) [211047](#) [211050](#) [2110562](#) [2110563](#)