



SUHNER® COAXIAL CONNECTOR DATA SHEET

TYPE 24_MCX-50-2-3/111_N

Description

Straight panel bulkhead cable jack, flange mount

Front mount chassis connector



General Information

MCX Interface dims acc. to:
Weight:

IEC 60169-36_CECC 22220
0.0017 Kg / 0.06 oz

Cable

Cable type:

EZ_86-TP/M17

Cable Entry

Centre contact:
Outer contact:

soldered
soldered

Electrical Data

Impedance:
Interface frequency max.:

50Ω
6 GHz

Piece Parts

Center contact:
Outer contact:
Body:

Material

Copper Beryllium Alloy
Brass
Brass

Surface Plating

Gold Plating (Nickel underplated)
Gold Plating (Nickel underplated)
Gold Plating (Nickel underplated)

Insulator:

PFA / PTFE

Fastening nut:
Washer:

Brass
Bronze

Gold Plating (Nickel underplated)
Gold Plating (Nickel underplated)

Attachments

Outline drawing:
Catalogue drawing:
Assembly instruction:

DOU-00009837
DCA-00009839
DOC-0000180183

Notes

Mounting hole:
Order as **24_MCX-50-2-3/111_NE**

DOU-00008855
for Single

WAIVER!

While the information contained in this folder has been carefully compiled to the best of our present knowledge, it is not intended as representation or warranty of any kind on our part regarding the fitness of the products concerned for any particular use or purpose and neither shall any statement contained herein be construed as a recommendation to infringe any industrial property rights or as a license to use any such rights. The fitness of each product for any particular purpose must be checked beforehand with our specialists.



HUBER+SUHNER

HUBER+SUHNER AG
Interconnect Division
CH-9100 Herisau
Phone +41 (0)71 353 41 11
Fax +41 (0)71 353 45 90
<http://www.hubersuhner.com>

Issued: 17.12.03 15:59

Document: DOC-0000186801

RF_Ca_Pa_C_PDF

uncontrolled copy

Page 1

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [huber & suhner](#) manufacturer:

Other Similar products are found below :

[31 MMBX-SMA-50-1/111_NE](#) [74Z-0-23-17](#) [32 MMBX-50-0-6 / 111_NE](#) [TL8A-11SMA-11SMA-03000-51](#) [TL8A-11SMA-11SMA-01500-51](#)
[23_SMA-50-0-1/111_NE](#) [TL-8A-11N-11SMA-01500-51](#) [7404.17.0003](#) [24_BNT-50-2-1/103_NE](#) [5906.17.0005](#) [53_SMA-50-0-2/111_NE](#)
[Microbend R-13](#) [5910_SMA-50-005/19-_NE](#) [16_SMA-50-2-55/199_NE](#) [16_SMA-50-2-43/133_NE](#) [11_716-50-7-31/033_-Y](#) [Minibend L-13](#)
[74_Z-0-0-58](#) [6550.17.AA](#) [Microbend R-4.5](#) [74_Z-0-0-53](#) [6603_SMA-50-2/199_NE](#) [85_SMC-50-0-1/133_NE](#) [MF53/1x8A_21MXP/11SK/305](#)
[1324.17.0114](#) [75_Z-0-0-51](#) [31_PC24-SK-50-1/199_NE](#) [65_BNC-50-0-2/133_NE](#) [76_Z-0-10-14](#) [65_MMCX-50-0-31/111_OE](#) [11_N-50-4-](#)
[19/12-_NE](#) [80346275](#) [23_SHV-50-0-2/133_NE](#) [33_SMA-QMA-50-1/133_NE](#) [11_C-50-7-6/133_NE](#) [6806.19.A](#) [33_716-N-50-51/-33_NE](#)
[5930_N-50-050/19-_NE](#) [16_BNC-50-7-6/133_NE](#) [11_SMB-50-2-41/111_NE](#) [Mini141 K-8](#) [74_Z-0-0-30](#) [33_BNC-N-50-1/133_NE](#) [6701.01.B](#)
[33_BNC-QLA-01-1/1--_NE](#) [25_N-50-7-8/133_NE](#) [22_BNC-50-0-5/133_NE](#) [6500_N-50-1/199_NE](#) [3401.17.0033](#) [6601_SMA-50-1/199_NE](#)